
PCB terminal block; 1.5 mm²; Pin spacing 3.5 mm; 3-pole; PUSH WIRE®; 1,50

mm<sup>2</sup>; white

www.wago.com/744-303







## Item description

- PCB terminal blocks with PUSH WIRE® connection
- Push-in termination of solid conductors low insertion forces
- Just 6.6 mm tall
- Conductor removal via disconnection tool or by twist & pull

# Data Electrical data

## Ratings per IEC/EN

| Ratings per                   | IEC/EN 60664-1 |
|-------------------------------|----------------|
| Nominal voltage (III/3)       | 250 V          |
| Rated impulse voltage (III/3) | 4 kV           |
| Rated voltage (III/2)         | 320 V          |

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$ 

WAGO GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/744-303



| Rated impulse voltage (III/2) | 4 kV  |
|-------------------------------|---|
| Nominal voltage (II/2)        | 630 V   |
| Rated surge voltage (II/2)    | 4 kV  |
| Rated current                 | 3 A   |
| Legend (ratings)              | (III / 2) ≙ Overvoltage category III / Pollution degree 2 |

## Ratings per UL 1059

| Approvals per                  | UL 1059 |
|--------------------------------|---------|
| Rated voltage UL (Use Group B) | 300 V   |
| Rated current UL (Use Group B) | 6 A     |
| Rated voltage UL (Use Group D) | 300 V   |
| Rated current UL (Use Group D) | 6 A     |

## Connection data

| Connection points          | 3 |
|----------------------------|---|
| Total number of potentials | 3 |
| Number of connection types | 1 |
| Number of levels           | 1 |

## Connection 1

| Connection technology                 | PUSH WIRE <sup>®</sup>    |
|---------------------------------------|---------------------------|
| Actuation type                        | Operating tool            |
| Solid conductor                       | 0.5 1.5 mm² / 20 16 AWG   |
| Strip length                          | 8 9 mm / 0.31 0.35 inches |
| Conductor connection direction to PCB | 0 °                       |
| Pole number                           | 3                         |

## Physical data

| Pin spacing                          | 3.5 mm / 0.138 inches    |
|--------------------------------------|--------------------------|
| Width                                | 11.4 mm / 0.449 inches   |
| Height                               | 10.1 mm / 0.398 inches   |
| Height from the surface              | 6.6 mm / 0.26 inches     |
| Depth                                | 12.5 mm / 0.492 inches   |
| Solder pin length                    | 3.5 mm                   |
| Solder pin dimensions                | 0.35 x 0.9 mm            |
| Drilled hole diameter with tolerance | 1.1 <sup>(-0.1)</sup> mm |

 $\label{thm:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$ 

WAGO GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/744-303



#### **PCB** contact

| PCB contact                         | ТНТ  |
|-------------------------------------|--|
| Solder pin arrangement              | over the entire terminal strip (staggered) |
| Number of solder pins per potential | 1  |

#### **Material Data**

Note (material data)

Information on material specifications can be found here

| Color                       | white            |
|-----------------------------|------------------|
| Material group              | I                |
| Insulation material         | Polyamide (PA66) |
| Flammability class per UL94 | VO               |
| Clamping spring material    | Copper alloy     |
| Contact plating             | Tin              |
| Fire load                   | 0.016 MJ         |
| Weight                      | 0.9 g            |

## **Environmental requirements**

| Limit temperature range | -60 +105 °C |  |
|-------------------------|-------------|--|
|-------------------------|-------------|--|

#### Commercial data

| eCl@ss 10.0           | 27-44-04-01   |
|-----------------------|---------------|
| eCl@ss 9.0            | 27-44-04-01   |
| ETIM 8.0              | EC002643      |
| ETIM 7.0              | EC002643      |
| PU (SPU)              | 1000 pcs      |
| Packaging type        | box           |
| Country of origin     | СН            |
| GTIN                  | 4055143300520 |
| Customs tariff number | 85369010000   |

## **Environmental Product Compliance**

## Approvals / Certificates

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$ 

WAGO GmbH & Co. KG Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/744-303



## General approvals

| Logo        | Approval                                    | Additional Approval Text | Certificate<br>name |
|-------------|---|--------------------------|---------------------|
|             | AOC DEKRA Certification B.V.                | EN 60998                 | 2261942.01-<br>AOC  |
| <b>71</b> ° | <b>UL</b><br>Underwriters Laboratories Inc. | UL 1059                  | E45172              |

#### **Optional accessories**

| _ |    | ı |
|---|----|---|
| - | υυ | ı |

| Operat | ting tool   |                      |
|--------|---|----------------------|
| /      | Item no.: 206-841 Disconnection tool; for 744 Series; multicoloured | www.wago.com/206-841 |

#### **Downloads**

#### Documentation

#### **Additional Information**

| Technical Section      | 2019 Apr 3 | pdf    | Download |
|------------------------|------------|--------|----------|
| Technical explanations |            | 2.0 MB |          |

## CAD/CAE-Data

## CAD data

| 2D/3D Models 744-303 | URL | Download |
|----------------------|-----|----------|
|                      |     |          |

#### **PCB** Design

Symbol and Footprint 744-303 URL Download CAx data for your PCB design, consisting of "schematic symbols and PCB footprints",

# Supported formats:

- Accel EDA 14 & 15
- Altium 6 to current version
- Cadence Allegro

 $\label{thm:constraint} \textbf{Subject to changes. Please also observe the further product documentation!}$ 

allow easy integration of the WAGO component into your development environment.

WAGO GmbH & Co. KG Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

05.06.2023 Page 4/6

www.wago.com/744-303



- DesignSpark
- Eagle Libraries
- KiCad
- Mentor Graphics BoardStation
- Mentor Graphics Design Architect
- Mentor Graphics Design Expedition 99 and 2000
- OrCAD 9.X PCB and Capture
- PADS PowerPCB 3, 3.5, 4.X, and 5.X
- PADS PowerPCB and PowerLogic 3.0
- PCAD 2000, 2001, 2002, 2004, and 2006
- Pulsonix 8.5 or newer
- STL
- 3D STEP
- TARGET 3001!
- View Logic ViewDraw
- Quadcept
- Zuken CadStar 3 and 4
- Zuken CR-5000 and CR-8000

PCB Component Libraries (EDA), PCB CAD Library Ultra Librarian

#### **CAE** data

ZUKEN Portal 744-303 URL Download

## **Environmental Product Compliance**

Compliance Search

Environmental Product Compliance 744-303

PCB terminal block; 1.5 mm<sup>2</sup>; Pin spacing 3.5 mm; 3-pole; PUSH WIRE®; 1,50 mm<sup>2</sup>;

URL

Download

white

#### **Installation Notes**

Conductor termination

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/744-303





Inserting a conductor via push-in termination.

#### Conductor removal



Removing a conductor via 1.0 mm  $\emptyset$  disconnection tool (206-841).

 $\label{lem:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$