# STANDARD SOLID-STATE RELAY SERIES

For 12 to 24V DC Systems



Expertise Applied | Answers Delivered



### Description

Solid state circuitry means no moving parts to wear out. Fully encapsulated construction gives extended protection against adverse environments.

### **Features and Benefits**

- Fully electronic switching mechanism: no electrical arcs
- Resistant to vibration and mechanical shock
- Withstands contamination from moisture, dust, salt spray
- Needs only a very low control current
- Suitable for high inrush demand circuits (see graph)
- · Ideal for a variety of system voltage applications
- Extended service life: tested to 1,000,000 on/off cycles
- Very low control current of .02 Amps (max)
- On/off control voltage must be identical to the system voltage
- Protected from transient voltage spikes or surges
- Studs permit high current connection

## Wiring Diagram



### **Inrush Current Capability**

**Specifications Overview** 

9 to 31V DC

.005 Ohms -40° to +85° C

5/16" x 18

16 AWG stranded on/off

Width: 3.0" Length: 5.0" Height: 2.9"

DESCRIPTION

Electronic Solid State Relay Switch

85A

Voltage Range:

**Resistance (on):** 

Operating Temp: Control Wires:

**Input Studs:** 

Size:

**Max Continuous Current:** 

Web Resources

littelfuse.com/48785

PART NUMBER

48785

Download technical resources at:

**Ordering Information** 





Visit Littelfuse.com for the most up-to-date product information. Littelfuse products are designed for specific applications and should not be used for any purpose (including, without limitation, automotive applications) not expressly set forth in applicable Littelfuse product documentation. Warranties granted by Littelfuse shall be deemed void for products used for any purpose not expressly set forth in applicable Littelfuse product documentation are applicable applications) not expressly set forth in applicable Littelfuse shall be deemed void for products used for any purpose not expressly set forth in applicable Littelfuse product documentation. Littelfuse for any claims or damages arising out of products used in applications not expressly intended by Littelfuse as set forth in applicable Littelfuse product documentation.

#### Datasheet Replaces Hotfeed Number D-579