## Aranet Soil sensor (Teros-12)

Measures volumetric water content, electroconductivity and temperature of soil

TDSPHE02 (EU)
TDSPHEU2 (US,AS)

Sensor performance				
	Volumetric Water Content (VWC)	Apparent dielectric permittivity	Bulk Electrical Conductivity (EC)	Temperature <sup>1</sup>
Range	0-100 %2	1-80	0 – 20 dS/m	-40 °C to 60 °C (-40 °F to 140 °F)
Resolution	0.1 %	0.01	0.001 dS/m	0.1 °C (0.1 °F)
Accuracy <sup>3</sup>	± 3 % <sup>4</sup>	1–40 : ±1 40–80 : 15%	±8 % of reading	±0.5 °C (±1.0 °F)

Radio parameters	
Line of sight range	3 km (1.9 mi)
Supported ISM bands	EU868, RU869 US920, AS923
Transmitter power	14 dBm
Data transmission interval	1, 2, 5 or 10 minutes
Data protection	XXTEA encryption
Compatible base stations	Aranet PRO

General	
Ingress protection rating	IP68
Operating temperature range	-40 °C to 60 °C (-40 °F to 140 °F)
Weight⁵	320 g (11.3 oz)
Included in the box	AA alkaline battery

Pov	ver	AA battery	
Тур	е	Alkaline <sup>6</sup>	Lithium <sup>7</sup>
TX interval		Battery lifetime at 20 °C (68 °F) <sup>8</sup>	
1	minute	0.9 years	1.2 years
2	minutes	1.7 years	2.3 years
5	minutes	3.9 years	5.3 years
10	minutes	6.6 years	9.5 years

Compliance		
CE	Conformité Européenne	
IC	Innovation, Science and Economic Development Canada	
FCC	Federal Communications Commission (USA)	

<sup>&</sup>lt;sup>1</sup> Temperature measurement may not be accurate if sensor is not fully immersed in the medium of interest, due to longer equilibration time.

<sup>&</sup>lt;sup>2</sup> The VWC range is dependent on the media the sensor is calibrated to. A custom calibration will accommodate the necessary ranges for most substrates.

<sup>&</sup>lt;sup>3</sup> 95 % of the sensors measure within these typical limits in equilibrium state at the time of sale.

<sup>&</sup>lt;sup>4</sup> A typical value in mineral soils that have solution EC <8 dS/m. The VWC accuracy is dependent on the media the sensor is calibrated to. A custom calibration can improve the accuracy up to 1 % of VWC.

<sup>&</sup>lt;sup>5</sup> Weight with alkaline Fujitsu Premium LR6G07 AA batteries.

<sup>&</sup>lt;sup>6</sup> Fujitsu Premium LR6G07 AA batteries used for tests and calculations.

<sup>&</sup>lt;sup>7</sup> Energizer Ultimate Lithium L91 AA batteries used for tests and calculations.

<sup>&</sup>lt;sup>8</sup> Battery lifetime data has been obtained by mathematical extrapolation and is provided for descriptive purposes only and is not intended to make or imply any guarantee or warranty.