Axial Lead & Cartridge Fuses

2AG > Fast-Acting > 2206 Series



2206 Series, Lead-Free 2AG, Fast-Acting Fuse





Agency Approvals

| Agency | Agency File Number | Ampere Range | |
|-------------|--------------------|--------------|--|
| 91 . | E10480 | 0.75A - 3A | |
| () A | 29862 | 0.75A - 3A | |
| Œ | N/A | 0.75A - 3A | |

Additional Information







Electrical Characteristic Specifications by Item

Description

The 2AG Fast-Acting Axial Leaded Fuses provide the same performance characteristics as their 3AG counterpart while occupying one-third the space.

Features

- In accordance with Underwriter's Laboratories Standard UL 248-14
- Fuses are boardwashable in most solvents with thermoplastic sleeve
- Available in axial lead form and with various lead forming dimensions
- RoHS compliant and lead–free

Applications

Used as supplimentary protection in appliance or utilization equipment to provide individual protection for components or internal circuits.

Electrical Characteristics for Series

| % of Ampere Rating | OpeningTime |
|-----------------------|-------------------|
| 100% | 4 hours, Minimum |
| 135% | 1 hour, Maximum |
| 200% | 1 second, Maximum |

| Ampere Rating | Amp | Max Voltage | Interrupting | Nominal Cold | Nominal Melting | Nom Voltage | Nom Power Dissipation (W) | Agency Approvals | |
|------------------|------|----------------|--------------|----------------------|---------------------------------------|----------------|------------------------------------|------------------|-----------|
| (A) | Code | Rating (V) | Rating | Resistance (Ohms) | I ² t (A ² sec) | Drop (mV) | | 77 | () |
| .750 | 0.75 | 300 | | 0.1520 | 1.05 | N/A | N/A | Х | Х |
| 1 | 001 | 300 | 100A@300Vac | 0.1027 | 2.22 | N/A | N/A | Х | X |
| 2 | 002 | 300 | 10KA@125Vac | 0.0497 | 1.50 | N/A | N/A | Х | х |
| 3 | 003 | 300 | | 0.0317 | 4.62 | N/A | N/A | Х | X |



Temperature Rerating Curve



Note:

1. Rerating depicted in this curve is in addition to the standard derating of 25% for continuous operation.

Average Time Current Curves



Soldering Parameters - Wave Soldering



Recommended Process Parameters:

| Wave Parameter | Lead-Free Recommendation | | |
|--|-----------------------------------|--|--|
| Preheat: (Depends on Flux Activation Temperature) | (Typical Industry Recommendation) | | |
| Temperature Minimum: | 100° C | | |
| Temperature Maximum: | 150° C | | |
| Preheat Time: | 60-180 seconds | | |
| Solder Pot Temperature: | 260° C Max | | |
| Solder Dwell Time: | 2-5 seconds | | |

Recommended Hand-Solder Parameters:

Solder Iron Temperature: 350° C +/- 5°C Heating Time: 5 seconds max.

Note: These devices are not recommended for IR or Convection Reflow process.

Axial Lead & Cartridge Fuses

2AG > Fast-Acting > 2206 Series



Product Characteristics

| Materials | Body: Glass Cap : Nickel-plated brass Leads: Tin-plated Copper | | |
|-------------------|--|--|--|
| Terminal Strength | MIL-STD-202, Method 211, Test Condition A | | |
| Solderability | MIL-STD-202 Method 208 | | |
| Product Marking | Cap1 : Brand logo, current and voltage ratings Cap2 : Series and agency approval marks | | |

| Operating Temperature | -55°C to +125°C |
|--------------------------|---|
| Thermal Shock | MIL-STD-202, Method 107, Test Condition B (5 Cycles -65° C to $+125^{\circ}$ C). |
| Vibration | MIL-STD-202, Method 201 |
| Humidity | MIL-STD-202, Method 103, Test Condition A: High RH (95%) and Elevated Temp (40°C) for 240 hours |
| Salt Spray | MIL-STD-202, Method 101, Test Condition B |

Part Numbering System





Packaging

Dimensions

| Packaging Option | Packaging Specification | Quantity | Quantity & Packaging Code | Reel Size |
|------------------|-------------------------|----------|---------------------------|-----------|
| Bulk | N/A | 100 | HX | N/A |
| Bulk | N/A | 1000 | MX | N/A |

Disclaimer Notice - Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littlefuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at: www.littlefuse.com/disclaimer-electronics.