DC to DC Converter



Innovative **Technology** for a **Connected** World



The DC to DC converter takes a "10-32" DC voltage and converts it 5 or 12 DC voltages. This device can be used for devices that use 5 VDC only, 12 VDC only or both 5 and 12 VDC.

FEATURES **FEATURES**

- Fuse protected input
- Short circuit protection
- Non-isolation circuit
- Efficiency: minimum 80%

MARKETS

- Remote routers, access points, and bridges
- Remote networking equipment
- SOHO equipment
- IP camera and phone systems
- VOIP systems

MODEL	DCDC-1032-5	DCDC-1632-12	DCDC-1532-5/12	
Input	10V~32VDC	16V~32VDC	15V~32VDC	
Output	+5V	+12V	+5V	+12V
Max. load	ЗA	1.25A	ЗA	1.25A
Power	15W Max	15W Max	15W Max	
Min. Load	0A	0A	0A	
Load reg. %	5%	5%	5%	
Line reg. %	1%	1%	1%	
Ripple %	2%	2%	2%	
Noise %	5%	5%	5%	
Operating temperature	-15°C to +40°C		-15°C to +60°C	
Storage temperature	-25°C to +85°C	-25°C to +85°C	-25°C to +85°C	
Operating humidity	5% to 90%	5% to 90%	5% to 90%	
Cooling	Free air cooling	Free air cooling	Free air cooling	
Dimensions L x D x H	46 x 33 x 24 mm		80 x 60 x 30 mm	

global solutions: local support ...

Americas: +1.847 839.6907 IAS-AmericasEastSales@lairdtech.com

Europe: +1.32.80.7866.12 IAS-EUSales@lairdtech.com

Asia: +1.65.6.243.8022 IAS-AsiaSales@lairdtech.com

www.lairdtech.com



Innovative **Technology** for a **Connected** World

DC to DC Converter

MECHANICAL DRAWINGS

DCDC-1532-5/12





DCDC-1032-5





A





ANT-DS-DC-DC 0709

Any information furnished by Laird Technologies, Inc. and its agents is believed to be accurate and reliable. All specifications are subject to change without notice. Responsibility for the use and application of Laird Technologies materials rests with the end user, since Laird Technologies and its agents cannot be aware of all potential uses. Laird Technologies materials rests with the end user, since Laird Technologies and its agents cannot be aware of all potential uses. Laird Technologies materials roots on sequential dates application of Laird Technologies products are subject to change without notice. Responsibility for the use and technologies products are subject to subject to subject to subject to a su