

MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Description

AH1884 is with two Hall effect plates and dual CMOS output driver, mainly designed for battery–operation, hand-held equipment (such as Cellular and Cordless Phone, PDA). The total operation power is down to 15uW in the 1.8V supply.

Either north or south pole of sufficient strength will turn the output on. The output will be turned off under no magnetic field.

While the magnetic flux density **(B)** is larger than operate point **(Bop)**, the output will be turned on (low), the output is held until **B** is lower than release point **(Brp)**, then turned off.

Features

- Micropower operation
- Operation with North or South Pole
- 1.65V to 3.3V battery operation
- Chopper stabilized
 - Superior temperature stability
 - Extremely Low Switch-Point Drift
- Insensitive to Physical Stress
- Good RF noise immunity
- -40°C to 85°C operating temperature
- ESD > 4KV in human body mode
- Package: SOT553
- "Green" Molding Compound

Typical Application Circuit



Pin Assignments



Applications

- Cellular phone
- PDA
- Cordless phone



MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Pin Descriptions

Pin Name	P/I/O	Pin #	Description
Out 2	0	1	Output Pin (active High)
GND	P/I	2	Ground
NC		3	No Connection
Vdd	P/I	4	Power Supply Voltage
Out 1	0	5	Output Pin (active Low)

Functional Block Diagram



Absolute Maximum Ratings (T_A = 25°C)

Symbol	Characteristics	Values	Unit
Vdd	Supply voltage	5	V
В	Magnetic flux density	Unlimited	
Ts	Storage Temperature Range	-65 to +150	°C
PD	Package Power Dissipation	230	mW
TJ	Maximum Junction Temperature	150	°C

Recommended Operating Conditions (T_A = 25°C)

Symbol	Parameter	Conditions	Rating	Unit
Vdd	Supply Voltage	Operating	1.65 to 3.3	V
T _A	Operating Temperature Range	Operating	-40 to +85	°C



MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Electrical Characteristics (T_A = 25°C, Vdd = 1.8V, unless otherwise specified)

Symbol	Characteristic	Conditions	Min	Тур.	Max	Unit
V _{OH}	Output On Voltage (High side)	I _O = -0.5mA	Vdd-0.2	-	-	V
V _{OL}	Output On Voltage (Low side)	I _O = 0.5mA	-	-	0.2	V
ldd(en)		Chip enable	-	2	4	mA
Idd(dis)	Supply Current	Chip disable	-	5	8	uA
ldd(avg)		average supply current	-	7	12	uA
Tawake	Awake Time		-	50	100	μs
Tperiod	Period		-	50	100	ms
D.C.	Duty Cycle		-	0.1	-	%

Magnetic Characteristics (T_A = 25°C, Vdd = 1.8V~3.0V, Note 1 & 2)

				(1mT	=10 Gauss)
Symbol	Characteristic	Min	Тур.	Мах	Unit
Bops(south pole to brand side)	Operate Daint	-	37	55	
Bopn(north pole to brand side)	Operate Point	-55	-37	-	
Brps(south pole to brand side)	Release Point	15	29	-	Gauss
Brpn(north pole to brand side)	Release Folli	-	-29	-15	
Bhy(Bopx - Brpx)	Hysteresis	3	8	-	

Notes: 1. Typical data is at Ta = 25°C, Vdd = 3V, and for design information only.

2. The magnetic characteristics may vary with supply voltage, operating temperature and after soldering.





MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Typical Operating Characteristics



Supply Current





MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Performance Characteristics

T _A (°C)	25	50	60	70	80	85	90	100	110	120	130	140	150
P _D (mW)	230	184	166	147	129	120	110	92	74	55	37	18	0



Ordering Information



🙉 AH18	🙉 AH1884-ZG-7		SOT553	3000/Tape & Reel	-7		
Notes: 3. EU Directive 2002/95/EC (RoHS). All applicable RoHS exemptions applied. Please visit our website at							

otes: 3. EU Directive 2002/95/EC (RoHS). All applicable RoHS exemptions applied. Please visit our website at http://www.diodes.com/products/lead_free.html.

4. Pad layout as shown on Diodes Inc. suggested pad layout document AP02001, which can be found on our website at http://www.diodes.com/datasheets/ap02001.pdf.



MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

Marking Information

(1) SOT553



Package Outline Dimensions (All Dimensions in mm)

(1) Package Type: SOT553





MICROPOWER, ULTRA-SENSITIVE HALL EFFECT SWITCH

IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel.

Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

A. Life support devices or systems are devices or systems which:

1. are intended to implant into the body, or

- 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products or systems.

Copyright © 2010, Diodes Incorporated

www.diodes.com