# C Series

Switch with IEC Connector Compact Size



### UL Recognized CSA Certified VDE Approved

### **C** Series

Two function power entry module combining a DPST switch and an IEC 320 power line connector. Compact packaging allows a smaller panel cutout with choice of snap-in or flange mounting. Available with general purpose filtering (F models - CFS, CFE), medical application filtering (H models - CHS, CHE) or unfiltered (CS, CE). Terminals allow for easy connection to any wiring scheme. Preconnected terminals from line to switch are available (B Models - CBS, CBE) for reducing OEM wiring time.

The medical versions (H models) are designed specifically for health care applications. Their extremely low leakage current allows compliance with UL544 and UL2601 as well as CSA22.2 health care specifications for use with both patient and non-patient care equipment.

The C series also has the adaptability to fit into existing panel cutouts using snap-on extender options. Using the CA430 extender, the panel cutout height is increased by 0.13". (Extender is available pre-assembled using part numbers with 'K' designation)

## **Electrical Schematic**

### F Models (CFS, CFE)



#### H Models (CHS, CHE)



### **B Models (CBS, CBE)**



Resistor location for reference only.

Note 1: Jumpers provided on CBS and CBE versions. Note 2: Location of optional filter.





### **Specifications**

Hipot rating (one minut	e):	
line-to-ground		2250 VDC
line-to-line		1450 VDC
Operating frequency:		50/60 Hz
Rated voltage:		120/250 VAC
Rated current:		10A@120 VAC
		10A @ 250 VAC
Operating voltages:		115/230 VAC
Switch:		Double-insulated rated
		for 10,000 operations
		at full load. 51 Amp
		inrush capability.
Terminals:	Unfiltered	.187" x .032" terminals
	Filtered	.25" x .032" terminals

### Filtered Models Only:

Maximum leakage current, each line-to-ground

•	•	
@	120 VAC 60 Hz:	.25mA
@	250 VAC 50 Hz:	.40mA
@	120 VAC 60 Hz:	2µA
@	250 VAC 50 Hz:	5μΑ
	@	@ 120 VAC 60 Hz: @ 250 VAC 50 Hz: @ 120 VAC 60 Hz: @ 250 VAC 50 Hz:

### Minimum insertion loss in dB:

Line-to-ground in 50 ohm circuit							
Current	Frequency MHz						
Rating	0.05	0.15	0.5	1	5	10	30
H Models							
1A	16	21	37	44	26	21	10
3A	9	14	31	32	26	24	14
6A	4	10	22	23	19	18	13
10A	2	6	10	15	11	11	9
F Models							
1A	10	26	46	48	46	47	46
3A	8	16	32	36	43	48	50
6A	4	11	22	27	36	41	50
10A	1	4	14	18	27	33	42

Line-to-line	in 50 o	hm circ	cuit				
Current			Freque	ency N	1Hz		
Rating	0.05	0.15	0.5	1	5	10	30
H Models							
1A	1	6	13	29	38	42	26
3A	1	5	10	22	36	34	36
6A	1	5	14	20	31	33	37
10A	1	4	11	19	32	37	38
F Models							
1A	1	3	13	28	62	67	42
3A	2	6	14	23	65	65	67
6A	2	6	14	27	46	48	58
10A	1	7	14	23	42	44	62



# Series C

# **Case Styles**

Metric shown in italics.

### CS, CBS<sup>†</sup>





### CFS, CHS





Mounting holes:  $\frac{.13}{3.3}$  Dia. (2) with .23 Dia. x 90° Counter sunk

CE, CBE<sup>†</sup>





### CFE, CHE





### <sup>†</sup>CBS, CBE Pre-wired Terminals (Side View)



# **Case Dimensions**

Metric shown in italics.

Part No.	A (max)	B (max)	C (max)	D ±.006 ±.152	E <u>±.006</u> <u>±.152</u>	F ±.006 ±.152
CS, CBS	<u> </u>	<u>.97</u> 24.64	<u>1.62</u> 41.17	<u>1.06</u> 26.92	<u> </u>	
CE, CBE	<u>1.74</u> 44.2	<u>.97</u> 24.64	<u>1.62</u> 41.17	<u>1.06</u> 26.92	<u>1.540*</u> <i>39.12*</i>	<u>1.417</u> <i>36.0</i>
CFS, CHS	<u>1.23</u> 31.24	2.53 64.26	<u>1.62</u> 41.17	<u>1.12</u> 28.5	<u>1.540*</u> <i>39.12*</i>	
CFE, CHE	<u>1.74</u> 44.2	<u>2.53</u> 64.26	<u>1.62</u> 41.17	<u>1.12</u> 28.5	<u>1.540*</u> <i>39.12*</i>	<u>1.417</u> 36.0

\* with K extender (CA430) add to height  $\frac{.13}{3.3}$ 

### **Panel Cutout**



Panel Cutout for thickness of .031-.098 (.8-2.5). Not recommended for plastic panels.

For snap-in applications, the D sides of the cutout must have a .02(.508) radius on the installation side.

Snap-in models allow front mounting only.

Ordering Information Consult your local Corcom sales representative for pricing.



### Available Part Numbers

Available Falt Nullibers						
10CE1 10CKE1 1CFE1 1CKFE1 3CFE1 3CKFE1 6CFE1 6CKFE1 10CFE1 10CKFE1 10CKFE1	1CHS1 1CKHS1 3CHS1 3CKHS1 6CHS1 6CKHS1 10CHS1 10CKHS1	1CHE1 1CKHE1 3CHE1 3CKHE1 6CHE1 6CKHE1 10CHE1 10CKHE1				
10CKBS1 10CKBE1 CORCOM World Headquarters 844 E. Rockland Road Libertyville, IL 60048 847.680.7400 www.cor.com						
	10CE1 10CKE1 1CFE1 1CKFE1 3CFE1 3CKFE1 6CFE1 6CKFE1 10CFE1 10CKE1 10CKE1 10CKBE1 10CKBE1 0CKBE1 0CKBE1 10CKBE1	10CE1 1CHS1   10CKE1 1CKHS1   1CFE1 3CHS1   1CKFE1 3CKHS1   3CFE1 6CHS1   3CKFE1 6CKHS1   6CFE1 10CKHS1   10CFE1 10CKHS1   10CFE1 10CKHS1   10CKE1 10CKHS1   10CKE1 10CKHS1   10CKBE1 10CKBE1				