

Tel: 1-800-722-8197 1-631-595-2217 Fax: 1-631-667-5484 EMAIL: sales@challelec.com WEB: www.challengeelectronics.com ISO 9001/14001:2015 Certified

INDICATORS • SPEAKERS • SOUND TRANSDUCERS • ENCLOSURES • MICROPHONES • BATTERY ACCESSORIES

CI44S-15W45-M-1

Rev. 0-2022 RoHS3 & REACH IEC 60601-1-8 Medical Alarm Compliant* Speaker Indicators



Operating Characteristics



Physical Characteristics



General tolerance = ±0.5 mm and all measurements in mm unless otherwise noted.

Revision	Description	Ву	Date
0-2022	Original Specification	AL	2022-09-07

Warranty: For a period of one (1) year from date of shipping under normal operations conditions. This warranty does not apply to products damaged through misuse, abuse, improper installation, alteration, rework, or attempt to repair.

The information contained herein is believed to be correct, but no guarantee or warranty, express or implied, with respect to accuracy, completeness or results is extended and no liability is assumed. Challenge Electronics reserves the right to make changes in any specification, data or material contained herein. *IEC 60601-1-8 compliance is assured by design and not production tested.

©2022 Challenge Electronics, Inc. Pub. 20220922160418



Tel: 1-800-722-8197 1-631-595-2217 Fax: 1-631-667-5484

EMAIL: sales@challelec.com WEB: www.challengeelectronics.com ISO 9001/14001:2015 Certified

INDICATORS • SPEAKERS • SOUND TRANSDUCERS • ENCLOSURES • MICROPHONES • BATTERY ACCESSORIES

CI44S-15W45-M-1

Rev. 0-2022 RoHS3 & REACH IEC 60601-1-8 Medical Alarm Compliant* Speaker Indicators



Control Chart

Wire	Low Priority	Medium Priority	High Priority
Black	Negative	Negative	Negative
Red	Positive	Positive	Positive
Blue		High Voltage	
White			High Voltage

High Voltage = 8 - 15 VDC

Timing Chart

Characteristic	High Priority Alarm Signal	Medium Priority Alarm Signal	Low Priority Alarm Signa	
Number of Pulses in Burst	10	3	2	
Pulse spacing (ts)				
between 1st and 2nd pulse	0.1	0.2	0.18	
between 2nd and 3rd pulse	0.1	0.2	Not Applicable	
between 3rd and 4th pulse	0.35	Not Applicable	Not Applicable	
between 4th and 5th pulse	0.1	Not Applicable	Not Applicable	
between 5th and 6th pulse	1.05	Not Applicable	Not Applicable	
between 6th and 7th pulse	0.1	Not Applicable	Not Applicable	
between 7th and 8th pulse	0.1	Not Applicable	Not Applicable	
between 8th and 9th pulse	0.35	Not Applicable	Not Applicable	
between 9th and 10th pulse	0.1	Not Applicable	Not Applicable	
Interburst Interval (tb)	10	16	16	
Effective Pulse Duration (td)		0.15		
Rise Time (tr)		0.025		
Fall Time (tf)	0.025			





Revision	Description	Ву	Date
0-2022	Original Specification	AL	2022-09-07

Warranty: For a period of one (1) year from date of shipping under normal operations conditions. This warranty does not apply to products damaged through misuse, abuse, improper installation, alteration, rework, or attempt to repair.

The information contained herein is believed to be correct, but no guarantee or warranty, express or implied, with respect to accuracy, completeness or results is extended and no liability is assumed. Challenge Electronics reserves the right to make changes in any specification, data or material contained herein. *IEC 60601-1-8 compliance and accompanying Timing Chart is assured by design and not production tested. ©2022 Challenge Electronics, Inc. Pub. 20220922160526