### Metal Line Switches https://www.schurter.com /PG70

# CDS1

### **Touch Display Switch**



CDS1 unpowered



Example: partial mode pictures



Backside with terminals

### \_\_\_\_\_

### Description

- Capacitive touch technology in combination with an OLED Display
- Four softkeys and one touch button
- Functions: rotating, swiping horizontally or vertically, and tapping
- Upload of own pictures in png format and animated gif videos via USB Interface
- No operation system software necessary for the operation of the CDS1, only the machine simulator runs on MS Windows 7 and higher
- Selection from three interfaces: I2C, SPI, RS232

### **Unique Selling Proposition**

- Configurable Input System
- Full Size Touchscreen
- Round shaped OLED Display
- Plug and Play

### See below: Approvals and Compliances

### Weblinks

pdf data sheet, html datasheet, General Product Information, CAD-Drawings, Product News, Detailed request for product, Landing Page, Video

## CDS1

### **Technical Data**

Teermiear Bata						
Electrical Data						
Supply Voltage Vcc	3.3 VDC ± 5%					
Logic Input Low	min. 70% Vcc					
Logic Input High	max. 30% Vcc					
Reverse Polarity Protection <sup>1)</sup>	yes					
Connector to internal Mass	Micro USB-B 2.0					
Storage						
Connector to Customer Sys- tem Control Unit	JST XHP 10, protected against torsion					
Interface to Customer System Control Unit	I2C (100 kHz or 400 kHz), 4-line SPI or RS232					
Current Consumption (Vcc = 3						
All features off, sleep mode	20 mA					
Only Touch active	20 mA					
Only LED active (white)	110 mA					
Only Display active, full white	210 mA					
All features on, LED and Dis-	260 mA					
play full white						
Display						
Туре	Graphic-PMOLED					
Color Resolution	65k colors					
Resolution	128 x 128 RGB Pixels					
Brightness	90 cd/m2, adjustable in 16 steps					
Contrast	2000:1					
Viewing Angle	160°					
Refresh Rate	25 Pictures per sec.					
Display Life Time <sup>2)3)</sup>	min. 11000 h					
Home Button LED on 6 o'cloc	ck position					
Туре	RGB					
Illumination type	constant, blinking 2x per sec., pumping from 0% to 100% within 1 sec and back					
Brightness	adjustable in 16 steps					
Touch Data						
Technology	PCAP					
Touch Pattern	Full X-Y					
Soft Key Positions	3, 6, 9, and 12 o'clock position on the Touch Wheel					
Touch Button Position	Center of the display					
Soft Key / Touch Button short	128 to 500 ms					
Soft Key / Touch Button long	> 500 ms					
Touch Movements	Swipe Left to Right					
	Swipe Right to Left					
	Swipe Top to Bottom					
	Swipe Bottom to Top					
	Rotation Left					
	Rotation Right					
	Tap on Soft Key / Touch Button					
	150					

< 150 ms

A						
Mass Storage Size	4 Mbyte					
Picture Format	png					
Picture Size <sup>4)</sup>	128 x 128 pixel					
File Size for Pictures	max. 20 kByte					
Video Format	gif					
Video Picture Size	128 x 128 pixel					
-ile Size for Videos	max. 128 kByte					
Frame Rate for animated gif videos	min. 60 ms					
Ambient Light Sensor						
Sensitive Wavelength Range	390 - 700 nm					
Resolution	12 Bit					
Mechanical Data						
Shock Protection	IK05 acc. to IEC/EN 62262					
Screw Tightening Torque for	max. 0.2 Nm					
Nounting Ring						
Climatical Data						
Operating Temperature	-20 to 60 °C					
Storage Temperature	-20 to 70°C					
P Protection Class Front Side	IP67 when mounted with Seal Ring⁵), IP40 otherwise					
Noisture sensitivity level	MSL 1					
Material						
Housing	PC					
Mounting Ring⁵)	PC					
Seal Ring	NBR70					
Touch Surface	Glass					
Product Tests						
EMC	IEC/EN 61000-4-2   IEC/EN 61000-4-3 IEC/EN 61000-4-4   IEC/EN 61000-4-6   IEC/EN 61000-4-8   IEC/EN 61000-6- 1:2016   IEC/EN 61000-6-2:2016   IEC/ EN 61000-6-3:2011   IEC/EN 61000-6- 4:2011   EN 61326-1:2013   EN 55014- 1:2006 + A1:2009 + A2:2011   EN					
	55014-2:2015   EN 61058-1-1:2015-05					
Change of temperature	55014-2:2015   EN 61058-1-1:2015-05 -25°C / +65°C / 50%RH according to					
Change of temperature						
Change of temperature Damp heat, steady state	-25°C / +65°C / 50%RH according to					

1) Mechanical reverse polarity protection made from the combination of the plug and the socket, no internal reverse polarity protection

2) The life time of the display is typically defined as the time it takes for the display to lose half of its brightness and depends on the displayed pictures and animated gif video pictures. The darker the picutes and the lower the brightness, the longer the display life time

3) The display of static images or videos with static image areas over a long period of time may lead to a so-called burn-in effect, in which the static image remains permanently visible on the display

4) Partial pictures are allowed to have smaller size

5) O-Ring is not included in the 10 pcs package

### Approvals and Compliances

System Response Time

Detailed information on product approvals, code requirements, usage instructions and detailed test conditions can be looked up in Details about Approvals

SCHURTER products are designed for use in industrial environments. They have approvals from independent testing bodies according to national and international standards. Products with specific characteristics and requirements such as required in the automotive sector according to IATF 16949, medical technology according to ISO 13485 or in the aerospace industry can be offered exclusively with customer-specific, individual agreements by SCHURTER.

	rds where the product can be used		
Organization	Design	Standard	Description
IEC	Suitable for applications acc.	IEC/UL 62368-1	Audio/video, information and communication technology equipment - Part 1: Safety requirements
Compliances			
-	lies with following Guide Lines		
Identification	Details	Initiator	Description
CE	CE declaration of conformity	SCHURTER AG	The CE marking declares that the product complies with the applicable requirements laid down in the harmonisation of Community legislation on its affixing in accordance with EU Regulation 765/2008.
UK CA	UKCA declaration of conformity	SCHURTER AG	The UKCA marking declares that the product complies with the applicable requirements laid down in the British Amendment of Regulation (EC) 765/2008.
RoHS	RoHS	SCHURTER AG	Directive RoHS 2011/65/EU, Amendment (EU) 2015/863
<b>5</b> 0	China RoHS	SCHURTER AG	The law SJ / T 11363-2006 (China RoHS) has been in force since 1 March 2007. It is similar to the EU directive RoHS.
REACH	REACH	SCHURTER AG	On 1 June 2007, Regulation (EC) No 1907/2006 on the Registration, Evaluation, Authorization and Restriction of Chemicals 1 (abbreviated as "REACH") entered into force.
Dimension [mm	1		
CDS1 Module			
Ed and the second secon	023.8 053.8		Pin 1 supply voltage (+) Pin 2 supply voltage (-)
Mounting ring			
	75.7	30.4 5.9 3.5 8. 5.9 3.5	9.1 variable for Front-Panel thickness

### **Assembly Instructions**





Mounting of the Design-In-Kit using the mounting ring (with double-sided adhesive tape)







g Example for housing with screws from the panel front for mounting without mounting ring

### Diagrams

Pinout o	of FST XHP-10				Pinout l						
in-Nr.:	Signal		plicatio		Pin-Nr.:						
	-	SPI	I2C	RS232	1		not conne	cted	1.1.1		
1	VCC	х	х	x	2	D- D+	negative of positive d	ifferential	data line		
2	GND	х	х	x	4	ID+	not conne		lata line		
3	IRQ_n <sup>2</sup>	X <sup>1</sup>	X <sup>1</sup>	X <sup>1</sup>	5		ground	oteu			
4	CS_n <sup>2</sup>	x				and	ground				
5	GND	x	x	x	-						
6	SCLK / SCL (external pull-up resistance 2.7kΩ)	x	x								
7	GND	x	х	x							
	MOSI / TX / SDA (external pull-up resistance 2.7kΩ)	x	x	x							
9	GND	x	х	x							
10	MISO / RX	х		x							
	nal signal is active low										

### **All Variants**

Packaging unit	Line Connector	Configurations Code	Order Number
10 pack	-	CDS1-00-10-PBKGLS00000-SYRGB-00-X0000-S	3-102-423
Design-In-Kit	EU	CDS1-00-DI-PBKGLS00000-SYRGB-EU-X0000-S	3-102-424
Design-In-Kit	EU / US	CDS1-00-DI-PBKGLS00000-SYRGB-US-X0000-S	3-102-436

### Most Popular.

Availability for all products can be searched real-time:https://www.schurter.com/en/Stock-Check/Stock-Check-SCHURTER



Contents of the Design-In-Kit

Contents of the 10 pack

The specifications, descriptions and illustrations indicated in this document are based on current information. All content is subject to modifications and amendments. Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability and test each product selected for their own applications.