

## RAMO 22 I - Signal indicator blue


## 1.10.071.001/0661

The RAMO I is a signal indicator light with M12 connection and a lot of other features:

- -Sealed body IP69K
- -No housing for the actuators necessary
- -Standardized M12 plug & play connector
- -No wiring necessary

**Dimensions** 

-Mounting holes 22,3 mm




Mounting hole	22.3 mm
Mechanical design	
Output	1 NO, PNP
Mounting	ring nut
Terminals	M12
Reverse polarity protection	yes
Labeling	individually with FLEXLAB
Torque for nut ring	1.2 Nm

Electrical characteristics	
Rated voltage	24 V
Current carrying capacity	200 mA
Output signal	NO / NC: PNP / NPN / active output
Rated current	max. 25 mA / 24 V

Other specifications		
Ambient temp. operating min.	-40 °C	
Ambient temp. operating max.	+70 °C	
Degree of protection from front side	IP 66, IP 67, IP 69K	
Degree of protection from rear side	IP 66 (je nach verwendetem Stecker IP 67 oder IP 69K	
Environmental restistance	acc. to IEC 60068-2-14, -30, -33 and -78	
ROHS compliant	yes	
REACH compliant	yes	





Einbauöffnung nach IEC 60947-5-1