Mallory Sonalert Products, Inc.				Part #: JT120-Y-CEL			
Sales Outline Drawing				Revision: C			
Specifications:	T	1					
Stack Number:	1						
LED Color:	YELLOW						
Connection Wires:	Yellow and Brown						
LED Current Draw:	<230 mA		400 \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \				
Rated Voltage:	120 VAC 90-120 VAC						
Operating Voltage: Sound Level Category:	Loud	Loud	Loud		I	Loud	
Mode of Operation:	Loud Continuous	Loud Medium Pulse				Loud for 5 sec then 0.1s beep until	
Wode of Operation.	Continuous	(5PPS)	·	reset			
Connection:	Black and Gray Wires	Black and Gray Wires; Orange wire connected to				Black and Gray wires; Orange and Purple wires connected to Green/Yellow wire	
Sound Current Draw:	40mA Max.	40mA Max.	40mA Max.		40mA Max.		
Loudness @ 1m:		80-85 dB(A) Typ.					
Frequency:	2000 ± 500 Hz						
Total Max Current:	<270mA with all LED's and sound unit working						
Operating Temperature:	-25° ~ +60°C						
Lens Color:	Opaque White						
Material:	ABS FR15U						
Mounting Method:	Stainless Steel Pole - Black						
Weight Typical (g):	645						
NEMA 12:	Approved						
Options: Dimensions: Inches (mr		cUL Recogn	Please contact facto	ry.		ROHS Compliant	
2.4 [61. 2.7 [68.3]— TOP VIEW		5.6 [422.0]———————————————————————————————————		GASKET	Ø0.57 [Ø14.6 for wires	.91	
LED OPERATION: CONNECT	STACK COLOR WIR	E TO POWER AND BE	ROWN WIRE TO POWER	₹.			
•			<u> </u>				
SOUND OPERATION: CONNECT GRAY AND BLACK WIRES TO POWER FOR CONTINUOUS SOUND.							
FOR MEDIUM PULSE, CONNECT GRAY & BLACK TO POWER AND ORANGE WIRE TO GREEN/YELLOW WIRE.							
FOR DOUBLE PULSE, CONNECT GRAY & BLACK TO POWER AND PURPLE WIRE TO GREEN/YELLOW WIRE. FOR CONT/BEEP, CONNECT GRAY & BLACK TO POWER AND ORANGE & PURPLE TO GREEN/YELLOW WIRE.							
	FOR CONT/BEEP, Co	ONNECT GRAY & BLA	ACK TO POWER AND OF	RANGE &	PURPLE TO	GREEN/YELLOW WIRE.	