

50Ω DC to 3500 MHz

## **VLFG-3500+**

## The Big Deal

- Excellent power handling, 4.5W
- Temperature stable
- Rugged unibody construction
- Good rejection, 40 dB typical



## **Product Overview**

VLFG-3500+ is a 50 $\Omega$  low pass filter built in rugged unibody construction. Covering DC-3500 MHz bandwidth, these units offer good matching within the passband and good rejection in stopband. VLFG-3500+ offer low insertion loss, and excellent power handling capability. It handles up to 4.5W RF input power and provides a wide operating temperature range from -55°C to 125°C.

## **Key Features**

Feature	Advantages		
Low passband insertion loss	Suitable for high performance application.		
4.5W Power handling	Supports a range of system power requirements.		
Connectorized package	The connectorized package is easy to interface with other devices and well suited for test setups.		

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Mini-Circuits trandard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp



# Coaxial Low Pass Filter

50Ω DC to 3500 MHz

#### **Features**

- Low loss, 1.3 dB typical
- Good rejection 40 dB typical
- Excellent power handling, 4.5W
- Temperature stable
- Connectorized package
- Rugged unibody construction

#### **Applications**

- Military radar applications
- Test and measurement
- Telecommunication and broadband wireless applications

#### **Functional Schematic**



#### **Typical Frequency Response**







Generic photo used for illustration purposes only CASE STYLE: FF704

+RoHS Compliant The +Suffix identifies RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications

#### Electrical Specifications at 25°C

Pa	rameter	F#	Frequency (MHz)	Min.	Тур.	Max.	Unit
	Insertion Loss	DC-F1	DC - 3500	_	1.3	2.2	dB
Pass Band	Freq. Cut-Off	F2*	3970	-	3.0	_	dB
	Return Loss	DC-F1	DC - 3500	_	14	_	dB
		F3-F4	4800 - 5000	20	35	_	dB
Stop Band	Rejection Loss	F4-F5	5000 - 8500	30	38	—	dB
		F5-F6	8500 - 15000	_	25	_	dB

In Application where DC voltage is present at either input or output port, DC blocks are required. \* Typically, a ±5% frequency deviation from the stated value may occur on a unit-to-unit basis.

Maximum Ratings				
Operating Temperature	-55°C to 125°C			
Storage Temperature	-55°C to 125°C			
RF Power Input*	4.5W max.@25°C			
Passhand rating, derate linearly to 1W at 125°C ambient				

\*Passband rating, derate linearly to 1W at 125°C ambient Permanent damage may occur if any of these limits are exceeded.

#### Typical Performance Data at 25°C

- ,		
Frequency (MHz)	Insertion Loss (dB)	Return Loss (dB)
10	0.05	41.80
100	0.10	37.37
1000	0.32	30.03
1400	0.41	23.93
1800	0.51	20.20
3000	0.88	22.19
3500	1.22	27.04
3970	2.49	13.34
4100	3.89	8.18
4500	18.91	1.75
4800	42.15	1.15
5000	53.59	1.00
6000	56.36	0.70
7000	50.22	0.60
8500	40.62	0.46
10000	36.21	0.40
11000	34.11	0.47
12000	33.37	0.64
13000	29.00	0.89
15000	28.16	1.08



Notes
A. Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document.
B. Electrical specifications and performance data contained in this specification document are based on Mini-Circuit's applicable established test performance criteria and measurement instructions.
C. The parts covered by this specification document are subject to Mini-Circuits standard limited warranty and terms and conditions (collectively, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

### Mini-Circuits

www.minicircuits.com P.O. Box 350166, Brooklyn, NY 11235-0003 (718) 934-4500 sales@minicircuits.com

REV.A ECO-013807 VLFG-3500+ EDU3946 URJ 220627 Page 2 of 3

#### **Coaxial Connections**

PORT - 1	SMA-Male
PORT - 2	SMA-Female

#### **Outline Drawing**



#### Outline Dimensions ( inch )

в	D	Е	wt.
.410	1.43	.312	grams
10.41	36.32	7.92	10

Note: Please refer to case style drawing for details

A Performance and quality attributes and conditions not expressly stated in this specification document are intended to be excluded and do not form a part of this specification document. B. Electrical specifications and performance data contained in this specification document are based on Min-Circuit's applicable established test performance criteria and measurement instructions. C. The parts covered by this specification document are subject to Min-Circuits and ard limited warranty and terms and conditions (collectivity, "Standard Terms"); Purchasers of this part are entitled to the rights and benefits contained therein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuits' website at www.minicircuits.com/MCLStore/terms.jsp

## **Mini-Circuits**