# Dual NPN Bias Resistor Transistors R1 = 2.2 k $\Omega$ , R2 = 47 k $\Omega$

### NPN Transistors with Monolithic Bias Resistor Network

This series of digital transistors is designed to replace a single device and its external resistor bias network. The Bias Resistor Transistor (BRT) contains a single transistor with a monolithic bias network consisting of two resistors; a series base resistor and a base-emitter resistor. The BRT eliminates these individual components by integrating them into a single device. The use of a BRT can reduce both system cost and board space.

### **Features**

- Simplifies Circuit Design
- Reduces Board Space
- Reduces Component Count
- S and NSV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC-Q101 Qualified and PPAP Capable
- These Devices are Pb-Free, Halogen Free/BFR Free and are RoHS Compliant

### **MAXIMUM RATINGS**

(T<sub>A</sub> = 25°C, common for Q<sub>1</sub> and Q<sub>2</sub>, unless otherwise noted)

Rating	Symbol	Max	Unit
Collector-Base Voltage	V <sub>CBO</sub>	50	Vdc
Collector-Emitter Voltage	$V_{CEO}$	50	Vdc
Collector Current - Continuous	Ic	100	mAdc
Input Forward Voltage	V <sub>IN(fwd)</sub>	12	Vdc
Input Reverse Voltage	V <sub>IN(rev)</sub>	5	Vdc

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

### **ORDERING INFORMATION**


Device	Package	Shipping <sup>†</sup>
MUN5235DW1T1G, SMUN5235DW1T1G	SOT-363	3,000 / Tape & Reel
SMUN5235DW1T3G	SOT-363	10,000 / Tape & Reel
NSBC123JDXV6T1G	SOT-563	4,000 / Tape & Reel



### ON Semiconductor®

www.onsemi.com

### **PIN CONNECTIONS**



### **MARKING DIAGRAMS**



SOT-363 CASE 419B





SOT-563 CASE 463A





SOT-963 CASE 527AD



7M/D = Specific Device Code M = Date Code\*

■ = Pb-Free Package

(Note: Microdot may be in either location)

\*Date Code orientation may vary depending upon manufacturing location.

### **ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
NSBC123JDXV6T5G	SOT-563	8,000 / Tape & Reel
NSBC123JDP6T5G	SOT-963	8,000 / Tape & Reel

<sup>†</sup>For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

### THERMAL CHARACTERISTICS

	Characteristic	Symbol	Max	Unit
MUN5235DW1 (SOT-363) ON	E JUNCTION HEATED			
Total Device Dissipation $T_A = 25^{\circ}C \qquad \text{(Note 1)}$ $\text{(Note 2)}$ Derate above 25°C $\text{(Note 2)}$	(Note 1)	P <sub>D</sub>	187 256 1.5 2.0	mW mW/°C
Thermal Resistance, Junction to Ambient	(Note 1) (Note 2)	$R_{ hetaJA}$	670 490	°C/W
MUN5235DW1 (SOT-363) BO	TH JUNCTION HEATED (Note 3)	·		
Total Device Dissipation $T_A = 25^{\circ}C \qquad \text{(Note 1)}$ $\text{(Note 2)}$ Derate above 25°C $\text{(Note 2)}$	(Note 1)	P <sub>D</sub>	250 385 2.0 3.0	mW mW/°C
Thermal Resistance, Junction to Ambient (Note 2)	(Note 1)	$R_{ hetaJA}$	493 325	°C/W
Thermal Resistance, Junction to Lead (Note 1) (Note 2)		$R_{ hetaJL}$	188 208	°C/W
Junction and Storage Temper	ature Range	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C
NSBC123JDXV6 (SOT-563) (	ONE JUNCTION HEATED			
Total Device Dissipation $T_A = 25^{\circ}C$ (Note 1) Derate above $25^{\circ}C$	(Note 1)	P <sub>D</sub>	357 2.9	mW mW/°C
Thermal Resistance, Junction to Ambient	(Note 1)	$R_{ hetaJA}$	350	°C/W
NSBC123JDXV6 (SOT-563) E	BOTH JUNCTION HEATED (Note 3)			
Total Device Dissipation $T_A = 25^{\circ}C$ (Note 1) Derate above 25°C	(Note 1)	P <sub>D</sub>	500 4.0	mW mW/°C
Thermal Resistance, Junction to Ambient	(Note 1)	$R_{ hetaJA}$	250	°C/W
Junction and Storage Temper	ature Range	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C
NSBC123JDP6 (SOT-963) OI	NE JUNCTION HEATED			
Total Device Dissipation $T_A = 25^{\circ}C$ (Note 4) (Note 5) Derate above 25 $^{\circ}C$ (Note 5)	(Note 4)	P <sub>D</sub>	231 269 1.9 2.2	MW mW/°C
Thermal Resistance, Junction to Ambient (Note 5)	(Note 4)	$R_{ hetaJA}$	540 464	°C/W
NSBC123JDP6 (SOT-963) BC	OTH JUNCTION HEATED (Note 3)			
Total Device Dissipation  T <sub>A</sub> = 25°C (Note 4)  (Note 5)  Derate above 25°C  (Note 5)	(Note 4)	P <sub>D</sub>	339 408 2.7 3.3	MW mW/°C

### THERMAL CHARACTERISTICS


Characteristic	Symbol	Max	Unit			
NSBC123JDP6 (SOT-963) BOTH JUNCTION HEATED (Note 3)						
Thermal Resistance, Junction to Ambient (Note 4) (Note 5)	$R_{ hetaJA}$	369 306	°C/W			
Junction and Storage Temperature Range	T <sub>J</sub> , T <sub>stg</sub>	-55 to +150	°C			


FR-4 @ Minimum Pad.
 FR-4 @ 1.0 × 1.0 Inch Pad.
 Both junction heated values assume total power is sum of two equally powered channels.
 FR-4 @ 100 mm², 1 oz. copper traces, still air.
 FR-4 @ 500 mm², 1 oz. copper traces, still air.

**ELECTRICAL CHARACTERISTICS** (T<sub>A</sub> = 25°C, common for Q<sub>1</sub> and Q<sub>2</sub>, unless otherwise noted)

Characteristic	Symbol	Min	Тур	Max	Unit
OFF CHARACTERISTICS			•		•
Collector-Base Cutoff Current $(V_{CB} = 50 \text{ V}, I_E = 0)$	I <sub>CBO</sub>	-	-	100	nAdc
Collector-Emitter Cutoff Current $(V_{CE} = 50 \text{ V}, I_B = 0)$	I <sub>CEO</sub>	-	-	500	nAdc
Emitter-Base Cutoff Current $(V_{EB} = 6.0 \text{ V}, I_C = 0)$	I <sub>EBO</sub>	-	-	0.2	mAdc
Collector-Base Breakdown Voltage ( $I_C = 10 \mu A, I_E = 0$ )	V <sub>(BR)CBO</sub>	50	_	-	Vdc
Collector-Emitter Breakdown Voltage (Note 6) $(I_C = 2.0 \text{ mA}, I_B = 0)$	V <sub>(BR)CEO</sub>	50	-	-	Vdc
ON CHARACTERISTICS					
DC Current Gain (Note 6) (I <sub>C</sub> = 5.0 mA, V <sub>CE</sub> = 10 V)	h <sub>FE</sub>	80	140	-	
Collector-Emitter Saturation Voltage (Note 6) (I <sub>C</sub> = 10 mA, I <sub>B</sub> = 1.0 mA)	V <sub>CE(sat)</sub>	-	-	0.25	V
Input Voltage (Off) (V <sub>CE</sub> = 5.0 V, I <sub>C</sub> = 100 $\mu$ A)	V <sub>i(off)</sub>	-	0.6	-	Vdc
Input Voltage (On) ( $V_{CE} = 0.2 \text{ V, } I_{C} = 5.0 \text{ mA}$ )	V <sub>i(on)</sub>	-	0.8	-	Vdc
Output Voltage (On) (V <sub>CC</sub> = 5.0 V, V <sub>B</sub> = 2.5 V, R <sub>L</sub> = 1.0 k $\Omega$ )	V <sub>OL</sub>	-	-	0.2	Vdc
Output Voltage (Off) (V <sub>CC</sub> = 5.0 V, V <sub>B</sub> = 0.5 V, R <sub>L</sub> = 1.0 k $\Omega$ )	V <sub>OH</sub>	4.9	-	-	Vdc
Input Resistor	R1	1.5	2.2	2.9	kΩ
Resistor Ratio	R <sub>1</sub> /R <sub>2</sub>	0.038	0.047	0.056	

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.






- (1) SOT-363;  $1.0 \times 1.0$  Inch Pad
- (2) SOT-563; Minimum Pad
- (3) SOT-963; 100 mm<sup>2</sup>, 1 oz. Copper Trace

Figure 1. Derating Curve

# TYPICAL CHARACTERISTICS MUN5235DW1, NSBC123JDXV6



V<sub>R</sub>, REVERSE BIAS VOLTAGE (VOLTS)

Figure 4. Output Capacitance

30


20

0

0

10

 $\label{eq:Vin} V_{in}, \mbox{ INPUT VOLTAGE (V)}$  Figure 5. Output Current vs. Input Voltage



50

0.001

Figure 6. Input Voltage vs. Output Current

## TYPICAL CHARACTERISTICS NSBC123JDP6




Figure 7. V<sub>CE(sat)</sub> vs. I<sub>C</sub>

Figure 8. DC Current Gain




Figure 9. Output Capacitance

Figure 10. Output Current vs. Input Voltage






Figure 11. Input Voltage vs. Output Current

### PACKAGE DIMENSIONS

### SC-88/SC70-6/SOT-363

CASE 419B-02 **ISSUE Y** 






- TES:
  DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
  CONTROLLING DIMENSION: MILLIMETERS.
  DIMENSIONS D AND E1 DO NOT INCLUDE MOLD FLASH,
  PROTRUSIONS, OR GATE BURRS. MOLD FLASH, PROTRUSIONS, OR GATE BURRS SHALL NOT EXCEED 0.20 PER END.
  DIMENSIONS D AND E1 AT THE OUTERMOST EXTREMES OF
  THE PLASTIC BODY AND DATUM H.
  DATUMS A AND B ARE DETERMINED AT DATUM H.
  DIMENSIONS A AND A ADDIT OF THE ELAT SECTION OF THE

- DIMENSIONS b AND c APPLY TO THE FLAT SECTION OF THE LEAD BETWEEN 0.08 AND 0.15 FROM THE TIP.
- DIMENSION 5 DOES NOT INCLUDE DAMBAR PROTRUSION.
  ALLOWABLE DAMBAR PROTRUSION SHALL BE 0.08 TOTAL IN
  EXCESS OF DIMENSION 5 AT MAXIMUM MATERIAL CONDITION. THE DAMBAR CANNOT BE LOCATED ON THE LOWER RADIUS OF THE FOOT.

	MILLIMETERS			INCHES		
DIM	MIN	NOM	MAX	MIN	NOM	MAX
Α			1.10			0.043
A1	0.00		0.10	0.000		0.004
A2	0.70	0.90	1.00	0.027	0.035	0.039
b	0.15	0.20	0.25	0.006	0.008	0.010
С	0.08	0.15	0.22	0.003	0.006	0.009
D	1.80	2.00	2.20	0.070	0.078	0.086
Е	2.00	2.10	2.20	0.078	0.082	0.086
E1	1.15	1.25	1.35	0.045	0.049	0.053
е	(	0.65 BS	С	0.026 BSC		
L	0.26	0.36	0.46	0.010	0.014	0.018
L2		0.15 BS	C	0.006 BSC		
aaa	0.15			0.006		
bbb	0.30			0.012		
ccc	0.10			0.004		
ddd		0.10			0.004	


### **RECOMMENDED SOLDERING FOOTPRINT\***



\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

### **PACKAGE DIMENSIONS**

**SOT-563, 6 LEAD** CASE 463A ISSUE G



- NOTES:


  1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.

  2. CONTROLLING DIMENSION: MILLIMETERS

  3. MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.

	MILLIMETERS			INCHES		
DIM	MIN	NOM	MAX	MIN	NOM	MAX
Α	0.50	0.55	0.60	0.020	0.021	0.023
b	0.17	0.22	0.27	0.007	0.009	0.011
С	0.08	0.12	0.18	0.003	0.005	0.007
D	1.50	1.60	1.70	0.059	0.062	0.066
Е	1.10	1.20	1.30	0.043	0.047	0.051
е		0.5 BSC		(	0.02 BSC	
L	0.10	0.20	0.30	0.004	0.008	0.012
HE	1.50	1.60	1.70	0.059	0.062	0.066


### **SOLDERING FOOTPRINT\***





<sup>\*</sup>For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

### PACKAGE DIMENSIONS

SOT-963 CASE 527AD **ISSUE E** 








#### NOTES

- DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. CONTROLLING DIMENSION: MILLIMETERS
- MAXIMUM LEAD THICKNESS INCLUDES LEAD FINISH THICKNESS. MINIMUM LEAD THICKNESS IS THE MINIMUM THICKNESS OF BASE MATERIAL.
- 4. DIMENSIONS D AND E DO NOT INCLUDE MOLD FLASH, PROTRUSIONS, OR GATE BURRS.

	MILLIMETERS				
DIM	MIN	NOM	MAX		
Α	0.34	0.37	0.40		
b	0.10	0.15	0.20		
С	0.07	0.12	0.17		
D	0.95	1.00	1.05		
E	0.75	0.80	0.85		
е		0.35 BSC			
HE	0.95	1.00	1.05		
L	0.19 REF				
L2	0.05	0.10	0.15		

### RECOMMENDED **MOUNTING FOOTPRINT\***



\*For additional information on our Pb-Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

ON Semiconductor and the are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="https://www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

### **PUBLICATION ORDERING INFORMATION**

### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free

Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

Phone: 81-3-5817-1050