# MOSFET - N-Channel Shielded Gate PowerTrench® 150 V, 15 mΩ, 61.3 A

# **NVDS015N15MC**

#### **Features**

- Shielded Gate MOSFET Technology
- Max  $R_{DS(on)} = 15 \text{ m}\Omega$  at  $V_{GS} = 10 \text{ V}$ ,  $I_D = 29 \text{ A}$
- Low R<sub>DS(on)</sub> to Minimize Conduction Losses
- Low Capacitance to Minimize Driver Losses
- Optimized Gate Charge to Minimize Switching Losses
- AEC-Q101 Qualified and PPAP Capable
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant

## **Typical Applications**

- Primary Side for 48 V Isolated Bus
- SR for MV Secondary Applications

# **MAXIMUM RATINGS** (T<sub>J</sub> = 25°C unless otherwise noted)

Parameter			Symbol	Value	Unit
Drain-to-Source Voltage			$V_{DSS}$	150	٧
Gate-to-Source Voltage	Gate-to-Source Voltage			±20	V
Continuous Drain		T <sub>C</sub> = 25°C	I <sub>D</sub>	61.3	Α
Current R <sub>0JC</sub> (Note 2)	Steady	T <sub>C</sub> = 100°C		43.4	
Power Dissipation	State	T <sub>C</sub> = 25°C	$P_{D}$	107.1	W
R <sub>θJC</sub> (Note 2)		T <sub>C</sub> = 100°C		53.6	
Continuous Drain			I <sub>D</sub>	10.5	Α
Current R <sub>θJA</sub> (Notes 1, 2)	Steady	T <sub>A</sub> = 100°C		7.4	
Power Dissipation	State	T <sub>A</sub> = 25°C	$P_{D}$	3.1	W
R <sub>θJA</sub> (Notes 1, 2)		T <sub>A</sub> = 100°C		1.6	
Pulsed Drain Current	$T_A = 25^{\circ}C, t_p = 10 \ \mu s$		I <sub>DM</sub>	382	Α
Operating Junction and Storage Temperature Range			T <sub>J</sub> , T <sub>stg</sub>	-55 to +175	°C
Source Current (Body Diode)			Is	89.3	Α
Single Pulse Drain-to-Source Avalanche Energy (I <sub>L(pk)</sub> = 4.4 A)			E <sub>AS</sub>	1301	mJ
Lead Temperature for Soldering Purposes (1/8" from case for 10 s)			TL	260	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.


- 1. Surface-mounted on FR4 board using a 650 mm<sup>2</sup>, 2 oz. Cu pad.
- The entire application environment impacts the thermal resistance values shown, they are not constants and are only valid for the particular conditions noted.



## ON Semiconductor®

#### www.onsemi.com


V <sub>(BR)DSS</sub>	R <sub>DS(ON)</sub> MAX	I <sub>D</sub> MAX
150 V	15 mΩ @ 10 V	61.3 A



**N-CHANNEL MOSFET** 

# MARKING DIAGRAM





015N15MCG = Specific Device Code

A = Assembly Location

Y = Year WW = Work Week

#### ORDERING INFORMATION

Device	Package	Shipping <sup>†</sup>
NVDS015N15MCT4G	DPAK (Pb-Free)	2500 / Tube

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

#### THERMAL RESISTANCE MAXIMUM RATINGS

Parameter	Symbol	Value	Unit
Junction-to-Case - Steady State (Note 2)	$R_{ hetaJC}$	1.4	°C/W
Junction-to-Ambient - Steady State (Notes 1, 2)	$R_{ hetaJA}$	47.9	

# ELECTRICAL CHARACTERISTICS /T OF C unloss otherwise of

Parameter	Symbol	Test Condition		Min	Тур	Max	Unit
OFF CHARACTERISTICS							
Drain-to-Source Breakdown Voltage	V <sub>(BR)DSS</sub>	$V_{GS} = 0 \text{ V}, I_D = 250 \mu\text{A}$		150			V
Drain-to-Source Breakdown Voltage Temperature Coefficient	V <sub>(BR)DSS</sub> /	I <sub>D</sub> = 250 μA, ref to 25°C			83		mV/°C
Zero Gate Voltage Drain Current	I <sub>DSS</sub>	V <sub>GS</sub> = 0 V, T <sub>J</sub> = 25°C				1.0	
	$V_{DS} = 0$	V <sub>DS</sub> = 120 V	T <sub>J</sub> = 125°C		1.1		μΑ
Gate-to-Source Leakage Current	I <sub>GSS</sub>	$V_{DS} = 0 \text{ V}, V_{GS} = \pm 20 \text{ V}$				±100	nA
ON CHARACTERISTICS	•					•	
Gate Threshold Voltage	V <sub>GS(TH)</sub>	$V_{GS} = V_{DS}, I_D =$	= 162 μA	2.5		4.5	V
Negative Threshold Temperature Coefficient	V <sub>GS(TH)</sub> /T <sub>J</sub>	I <sub>D</sub> = 162 μA, ref	to 25°C		-8.2		mV/°C
Drain-to-Source On Resistance	R <sub>DS(on)</sub>	V <sub>GS</sub> = 10 V, I <sub>D</sub>	= 29 A		11.8	15	mΩ
Forward Transconductance	9FS	V <sub>DS</sub> = 10 V, I <sub>D</sub> = 29 A			58		S
CHARGES, CAPACITANCES & GATE RESIS	STANCE					•	•
Input Capacitance	C <sub>ISS</sub>	V <sub>GS</sub> = 0 V, f = 1 MHz, V <sub>DS</sub> = 75 V			2120		pF
Output Capacitance	C <sub>OSS</sub>				595		
Reverse Transfer Capacitance	C <sub>RSS</sub>				10.5		
Total Gate Charge	Q <sub>G(TOT)</sub>	V <sub>GS</sub> = 10 V, V <sub>DS</sub> = 75 V; I <sub>D</sub> = 29 A			27		nC
Threshold Gate Charge	Q <sub>G(TH)</sub>				7		
Gate-to-Source Charge	$Q_{GS}$				11		
Gate-to-Drain Charge	$Q_{GD}$				4		
Plateau Voltage	V <sub>GP</sub>				5.5		V
SWITCHING CHARACTERISTICS (Note 3)	•					•	
Turn-On Delay Time	t <sub>d(ON)</sub>				16		
Rise Time	t <sub>r</sub>	V <sub>GS</sub> = 10 V, V <sub>DE</sub>	n = 75 V.		5		
Turn-Off Delay Time	t <sub>d(OFF)</sub>	$I_D = 29 \text{ A}, R_G = 6 \Omega$			21		ns
Fall Time	t <sub>f</sub>				4		
DRAIN-SOURCE DIODE CHARACTERISTIC	s					•	
Forward Diode Voltage	V <sub>SD</sub>	V <sub>GS</sub> = 0 V, I <sub>S</sub> = 29 A	T <sub>J</sub> = 25°C		0.89	1.2	V
Reverse Recovery Time	t <sub>RR</sub>	V <sub>GS</sub> = 0 V, V <sub>DD</sub>	= 75 V		49		ns
Reverse Recovery Charge	Q <sub>RR</sub>	dl <sub>S</sub> /dt = 300 A/μs, l <sub>S</sub> = 29 A			197		nC
Reverse Recovery Time	t <sub>RR</sub>	$V_{GS} = 0 \text{ V}, V_{DD} = 75 \text{ V}$ $dI_S/dt = 1000 \text{ A}/\mu\text{s}, I_S = 29 \text{ A}$			34		ns
Reverse Recovery Charge	Q <sub>RR</sub>				345		nC

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

3. Switching characteristics are independent of operating junction temperatures.

#### **TYPICAL CHARACTERISTICS**




Figure 5. Normalized On-Resistance vs. **Junction Temperature** 

Figure 6. Drain-to-Source Leakage Current vs. Voltage

V<sub>DS</sub>, DRAIN-TO-SOURCE VOLTAGE (V)

#### **TYPICAL CHARACTERISTICS**




Figure 7. Capacitance vs. Drain-to-Source Voltage



/<sub>DD</sub> = 75 V

24

30




Figure 9. Resistive Switching Time Variation vs. Gate Resistance




Figure 10. Source-to-Drain Diode Forward Voltage vs. Source Current




Figure 11. Forward Bias Safe Operating Area




Figure 12. Unclamped Inductive Switching Capability

# **TYPICAL CHARACTERISTICS**





Figure 13. Transient Thermal Impedance





DOCUMENT NUMBER:	98AON10527D	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	DPAK (SINGLE GAUGE)		PAGE 1 OF 1	

STYLE 10:

PIN 1. CATHODE 2. ANODE

3 CATHODE

4. ANODE

STYLE 9:

PIN 1. ANODE 2. CATHODE

3 RESISTOR ADJUST

CATHODE

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.

STYLE 7: PIN 1. GATE 2. COLLECTOR

3 FMITTER

4. COLLECTOR

STYLE 8:

PIN 1. N/C 2. CATHODE

3 ANODE

CATHODE

STYLE 6:

PIN 1. MT1 2. MT2

3 GATE

\*This information is generic. Please refer to device data sheet for actual part marking.

Pb-Free indicator, "G" or microdot "=", may

or may not be present. Some products may

not follow the Generic Marking.

onsemi, Onsemi, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdf/Patent-Marking.pdf">www.onsemi.com/site/pdf/Patent-Marking.pdf</a>. Onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA class 3 medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase

#### ADDITIONAL INFORMATION

**TECHNICAL PUBLICATIONS:** 

 $\textbf{Technical Library:} \ \underline{www.onsemi.com/design/resources/technical-documentation}$ 

onsemi Website: www.onsemi.com

ONLINE SUPPORT: www.onsemi.com/support

For additional information, please contact your local Sales Representative at

www.onsemi.com/support/sales