





The Sound Solution

Small, Smart and Effective Hearing Protection

The $3M^{TM}$ PELTORTM TEP-100 Tactical Earplug helps provide hearing protection, and helps improve situational awareness and communication. The small, lightweight, and rechargeable tactical earplugs are designed for tactical, engineering, and maintenance applications.





The power to protect your world[™]

Hearing Protection & Situational Awareness

Rechargeable:

Charging contacts recharge the unit while in the case. Li-ion battery provides up to 16 hours of continuous operation.

Button:

Intuitive one-button operation turns unit on, off, and selects volume settings (2).

Hearing Protection:

Replaceable communications eartip helps provide hearing protection in noisy environments. Multiple sizes and types designed to fit most ear canals.

Cord Connection:

Attachment point for optional earplug cord. (included)





Water Resistant:

Innovative design helps protect microphone against water ingress.

Design:

Corner radius designed to help soften contact zone and increase comfort.

Microphone Port: Helps minimize wind noise



The 3M[™] PELTOR[™] Tactical Earplug helps protect your hearing, and can help improve situational awareness and communications in challenging environments. Integrated with state-of-the-art level dependent technology, the TEP-100 helps provide hearing protection in noise and situational awareness in quiet environments.

Communication

3M[™] PELTOR[™] level dependent technology helps provide hearing protection in noise and improves communication in quiet. Protecting hearing and improving situational awareness can help increase safety and improve productivity.

Compatibility

3M[™] PELTOR[™] Tactical Earplug is compatible with most headborne 3M[™] Personal Protective Equipment (PPE) such as helmets, hardhats, and face shields.

Comfort

The small and lightweight design helps improve overall comfort and user experience.



Solid red = Charging Blinking red = Not Charging Fast blinking red = Temperature Fault Solid yellow = Charging - Low Battery Blinking yellow = Not Charging - Low Battery Solid green = Charging Complete





Earplug Clips:

Steel clips help secure earplugs in case helps ensure contact for charging.

Micro B USB Charging Port:

USB Port charges earplugs when plugged vinto a computer or wall socket.

Sealing Ring:

Rubber sealing ring helps protect earplugs in wet and dirty environments.

Technical data specifications

3M[™] PELTOR[™] TEP-100 Tactical Earplug

Technical data specifications

Model

Microphone Type

Earpiece Power / Electrical Characteristics

Earpiece Battery Type:	Lithium Ion
Earpiece Battery Life:	Up to 16 hours
Earpiece Battery Charge Time:	Approximately 90 minutes
Earpiece Volume Steps	2 steps, Low and High
Case Battery Type	3 AA Alkaline Batteries
Case Battery Life:	Up to 16 recharging cycles
Case USB Type:	Micro B

Omni-directional

Laboratory Attenuation

n ANSI \$3.19-1974

3M[™] UltraFit[™] Eartips

Frequency [Hz]	125	250	500	1000	2000	3150	4000	6300	8000	NRR	CSA Class
Mean Attenuation [dB]	36.2	33.7	34.7	32.0	34.5	37.4	35.6	38.0	37.5	23	AL
Standard Deviation [dB]	5.1	5.2	5.5	3.9	3.4	5.3	6.5	4.4	5.4	23	AL

3M[™] Skull Screws[™] Eartips

Frequency [Hz]	125	250	500	1000	2000	3150	4000	6300	8000	NRR	CSA Class
Mean Attenuation [dB]	36.3	35.7	39.8	41.4	40.4	43.0	41.9	48.2	46.0	30	AL
Standard Deviation [dB]	5.3	5.5	5.5	4.2	3.4	4.6	3.5	4.6	4.2	30	

Standards

Waterproof Rating	Complies with IP67 with cover and USB ports closed.
Noise Reduction Rating (NRR)	Tested in accordance with ANSI S3.19-1974

Physical Characteristics

Case Size (L x W x H)	4.5" long x 3.1" wide x 1.1" thick
	(114.2 mm x 78.2 mm x 26.9 mm)
Case Material	Glass filled polyetherimide
Earpiece Keypad	One button operation
	(On / Off / Mode Selection)
Case Keypad	One button operation (Charging Status)
RoHS Compliance	RoHS II
Weight Box containing charger, 2 earpieces, 4 pair communications eartips, cord, 3 AA batteries	9.6 oz
Weight Charger with batteries, 2 earpieces, and cord	7.0 oz
Weight: Charger	4.2 oz
Weight: 1 earpiece:	0.13 oz

Environmental Characteristics

Operating Temperature Range	0 to 122°F (0 to 50°C)
Storage Temperature Range	1 year at -4 to 68°F (-20 to 20°C)
	3 months at -4 to 113°F (-20 to 45°C)
	1 month at -4 to 140°F (-20 to 60°C)

3M

3M Personal Safety Division

3M Center Building 235-2W-70 St. Paul, MN 55144-1000 For More Information www.3M.com/PeltorTEP Technical Assistance (U.S.A.) 1-800-665-2942 Customer Service (U.S.A.) 1-800-328-1667

3M is a trademark of and The Power to Protect Your World is a service mark of 3M Company, used under license in Canada. Peltor is a trademark of 3M Svenska AB, used under license in Canada.

Please recycle. Printed in USA. © 3M 2014. All rights reserved.

Part #	SKU	Description
TEP-100	70-0716-5628-7	3M [™] PELTOR [™] TEP-100 Tactical Earplug Kit
TEP-CORD	70-0716-7379-5	3M™ PELTOR™ Tactical Earplug Replacement Cord
TEP-100E	70-0716-5025-6	3M™ PELTOR™ Replacement Earpiece
TEP-100C	70-0716-5026-4	3M™ PELTOR™ Tactical Earplug Replacement Case
370-TEPL-25	70-0716-7374-6	3M™ PELTOR™ UltraFit Communication Tips Replacement, Large
370-TEPM-25	70-0716-7373-8	3M™ PELTOR™ UltraFit Communication Tips Replacement, Medium
370-TEPS-25	70-0716-7372-0	3M™ PELTOR™ UltraFit Communication Tips Replacement, Small
370-1019-10	70-0716-1527-5	3M [™] Skull Screw [™] Ear Tips

▲ WARNING!

Hearing Protection Products* These hearing protectors help reduce exposure to hazardous noise and other loud sounds. Misuse or failure to wear hearing protectors at all times that you are exposed to noise may result in hearing loss or injury. For proper use, see supervisor, User Instructions, or call 3M Technical Service in the U.S.A. at 1-800-243-4630. If there is any drainage from your ear or you have an ear infection, consult with your physician before wearing earlplugs. Failure to do so may result in hearing loss or injury. Choking Hazard - Keep awag from infants and small children.

Noise Reduction Rating (NRR):

Research suggests that many users will receive less noise reduction than indicated by the NRR due to variation in hearing protector fit, fitting skill and motivation of the user. It is recommended that the NRR be reduced by 50% to better estimate typical workplace protection.

△ **CAUTION!** When worr according to the User Instructions, this hearing protector helps reduce exposure to both *continuous* noises, such as industrial noises and noises from vehicles and aircraft, as well as very loud *impulse* noises, such as gunfire. It is difficult to predict the required and/or actual hearing protection obtained during exposure to impulse noises. For gunfire, the weapon type, number of rounds fired, proper selection, fit and use of hearing protection, proper care of hearing protection, and other variables will impact performance. If your hearing seems dulled or you hear a ringing or buzzing during or after any noise exposure (including gunfire), or for any other reason you suspect a hearing problem, your hearing may be at risk. To learn more about hearing protection for impulse noise, visit www.3M.com/hearing.