PIN diode

RN142V

Applications


High frequency switching

● Features


- 1) Small mold type. (UMD2)
- 2) Low high-frequency forward resistance / low capacitance (CT).

Construction

Silicon epitaxial planar



●Taping dimensions (Unit: mm)



● Absolute maximum ratings (Ta=25°C)

PADSOIDLE MAXIMUM ratings (1a-23 C)							
Parameter	Symbol Limits		Unit				
Reverse voltage	V_R	60	V				
Reverse current	I _F	100	mA				
Junction temperature	Tj	150	°C				
Storage temperature	Tstg	-55 to +150	°C				

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions
Forward voltage	V_{F}	ı	-	1	V	I _F =10mA
Reverse current	I _R	ı	-	0.1	μA	$V_R=60V$
Capacitance between terminals	Ct	1	-	0.45	pF	V _R =1V , f=1MHz
High frequeny switching	Rf	-	-	3	Ω	I _F =3mA,f=100MHz

●Electrical characteristic curves (Ta=25°C) f=1MHz 100 FORWARD CURRENT:IF(mA) REVERSE CURRENT:IR(nA) CAPACITANCE BETWEEN TEBMINALS:Ct(pF) Ta=25°C 0.1 0.01 30 20 30 40 50 60 REVERSE VOLTAGE: VR(V) 0 10 20 0 70 REVERSE VOLTAGE:VR(V) VR-Ct CHARACTERISTICS FORWARD VOLTAGE: VF(V) VF-IF CHARACTERISTICS VR-IR CHARACTERISTICS Ta=25°C VR=0V Ta=25°C IF=10m/ VOLTAGE: VF(mV) CAPACITANCE BETWEEN TERMINALS:Ct(pF) FORWARD OPERATING RESISTANCE:#(♀) 830 820 FORWARD AVE:825.4mV 0.1 0.1 800 0.1 10 100 FREQUENCY(MHz) Ct-f CHARACTERISTICS 1000 FORWARD CURRENT:IF(mA) rf-IF CHARACTERISTICS VF DISPERSION MAP 10 Ta=25°C Ta=25°C f=100MHz 0.9 1.9 VR=60V n=30pcs IF=3mA REVERSE CURRENT:IR(nA) CAPACITANCE BETWEEN OPERATING TERMINALS:Ot(pF) 6.0 5.0 7.0 4.0 8.0 5.0 8.0 5.0 n=10pcs RESISTANCE:rf(Ω) AVE:1.206 Ω 1.3 0.2 AVE:0.364pF 0.1 0 FORWARD CURRENT:IF(mA) IR DISPERSION MAP Ct DISPERSION MAP rf DISPERSION MAP Ta=25°C f=100MHz 0.9 0.8 IF=10mA DISCHARGE TEST ESD(KV) FORWARD OPERATING n=10pcs RESISTANCE:元(♀) ELECTROSTATIC 0.6 0.5 0.4 AVE:0.71kV 0.3 AVE:0.639 Ω 0.1 R=0 Ω FORWARD CURRENT:IF(mA) rf DISPERSION MAP ESD DISPERSION MAP



Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any
 means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the
 product described in this document are for reference only. Upon actual use, therefore, please request
 that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or
 otherwise dispose of the same, no express or implied right or license to practice or commercially
 exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

