



1.85mm Female Field Replaceable Connector 2 Hole Flange Mount 0.009 inch Pin, .400 inch Hole Spacing with Metal Contact Ring

## RF Connectors Technical Data Sheet



## PE45633

### Configuration

- 1.85mm Female Connector
- Straight Body Geometry

#### Features

- Max. Operating Frequency 67 GHz
- Excellent VSWR of 1.25:1

#### **Applications**

- General Purpose Test
- Rack and Panel Mount Applications
- Metal Contact Ring

2 Hole Flange

- Used in Product Requiring Hermetic Seals
- Allows for Replacement of Damaged Connectors

Connector Interface Types: 0.009 inch Pin

Gold Plated Beryllium Copper Contact

#### Description

Pasternack's PE45633 1.85mm female 2 hole flange mount field replaceable connector is part of our full line of RF components available for same-day shipping. Our 1.85mm female connector operates up to a maximum frequency of 67 GHz and offers excellent VSWR of 1.25:1. This 1.85mm 2 hole flange connector allows designers to create external connections on their product enclosures, and can be used in a variety of other rack mount and panel mount applications. This field replaceable connector is easy to install or replace in the field.

Our 1.85mm female 2 hole flange connector PE45633 datasheet specifications and drawing with dimensions are shown below in this PDF. Pasternack's broad catalog of RF, microwave and millimeter wave connectors allows designers to configure and customize their signal connections however they like. Whether the need is to provide an I/O for a board design, or simply create a custom cable assembly configuration, Pasternack has the right connector for the job. Pasternack can also expertly build your custom cable assemblies for you and ship same-day.

### **Electrical Specifications**

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		67	GHz
VSWR			1.25:1	

#### **Mechanical Specifications**

Size	
Length	0.443 in [11.25 mm]
Width/Dia.	0.275 in [6.99 mm]
Height	0.55 in [13.97 mm]
Weight	0.004 lbs [1.81 g]
Mating Cycles	500 Cycles

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 1.85mm Female Field Replaceable Connector 2 Hole Flange Mount 0.009 inch Pin, .400 inch Hole Spacing with Metal Contact Ring PE45633

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



1.85mm Female Field Replaceable Connector 2 Hole Flange Mount 0.009 inch Pin, .400 inch Hole Spacing with Metal Contact Ring

# **RF Connectors Technical Data Sheet**



PE45633

Description Contact		
	Material	Plating
	Beryllium Copper	Gold
Insulation	PEI	
Outer Conductor	Passivated Stainless Steel	
Body	Passivated Stainless Steel	
Environmental Specification Temperature Operating Range	n <b>s</b> -40 to +165 d	eg C
Compliance Certifications (s	see product page for current document)	
Plotted and Other Data Notes:		
Ring from Pasternack Enterprise	le Connector 2 Hole Flange Mount 0.009 inch Pin is has same day shipment for domestic and Int in a 99.4% availability and are part of the broades	ernational orders. Our RF, microway
	part number in "SEARCH" on website) to obtain Inm Female Field Replaceable Connector 2 Hole F PE45633	
URL: https://www.pasternack.com	n/1.85mm-female-0.009-pin-connector-pe45633-	-p.aspx
	nt is accurate to the best of our knowledge and representative locumentation of the part, in order to implement improvements pecifications are nominal. <u>Pasternack does not make any repre</u> a, and Pasternack does not assume any liability arising out of the	s. Pasternack reserves the right to make such esentation or warranty regarding the suitability of

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

# PE45633 CAD Drawing

1.85mm Female Field Replaceable Connector 2 Hole Flange Mount 0.009 inch Pin, .400 inch Hole Spacing with Metal Contact Ring

