

Gas Discharge Tubes GTCC23-XXXM-R01-2 Series

Littelfuse Circuit Protection 3mm 2Pole Chip type GDTs (ceramic gas discharge tubes), are commonly used to help protect sensitive telecom equipment such as communication lines, signal lines and data transmission lines from damage caused by transient surge voltages that typically result from lightning strikes and equipment switching operations.

Littelfuse Circuit Protection 3mm Chip type GDTs offer excellent surge protection characteristics, low capacitance and a broad array of breakover voltage levels, making them suitable for applications such as high data-rate telecom communication network protection (e.g. ADSL, VDSL).



Benefits:

- Compact, small form factor suitable for efficient assembly
- Suitable for high-frequency applications

Features:

- 2Poles, 3mm devices
- Broad voltage range from 75V-400V
- · Form factor: surface mount
- · Low capacitance and insertion loss
- Referring to ITUT K.20 and ITUT K.21
- UL 497B recognized
- RoHS compliant
- Devices tested per ITU K.12 recommendations
- · Non-radioactive materials

Applications:

Telecommunications, RF system protection, CATV Modem, Hub protection, Security Systems, Data acquisition



GTCC23-XXXM-R01-2 Series

Device Voltage Ratings

Part Number	DC Sparkover	Impulse Sparkover Voltage	
	@ 100V/s ±20% Tolerance (V)	@1000 V/µs (V)	
GTCC23-750M-R01-2*	75	600	
GTCC23-900M-R01-2	90	600	
GTCC23-141M-R01-2	140	600	
GTCC23-151M-R01-2	150	600	
GTCC23-201M-R01-2	200	700	
GTCC23-231M-R01-2	230	700	
GTCC23-301M-R01-2	300	900	
GTCC23-351M-R01-2	350	1000	
GTCC23-401M-R01-2	400	1000	
GTCC23-421M-R01-2	420	1000	
GTCC23-501M-R01-2	500	1200	

*DCSO 60~105

Part Marking : Not Applicable

Device Surge Rating, Capacitance, Insulation Resistance, UL

Part Number	Insulation Resistance	Capacitance	Impulse Discharge Current 8/20µs			
	@100V _{DC} *	@1Mhz	10 hits (5hits each polarity)	300 hits (150hits each polarity)	10 hits (5 times each polarity)**	UL497B #E179610
GTCC23-xxxM-R01-2	≥ 1,000 (MΩ)	<0.5pF	1kA	100A	4kV	All Devices

* Devices <=150V measured @ 50Vdc

** Effective output impedance: 40ohms



GTCC23-XXXM-R01-2 Series **Product Dimensions** DIMENSIONS = MILLIMETERS [INCHES] Surface-mount (GTCC23-XXXM-R01-2) 2,7±0,2 0.5 0.5 4.5±0.3 3.2±0.2 Pad Layout - Surface- mount Devices (GTCC23-XXXM-R01-2) Х Υ **Z1** Ζ2 NOM NOM NOM NOM 3.5 2.0 2.0 mm: 2.7 in*: (0.138)(0.106)(0.079)(0.079)*Rounded off approximation Z1 Z2 **General Characteristics** No Radioactive Material Storage Temperature: -40°C to +90°C Operating Temperature: -40°C to +90°C Electrode: Tin Plated **Materials Information ROHS Compliant ELV Compliant Pb-Free Halogen Free*** Directive 2002/95/EC Directive 2000/53/EC HF Compliant Compliant

© 2016 Littelfuse,Inc. Specifications are subject to change without notice Revised July 26,2016. Document: SCD27776 Status: RELEASED Rev: G Date: JULY 26, 2016



GTCC23-XXXM-R01-2 Series

Packaging Information

Part Description	Reel	Standard Package
Surface-mount: GTCC23-XXXM-R01-2	2000pcs (Reel)	16,000pcs

Packaging Information





1			DIMENSION	I IN	MM		
W	16.00±0.30	P	8.00±0.10	AO	3.40±0.10	BO	5.00±0.10
s		PO	4.00±0.10				
E	1.75±0.10	P2	2.00±0.10				
F	7.50±0.10	DO	\$1.50±8.10	KO	3.30±0.10		
т	0.35±0.05	D1	<u> </u>			CC	LOR : B



GTCC23-XXXM-R01-2 Series

Part Numbering System

Example Part Number: GTCC23-351M-R01-2

- GT = Gas Tube
- C = Ceramic
- C = Lead Configuration: **C**= Chip Type
- 2 = 2 Electrode device
- 3 = 3mm Diameter
- 351 = DC Spark Over Voltage of 350V (at 100V/s)
- M = Tolerance of 20% on DC Spark Over Voltage
- R = Product Family Designator
- 01 = Surge rating: 8x20µs 1kA 10 times
- -2 = Tape and Reel Packaging

Littlefuse products are not designed for, and shall not be used for, any purpose (including, without limitation, automotive, military, aerospace, medical, life-saving, life-sustaining or nuclear facility applications, devices intended for surgical implant into the body, or any other application in which the failure or lack of desired operation of the product may result in personal injury, death, or property damage) other than those expressly set forth in applicable Littelfuse product documentation. Warranties granted by Littelfuse shall be deemed void for products used for any purpose not expressly set forth in applicable Littelfuse documentation. Littelfuse shall not be liable for any claims or damages arising out of products used in applications not expressly intended by Littelfuse as set forth in applicable Littelfuse documentation. The sale and use of Littelfuse products is subject to Littelfuse Terms and Conditions of Sale, unless otherwise agreed by Littelfuse.