

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Plug-in power solid-state relay, with LED and protective circuit in input and output circuits, input: 24 V DC, output: short-circuit-proof, 10 - 30 V DC/max. 2 A, can be plugged into basic terminal blocks

The illustration shows version ST-OV 3- 5 DC/24 DC/2

Product Features





Key commercial data

| Packing unit | 1 pc |
|--------------------------------------|-----------------|
| GTIN | 4 017918 079338 |
| Weight per Piece (excluding packing) | 30.23 GRM |
| Custom tariff number | 85364190 |
| Country of origin | Germany |

Technical data

Note

| Utilization restriction | EMC: class A product, see manufacturer's declaration in the download area |
|-------------------------|---|
| | |

Dimensions

| Width | 20.8 mm |
|--------|---------|
| Height | 33 mm |
| Depth | 66.5 mm |

Ambient conditions

| Ambient temperature (operation) | -20 °C 60 °C |
|---|--------------|
| Ambient temperature (storage/transport) | -20 °C 70 °C |



Technical data

Input data

| Nominal input voltage U_N | 24 V DC ±20 % |
|---|--------------------------------------|
| Switching threshold "0" signal, voltage | ≤ 6.9 V |
| Switching threshold "1" signal voltage | ≥ 8.5 V |
| Typical input current at U_N | 5 mA |
| Typical response time | 17 µs |
| Typical turn-off time | 104 µs |
| Status display | Yellow LED |
| Type of protection | Protection against polarity reversal |
| | Surge protection |
| Protective circuit/component | Polarity protection diode |
| Transmission frequency | 1000 Hz |

Output data

| Output voltage range | 10 V DC 30 V DC |
|--|---|
| Limiting continuous current | 2 A (see derating curve) |
| Peak offstate voltage | 35 V DC (Collector-emitter reverse voltage) |
| Voltage drop at max. limiting continuous current | 1.5 V |
| Output circuit | 3-conductor, ground-referenced |
| Status display | LED red |
| Type of protection | Protection against polarity reversal |
| | Free running |
| Protective circuit/component | Polarity protection diode |
| | Damping diode |

General

| Test voltage input/output | 2.5 kV AC |
|---------------------------|--------------|
| Mounting position | any |
| Standards/regulations | DIN VDE 0110 |

Classifications

eCl@ss

| eCl@ss 4.0 | 27371102 |
|------------|----------|
| eCl@ss 4.1 | 27371102 |
| eCl@ss 5.0 | 27371001 |
| eCl@ss 5.1 | 27371001 |
| eCl@ss 6.0 | 27371001 |
| eCl@ss 7.0 | 27371001 |



Classifications

ETIM

| ETIM 2.0 | EC001504 |
|----------|----------|
| ETIM 3.0 | EC001504 |
| ETIM 4.0 | EC001504 |
| ETIM 5.0 | EC001504 |

UNSPSC

| UNSPSC 6.01 | 30211916 |
|---------------|----------|
| UNSPSC 7.0901 | 39121542 |
| UNSPSC 11 | 39121542 |
| UNSPSC 12.01 | 39121542 |
| UNSPSC 13.2 | 39121542 |

Approvals

Approvals

Approvals

EAC / EAC

Ex Approvals

Approvals submitted

Approval details

EAC

EAC

Drawings

05/06/2015 Page 3 / 5





Circuit diagram







Phoenix Contact 2015 $\ensuremath{\mathbb{C}}$ - all rights reserved http://www.phoenixcontact.com