



QT-Brightek Chip LED Series

0805 IR LED

Part No.: QBLP630-IR3

| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 1 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

Table of Contents:

| Introduction | 3 |
|--|---|
| Electrical / Optical Characteristic (Ta=25 °C) | 4 |
| Absolute Maximum Rating | 4 |
| Characteristic Curves | |
| Solder Profile & Footprint | 6 |
| Packing | 7 |
| Labeling | 8 |
| Ordering Information | 8 |
| Revision History | 9 |
| Disclaimer | |
| | |

| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 2 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

QBLP630-IR3

Introduction

Feature:

- Water clear lens
- Package in tape and reel
- 0805 Package
- AlGaAs technology
- Viewing Angle = 140 deg

Description:

This 0805 IR LED has a height profile of 1.1mm. With a small footprint, this IR LED is ideal for smaller equipment and miniature application.

Application:

- Infrared Sensor
- Optoelectronic Switch
- Smoke detector
- Drive sensor

Certification & Compliance:

- TS16949
- ISO9001
- RoHS Compliant



Dimension:



| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 3 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

Electrical / Optical Characteristic (Ta=25 °C)

| Product | Color | L (m A) | V _F (V) | | | λ _P (nm) | | l | e (mW/s | r) | |
|---------|------------|----------|---------------------|------|------|---------------------|------|------|---------|------|------|
| | Floadel | COIDI | I _F (mA) | Тур. | Max. | Min. | Тур. | Max. | Min. | Тур. | Max. |
| QE | BLP630-IR3 | Infrared | 20 | 1.3 | 1.8 | - | 850 | - | 0.1 | 0.6 | 1.6 |

Absolute Maximum Rating

| Material | P _d (mW) | I _F (mA) | I _{FP} (A)* | V _R (V) | Т _{оР} (°С) | Т _{sт} (°С) | T _{SOL} (°C)** |
|----------|---------------------|---------------------|----------------------|--------------------|----------------------|----------------------|-------------------------|
| AlGaAs | 90 | 50 | 1 | 5 | -40 ~ +80 | -40 ~ +85 | 260 |

*Duty cycle=1%, Pulse width 100us

**IR Reflow for no more than 10 sec @ 260 °C

| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 4 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

QBLP630-IR3

Characteristic Curves



| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 5 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

Solder Profile & Footprint

-Recommended tin solder specifications: melting temperature in the range of 178~192 ^OC -The recommended reflow soldering profile is as follows (temperatures indicated are as measured on the surface of the LED resin):





| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 6 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |



Packing

Reel Dimension:



Unit: mm

Tape Dimension:



Arrangement of Tape:



Packaging Specification:



| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 7 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

Labeling

| 😥 QT-Brightek 🔮 |
|----------------------|
| Part No: |
| <u>Customer P/N:</u> |
| Item: |
| Q'ty: |
| <u>Vf:</u> |
| <u>lv:</u> |
| <u>VVI:</u> |
| Date: |
| Made in China |

Ordering Information

| Part # | Orderable Part # | Spec Range | Quantity per reel |
|-------------|------------------|--|-------------------|
| QBLP630-IR3 | QBLP630-IR3 | le=0.6mW/sr typ. @ I_F =20mA / λ_P =850nm typ. | 3,000 units |

| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 8 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |

Revision History

| Description: | Revision # | Revision Date |
|----------------------------|------------|---------------|
| New Release of QBLP630-IR3 | V1.0 | 02/09/2015 |
| Update le spec | V1.1 | 05/04/2015 |
| | | |
| | | |
| | | |

Disclaimer

QT-BRIGHTEK reserves the right to make changes without further notice to any products herein to improve reliability, function or design. QT-BRIGHTEK does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under its patent rights, nor the rights of others.

Life Support Policy

QT-BRIGHTEK's products are not authorized for use as critical components in life support devices or systems without the express written approval of QT-BRIGHTEK. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.

2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

| Product: QBLP630-IR3 | Date: May 04, 2015 | Page 9 of 9 |
|----------------------|--------------------|-------------|
| | Version# 1.1 | |