

Sound Level CalibratorModel **R8090**



TECHNICAL DATA

Features

- Generates stable acoustic signal at a controlled frequency and amplitude to verify sound level meter accuracy
- Accommodates sound meters with 1/2" diameter microphones
- Simply place calibrator on microphone, turn on and adjust your sound level meter
- Complies with IEC 942 Class 2
- Includes battery

Specifications

Output Sound Pressure: 2 levels (94dB and 114dB)

Accuracy: ±0.5dB

Output Frequency: 1000Hz ±4% Power Supply: 9V Battery

Product Certifications: CE

Operating Temperature: 32 to $104^{\circ}F$ (0 to $40^{\circ}C$) Storage Temperature: -4 to $140^{\circ}F$ (-20 to $60^{\circ}C$)

Operating Humidity: O to 80% Dimensions: 4.7 x 2 x 1.7"

(120 x 51 x 43 mm)

Weight: 4.6oz (130g)

Model	Description
R8090	Sound Level Calibrator
R8090-NIST	Sound Level Calibrator & NIST

