#### SAFETY ORGANIZATIONS

THIS FILTER HAS BEEN FORMALLY RECOGNIZED, CERTIFIED OR APPROVED BY THE LISTED AGENCY. THEREFORE, ALL TEST/REQUIREMENTS SPECIFIED IN THE LATEST REVISION OF THE FOLLOWING AGENCY STANDARDS HAVE BEEN MET:

UL RECOGNIZED: UL 1283 CSA CERTIFIED: CSA 22.2, # 8 VDE APPROVED: EN133200

#### OPERATING SPECIFICATIONS

LINE CURRENT/VOLTAGE: 3 AMP, 120/250 VAC,

3 AMP/40°C, 250 VAC

LINE FREQUENCY: 50-60Hz

MAXIMUM LEAKAGE CURRENT,

EACH LINE TO GROUND: µA @120V 60Hz µА @ 250V 50Hz

OPERATING AMBIENT TEMP. RANGE: -10°C TO +40°C @ RATED CURRENT, Ir.

IN AN AMBIENT, T<sub>0</sub>, HIGHER THAN 40°C, THE MAXIMUM OPERATING CURRENT, I<sub>0</sub>, IS AS FOLLOWS: I<sub>0</sub> = I  $_{\infty}$   $_{\infty}$   $_{\infty}$   $_{\infty}$   $_{\infty}$   $_{\infty}$ 

 $I_0 = I_r - \sqrt{85 - I_0}$ 

## RELIABILITY SPECIFICATIONS

STORAGE TEMPERATURE: -40°C TO +85°C HUMIDITY: 21 DAYS @ 40°C 95% RH. CURRENT OVERLOAD TEST: 6 TIMES In FOR 8 SECONDS

# TEST SPECIFICATIONS:

INDUCTANCE: 10.0 mH NDMINAL CAPACITANCE: (MEASURED @ 1KHz, 0.250VAC MAX., 25°C±1°C)

NDNE μF 0.1014 μF ±20% LINE TO GROUND: I THE THITTE: DISCHARGE RESISTOR: 1.5M ∧

L/G AND L/L I.R.

6000M₁ (MIN.) @ 100VDC, ND DISCHARGE RESISTOR:

20°C AND 50% RH


## RECOMMENDED RECEIVING INSPECTION HIPOT:


LINE TO GROUND: 1500 VAC OR 2250 VDC FOR 1 MINUTE


LINE TO LINE: 1450 VDC FOR I MINUTE

#### FILTER APPROVAL:

THE BEST WAY TO SELECT AND QUALIFY A FILTER IS FOR YOUR ENGINEERING TO TEST THE UNIT IN YOUR EQUIPMENT.








0.250 FASTON WITH 0.069 X 0.155 SLOT

CATALOG # 3EJHS1


0631-0171-04

EC APPRVD. DATE

12N0V04




#### PUNCH PANEL FROM OUTSIDE



PANEL CUTOUT (FRONT MOUNT)

| PANEL THICKNESS | PANEL CUTOUT "A" |
|-----------------|------------------|
| 0.031-0.052     | 1.260            |
| 0.046-0.068     | 1.350            |



## \* RESISTOR LOCATION OPTIONAL

| 50A- 50A(MINIMUM) INSERTION LOSS |      |      |      |      |      |    |    |    |    |  |
|----------------------------------|------|------|------|------|------|----|----|----|----|--|
| FREQUENCY<br>MHz                 | . 01 | . 05 | . 10 | . 15 | . 50 | 1  | 5  | 10 | 30 |  |
| COMMON<br>dB                     | -    | 9    | 15   | 19   | 27   | 31 | 30 | 26 | 20 |  |
| DIFF.<br>dB                      | 5    | 8    | 17   | 23   | 25   | 31 | 32 | 30 | -  |  |

THIRD ANGLE PROJECTION



*tyco | Electronics* **B**corcom 844 E. ROCKLAND RO. LIBERTYVILLE IL 60048

POWER LINE FILTER

MATERIAL & FINISH: AS SUPPLIED This document is proprietary to  $\overline{\text{CORCOM INC}}$ and is not to be reproduced nor used for manufacturing purposes except on CDRCDM'S prior written consent.

TOLERANCE TO BE ±.025

| CAD FILE:  G:` |          | TYCO # 1-1609008-7 |     |
|----------------|----------|--------------------|-----|
| SCALE: NITS    | DATE:    | CATALOG NO.        | REV |
| N12            | 11-12-04 | 0.0.11104          | _   |
| DRW. BY:       | ORIG:    | 3EJHS1             | U   |
| DZ             | ELC      |                    | _   |