For Reference

Number: G6A-0903024B

Date of Issue: Nov. 10. 2011

OMRON Corporation

OMRON Relay & Devices Corporation
Prepared by | Checked by | Authorized by |

Y. SUGA T. ASO T. MATSUSHITA

PRODUCT SPECIFICATIONS

Name: MINI RELAY

Model: G6A-2-H

Item: DC ALL

Registration part number for Customer	
Type name: Type number:	
Receipt Stamp(For receipt purpose only)	
	Handled by
	114114100 2)
Please accept handling of this specification sheet as for	
reference use if no reply received.	

Distribution

Revision Record

	Сору
Customer	
Sales()	

Mark	Date	Contents

P. 2

```
1. Classification
                                Single stable relay
2. Construction
 2.1 Outline dimensions
                                Drawing No. 2479484-3
                                Drawing No. -----
 2.2 Structure drawing
                                DPDT (2c contact)
 2.3 Contact configuration
 2.4 Contact structure
                                Twin crossbar contact
 2.5 Contact material
                                Face material
                                                Au Alloy
                                Base material
                                                Αg
 2.6 Protective construction Plastic sealed
3. Standards
 3.1 Approved by standard(s) UL
                                           File No.
                                                       : E41515
                                CSA
                                           File No.
                                                        : LR31928
                                FCC Part68
 3.2 Others
4. Ratings
 4.1 Coil ratings See table 1
 4.2 Contact ratings
                       (1) Rated load
                       Inductive load 125VAC 0.3A
                                        (p. f. = 0.4)
                                       30 VDC 1A
                                        (L/R = 7 \text{ ms})
     (2) Rated carry current
                                 3 A
     (3) Maximum rated voltage
                                250 VAC 220VDC
     (4) Maximum rated current
                       Resistive load AC2A DC2A
                       Inductive load AC1A
                                       (p. f. = 0.4)
DC1A
                                        (L/R = 7 \text{ ms})
     (5) Maximum switching capacity
                                       AC125VA DC60W
AC62.5VA
                       Resistive load
                       Inductive load
                                        (p. f. = 0.4)
DC 3 0 W
                                        (L/R = 7 \text{ ms})
     (6) Failure rate (reference value)
                              DC 1 0 mV 1 0 \mu A (P level) (\lambda 60=0.1×10<sup>-6</sup> /ops.)
5. Characteristics (initial value)
 5.1 Contact resistance
                          50 \text{ m} \Omega MAX.
                           Measured by the voltage drop method with
                           DC1V 10mA applied
 5.2 Must operate voltage (or set voltage)
                                               See table 1
                                               See table 1
 5.3 Must release voltage (or reset voltage)
 5.4 Operate time (or set time) 5 ms MAX. (at rated voltage) 5.5 Release time (or reset time) 3 ms MAX. (at rated voltage)
                                 --- ms
 5.6 Minimum input pulse width
     (Applicable to latching relay only, at rated voltage)
```

5.7 Insulation resistance 500VDC (1) Between coil terminals and contact terminals 1 0 0 0 M Ω MIN. (2) Between non-continuous current-carrying contact terminals 1 0 0 0 M Ω MIN. (3) Between contact terminals of the same polarity 1 0 0 0 M Ω MIN. (4) Between set coil and reset coil ---- M Ω MIN. (5) Between current-carrying terminal and exposed non-current currying metal part. ---- M Ω MIN. 5.8 Dielectric strength(leakage current 1 mA 50/60Hz for a minute) (1) Between coil terminals and contact terminals AC1000 V (2) Between non-continuous current-carrying terminals AC1000 V (3) Between contact terminals of the same polarity AC750 V AC---- V (4) Between set coil and reset coil (5) Between current-carrying terminal and exposed non-current carrying metal part. AC ----V5.9 Temperature rise (1) Coil 6 5 °C MAX. (by the coil resistance method) at ---°C Applied voltage of coil: 100% of rated voltage -- Hz Carry current of contact 3 A (2) Contact 6 5 °C MAX. (by the thermometer method) at --°C Applied voltage of coil: 100% of rated voltage ---Hz Carry current of contact 3 A 5.10 Vibration (1) Mechanical durability Must be free from any abnormality in both

Must be free from any abnormality in both the construction and characteristics after the relay is subjected to a variable vibration of 2.5mm single amplitude (5mm double amplitude) at a vibration frequency of 10-55-10 Hz in each direction for 2 hours.

(2) Malfunction durability
(When energized)
or set status

Contacts must not open for $1\,\mathrm{ms}$ or longer after the relay is subjected to a variable vibration of $1.65\,\mathrm{mm}$ single amplitude (3.3mm double amplitude) at a vibration frequency of 10-55-10 Hz in each direction for $1\,\mathrm{cycle}$.

(When not energized) or reset status

Contacts must not open for 1 ms or longer after the relay is subjected to a variable vibration of 1.65mm single amplitude (3.3mm double amplitude) at a vibration frequency of 10-55-10 Hz in each direction for 1 cycle.

5.11 Shock

(1) Mechanical durability

Must be free from any abnormality in both the construction and characteristics after the relay is subjected to a shock of $1~0~0~m/s^2$ in each direction 3~times.

(2) Malfunction durability (When energized) or set status

Contacts must not open for 1 ms or longer after the relay is subjected to a shock of 500 m/s^2 in each direction

(When not energized) or reset status

Contacts must not open for 1 ms or longer after the relay is subjected to a shock of 5 0 0 m/s $^{\!2}$ in each direction 3 times.

5.12 Terminal strength

Must be free from any abnormality after a tensile stress of 4.9N is applied to the terminal in any direction vertical to the terminal tip for 10 seconds. Any deformation of the terminal by the load shall not be regard as a mechanical damage.

5.13 Temperature resistance (1) Heat resistance

Must be free from any abnormality in both the construction and characteristics after the relay is left in a temperature of $85 \pm 2^{\circ}$ C for 16 hours and then in room temperature and humidity for 2 hours.

(2) Cold resistance

Must be free from any abnormality in both the construction and characteristics after the relay is left in a temperature of -5.5 ± 3 °C for 72 hours and then in room temperature and humidity for 2 hours.

5.14 Moisture resistance

Must be free from any abnormality in both the construction and characteristics after the relay is left in a humidity of 90 to 95% RH for 48 hours at a temperature of $40\pm2^{\circ}\text{C}$, and then in room temperature and humidity for 2 hours.

Insulation resistance, however, must be 5 $\,M\,\Omega\,$ MIN.

5.15 Soldering heat

The product shall be free from any abnormality in both the construction and characteristics after the terminals are dipped into molten solder at $2.6.0 \pm 5$ °C for 1.0 seconds and then left in room temperature and humidity for 2 hours or after mounted by the recommended condition of temperature profiles shown in item ---.

5.16 Endurance

(1) Mechanical endurance

100,000,000 operations MIN.

(under no load at operating frequency of

36,000 operations/hour) 100,000 operations MIN.

(2) Electrical endurance

(under rated load, at operating frequency of 1,800 operations/hour)

lphaUnless otherwise specified, the above mentioned item 4 (Ratings) and 5 (Characteristics) values are under the standard conditions of Ambient temperature 23°C and Humidity 65%RH.

P. 5

6. Storage conditions

- (1) Store in locations in normal temperature, humidity and atmosphere pressure.
- (2) Environments
 - •Store in locations where the product or container is not exposed to corrosive gas such as hydrogen sulfide gas or salty air.
 - ·Store in locations where no visible dust exists.
 - •Store in locations where the product is not exposed to the direct ray of the sun and rain, snow.

Also please do not apply the force to product which may result in the deformation or a change in quality of the product.

7. Operating conditions Use the product under the following conditions.

7.1 Ambient temperature $-40 \text{ to } +70 \text{ }^{\circ}\text{C}$

(without freezing or condensation)

7.2 Relative humidity 5 to 85 % R H

7.3 Mounting direction Free

7.4 Environments

- (1) Use in locations where the product is not exposed to corrosive gas such as hydrogen sulfide gas or salty air.
- (2) Use in locations where no visible dust exists.
- (3) Use in locations where the product is not exposed to the direct ray of the sun and rain, snow.

 Also please do not apply the force to product which may result in the deformation or a change in quality of the product.
- 8. Others
 - 8.1 Weight Approx. 3.5g
 - 8.2 Impulse withstand voltage (at $10 \times 160 \,\mu$ s)
 Between coil and contact 1500V
 Between non-continuous contact ---Between continuous contact ----

9. PRECAUTIONS

(1) Following terms are defined as below.

1) Conditions; Use conditions, rating, performance, operating environment, handling procedure, precautions and/or prohibited use described in this "product specifications", documentations or manuals

2) User Application; Application of this product by a customer, including but not limited to embedding this product into customer's components, electronic circuit boards, devices, equipments or systems

3) Fitness; (a) Fitness, (b) performance, (c) no infringement of intellectual property of third party, (d) compliance with laws and regulations and (e) conformity to various standards

(2) Note about this specification

- 1) The product may be discontinued or change its specification without prior notice, unless the specification is not returned or the product is not ordered within one year after issue of this specification. Please confirm current specifications if you return this specification or you place an order of this product one year after issue of this specification.
- 2) Rating and performance is tested separately. Combined conditions are not warranted.
- 3) Reference data is intended to be used just for reference. Omron does not warrant that the product can work properly in the range of reference data.
- 4) Examples are intended for reference. Omron does not warrant the fitness in usage of the examples.
- 5) Omron may, at its discretion, change factors other than rating, performance, structure, outside dimensions or mounting dimensions.

(3) Note about adoption and use

- 1) Please use the product in conformance to the conditions, including rating and performance.
- 2)Please confirm the fitness and decide whether or not the product is able to be adopted in User Application.
- 3) Omron will not warrant any items in (1) 3) (b) \sim (e) of User Application nor the fitness.
- 4) If you use the product in the application below, please ensure followings; (i) allowance in aspect of rating and performance, (ii) safety design which can minimize danger of the User Application when the product does not work properly and (iii) periodical maintenance of the product and the User Application.
- (a) Applications requiring safety, including, without limitation, nuclear control facilities, combustion facilities, aerospace and aviation facilities, railroad facilities, elevating facilities, amusement facilities, medical facilities, safety devices or other applications which has possibility to influence lives or bodies
- (b) Applications requiring high reliability, including, without limitation, supplying systems of gas, water and electric power and applications handling right, title, ownership or property, such as payment systems
- (c) Applications in a harsh condition or environment, including, without limitation, outdoor facilities, facilities with potential of chemical contamination or electromagnetic interference, facilities with vibration or impact and facilities on continual operation for a long period
- (d) Applications under conditions or environment which are not described in this specification
- 5) This product is not intended to be used in automotive applications (including two wheel vehicles). Please do not use this product in the automotive application.

P. 7

- (4) Warranty
 - 1) Warranty period; One year after your purchase
 - 2) Warranty; Omron will provide, free of charge, replacements of the same number of malfunctioning products
 - 3) Exceptions; This warranty does not cover malfunctions caused by any of the following.
- (a) Usage in the manner other than its original purpose
- (b) Usage out of the condition
- (c) Cause which could not be foreseen by the level of science and technology at the time of shipment of the product
- (d) Cause outside Omron or the product, including force majeure such as disasters
- (5) The warranty described in this "conditions" is a whole and sole liability for the products. There are no other warranties, expressed or implied. Omron and distributors are not liable for any damages arisen from or relating to the products.
- (6) Please comply with laws and regulations of security trade control in relevant countries if you export or provide a nonresident with the product or technical information.

	_	~		/	. \
1	().	Coil	rating	(table	1)

Rated voltage (V)	Rated current (m A)	Coil resistance (Ω)	Must operate voltage	Must release voltage	Rated power consumption (mW)	Maximum Voltage
D C 1.5	132.7	11.3	Ü	J		
DC 3	66.7	45				
DC 4.5	44.6	101	70%max	10%min		200%
DC 5	40.0	125	of rated	of rated	Approx. 200	of rated voltage
DC 6	33.3	180	voltage	voltage		(at23℃)
DC 9	22.2	405				
DC 12	16.7	720				
DC 2 4	8.3	2880				
DC48	4.9	9750			Approx. 235	

- 1: The rated current and coil resistance are measured at a coil temperature of 23°C with a tolerance of $\pm 10\%$
- 2: Operating characteristics are measured at a coil temperature of 23°C.
- 3: The maximum coil voltage refers to the maximum value in a varying range of operating power voltage.

1 1. Handling precautions

- 1: Please avoid micro-wave washing not to cause the internal which cause coil wire cutting and sticking of the contact.
- 2: Don't give the relay dropping shock to keep initial performance.
- 3: The relay mounted on the PCB may be coated or washed but do not apply silicone coating or detergent coating silicone, otherwise the silicone coating or detergent may remain on the surface of the relay.
- 4: If wash the product after soldered the relay on PCB, please use water-based solvent or alcohol-based solvent. At that time, please keep the solvent temp. less than 40 degree C. Do not put the relay in a cold cleaning bath immediately after soldering.

5: In case that load is cut to two and switched in the contact of 2 pole as shown in the figure below, the 1 and 2 pole-between mechanically becomes MBB(Make Before Break) because of the timing-gap of the two contacts in switching, and the miss-operation might be caused (by the short-circuit mode).



