

0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz

VSWR

RF Variable Attenuators Datasheet

Features

- 30dB Attenuation Level
- Rotary Dial Design for Continuous Adjustment
- Frequency Range from 12.4GHz to 18GHz

Applications

- InstrumentationPrecision Measurements
- Prototyping and Characterization
- Production Systems

Description

Pasternack's PE7435-30 is a continuously variable attenuator that has 30 dB of total attenuation with rotary dial design for continuous attenuation level adjustment across a frequency range from 12.4 to 18GHz. With SMA female connectors, this RF variable attenuator design is tried and true technology that offers exceptional RF performance characteristics that include 1 dB maximum insertion loss and a maximum VSWR of 1.6:1. Continuously variable attenuators are part of Pasternack's comprehensive RF attenuator product offerings which are available in stock and ready for same-day shipment.

Configuration

Design Body Material and Plating Continuously Variable Attenuator Aluminum

SMA Female Connectorized Design

Max Power Rating: 5W (CW)

• Max VSWR 1.6:1

Electrical Specifications Values at 25°C, sea level

Minimum	Typical	Maximum	Units
12.4		18	GHz
	50		Ohms
	0 to 30		dB
		5	Watts
		3	kWatts
		1	dB
		1.6:1	
		12.4 50	12.4 18 50 0 to 30 5 3 1 1

Mechanical Specifications

Operating Range	-40 to +85 deg C
Size Length Width Height	3.07 in [77.98 mm] 1.99 in [50.55 mm] 0.5 in [12.7 mm]
Weight	0.19 lbs [86.18 g]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz PE7435-30

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com

PE7435-30



0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz



RF Variable Attenuators Datasheet

PE7435-30

Connectors

Description	Connector 1	Connector 2
Туре	SMA Female	SMA Female
Contact Material and Plating	Beryllium Copper, Gold	Beryllium Copper, Gold
Body Material and Plating	Brass, Nickel	Brass, Nickel

Compliance Certifications (see product page for current document)

Plotted and Other Data

- Notes:
- Values at 25 °C, sea level

0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: 0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz PE7435-30

URL: https://www.pasternack.com/30db-continuously-variable-sma-female-sma-female-5-watts-attenuator-pe7435-30-p. aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

PE7435-30 CAD Drawing

0 to 30 dB Variable Attenuator, SMA Female to SMA Female Rated to 5 Watts from 12.4 GHz to 18 GHz

