# ioLogik 2500 Series

## -Smart remote I/O with Click&Go Plus Logic



- > New Click&Go Plus logic provides powerful front-end intelligence
- > 4-port unmanaged switch built in for linking to Ethernet devices
- > Optimized I/O expansion port for daisy chaining up to 8 ioLogik E1200 units
- > 2 serial ports (RS-232/422/485) for connecting field devices
- > Built-in datalogger supports an FTP server and microSD™ card with up to a 32 GB
- > Transforms Modbus RTU into Modbus TCP or Active Tags
- > Active communication with patented MX-AOPC UA Server
- > Smart alarm management: Email, SNMP traps, TCP, UDP
- > Wide operating temperature: -40 to 75°C (-40 to 167°F)

## : Introduction

The ioLogik 2500 is a smart remote I/O product with unique hardware and software designs, making it an ideal solution for a variety of industrial data acquisition applications.

The ioLogik 2500's hardware design includes a 4-port unmanaged Ethernet switch and 2 serial ports, enabling the ioLogik 2500 to seamlessly connect to a variety of field devices. One of the Ethernet ports can be used to link to 8 daisy-chained ioLogik E1200 expansion

## Powerful Control Logic from the New Click&Go Plus™

The new Click&Go Plus<sup>™</sup> control logic now supports up to 48 rules with further upgrades to 8 conditions/actions. In addition, its graphical user interface provides 3 logic gates and 3 multi-layers, helping you build more powerful and efficient IO solutions.

Once you finish setting up your Click&Go Plus<sup>™</sup> logic rules, IOxpress's easy-to-use simulation function can be used to find potential errors in your Click&Go Plus<sup>™</sup> rules before uploading them to your online devices.

modules to provide more than 100 channels. The ioLogik 2500 acts as the "head" unit, with Click&Go Plus logic used to control the entire I/O array. Most importantly, the ioLogik 2500's single IP is all that's required to connect the entire I/O array to your network, providing the perfect solution for industrial field sites that have an insufficient number of IP addresses.

Peer-to-peer (P2P) mode is widely used for industrial applications. Traditionally, you would need to use P2P devices on both sides of the connection. However, if a configuration mismatch occurred between the P2P devices, the P2P connection would fail, after which you would need to spend extra time and effort to check the P2P settings. With IOxpress, all you need to do is set up the output device, and the P2P connection will be established automatically.

## One IP for Multiple Expansion I/Os Gives You a Smarter Data Acquisition Solution

The ioLogik 2500's unique IO expansion hardware design lets you link up to 8 ioLogik E1200 modules into a versatile I/O array with 100+ different I/O channels. The ioLogik 2500 acts as the perfect "head" unit, using Click&Go Plus logic to control the entire I/O array, and providing a single IP to connect the entire I/O array to your network.

#### User-Friendly IOxpress with Offline/Online Configuration for Easy Device Management

IOxpress integrates a user-friendly interface with offline/online configuration, allowing you to configure every I/O parameter offline,

and then upload the settings to your online devices, greatly reducing the time and cost needed to manage and configure your IO solutions.

#### Powerful Datalogger and Value-added MODBUS Gateway

The ioLogik 2500 supports micro SD cards with up to 32 GB of memory, turning the ioLogik into a powerful datalogger for storing valuable data. And with a built-in FTP server, important data from field sites can be accessed remotely by different systems. In addition,

#### New MX-AOPC UA Server Efficiently Reduces System Response Time

The new MX-AOPC UA supports both UA server and DA server types. MX-AOPC UA server has a number of strengths. UA server provides a standard, state of the art security model, assuring your system's security, and supports communication channels via the standard UA TCP port. This means that messages can be relayed through third party proxies. In addition, configuring the firewall is be easier, since you won't need to worry about DCOM settings. the 2 serial communication ports can be used to input data from devices using the Modbus RTU protocol, and then transform the data into Modbus TCP or AOPC tag format before sending it out over the Ethernet network.

In addition, MX-AOPC supports both the traditional Modbus protocol and Moxa's patented Push type communication. Unlike the traditional passive "pull" method, "active" messages are automatically "pushed" from the ioLogik 2500 to the SCADA system when the I/O state changes or pre-configured events occur. In this way, information can be accurately and efficiently pushed to the SCADA system as it becomes available.



## ioLogik 2512 Specifications

**Inputs and Outputs** Digital Inputs: 8 channels Configurable DI/Os: 8 channels Isolation: 3k VDC or 2k Vrms **Digital Input** Sensor Type: Wet Contact (NPN or PNP) and Dry Contact Input Leakage Current: < 1 mA (@ 30 VDC) I/O Mode: DI or Event Counter **Dry Contact:** • On: short to GND • Off: open Wet Contact (DI to COM): • On: 10 to 30 VDC • Off: 0 to 3 VDC Common Type: 8 points per COM Counter Frequency: 2.5 kHz Digital Filtering Time Interval: Software configurable

#### **Digital Output**

Type: Sink I/O Mode: DO or Pulse Output Pulse Output Frequency: 5 kHz Over-voltage Protection: 45 VDC Over-current Protection: 1.5 A per channel @ 25°C Over-temperature Shutdown: 175°C (min.) Current Rating: 500 mA per channel @ 25°C

## ioLogik 2542 Specifications

**Inputs and Outputs** Analog Inputs: 4 channels Configurable DI/Os: 12 channels Isolation: 3k VDC or 2k Vrms **Analog Input** Type: Differential input Resolution: 16 bits I/O Mode: Voltage / Current (software selectable) Input Range: ±10 V. 0 to 10 V. 0 to 20 mA. 4 to 20 mA (with burn-out detection) Accuracy: • ±0.1% FSR @ 25°C • ±0.3% FSR @ -10 and 60°C • ±0.5% FSR @ -40 and 75°C Sampling Rate: All channels: 400 samples/sec • Per channel: 100 samples/sec Input Impedance: > 1M ohms (min.) Built-in Resistor for Current Input: 120 ohms

#### **Common Specifications**

## I AN

Ethernet:

• 4 switched 10/100 Mbps RJ45 ports • 1 optimized port for faster downstream communications with daisv-chained ioLogik E1200 units Note: The optimized daisy-chain port is not supported on wind industry devices (ioLogik E1261W-T, E1261H-T, or E1263H-T). Protection: 1.5 kV magnetic isolation Protocols: Modbus/TCP, TCP/IP, UDP, DHCP, BOOTP, SNMP, HTTP, CGI, SNTP, SMTP Serial Communication Serial Ports: 2, RJ45, 3-in-1 interface Protocols: Modbus/RTU (master), serial tunnel mode (client/server) Serial Line Protection:  $\geq$  8 kV ESD for all signals Serial Communication Parameters Parity: None, Odd, Even Data Bits: 5, 6, 7, 8 Stop Bits: 1, 1.5, 2 Flow Control: None, RTS/CTS Baudrate: 1200 to 115200 bps Protocol: Modbus/RTU **Power Requirements** Power Input: 24 VDC nominal, 9 to 48 VDC **Physical Characteristics** Wiring: I/O cable max. 14 AWG Mounting: DIN rail, wall Storage Expansion Slot: Up to 32 GB microSD™ memory card (SDHC compatible) Note: For units operating in extreme temperatures, industrial grade, widetemperature SD cards are required. **Environmental Limits Operating Temperature:** Standard Models: -10 to 60°C (14 to 140°F) Wide Temp. Models: -40 to 75°C (-40 to 167°F) Storage Temperature: -40 to 85°C (-40 to 185°F) Ambient Relative Humidity: 5 to 95% (non-condensing) Altitude: Up to 2000 m Note: Please contact Moxa if you require products guaranteed to function properly at higher altitudes.

**Digital Input** Sensor Type: Wet Contact (NPN or PNP) and Dry Contact Input Leakage Current: < 1 mA (@ 30 VDC) I/O Mode: DI or Event Counter **Drv Contact:** • On: short to GND • Off: open Wet Contact (DI to COM): • On: 10 to 30 VDC • Off: 0 to 3 VDC Common Type: 6 points per COM Counter Frequency: 2.5 kHz Digital Filtering Time Interval: Software configurable **Digital Output** Type: Sink I/O Mode: DO or Pulse Output Pulse Output Frequency: 5 kHz Over-voltage Protection: 45 VDC Over-current Protection: 1.5 A per channel @ 25°C Over-temperature Shutdown: 175°C (min.) Current Rating: 500 mA per channel @ 25°C

Standards and Certifications Safety: UL 508, EN 60950-1, NCC EMI: EN 55022; EN 61000-3-2; EN 61000-3-3; FCC Part 15, Subpart B, Class A EMS: EN 55024. EN 61000-4-2. EN 61000-4-3. EN 61000-4-4, EN 61000-4-5, EN 61000-4-6, EN 61000-4-8, EN 61000-4-11, EN 61000-6-2 Radio: FCC Part 22H, FCC Part 24E, EN 301 489-1, EN 301 489-7, EN 301 511 Shock: IEC 60068-2-27 Freefall: IEC 60068-2-32 Vibration: IEC 60068-2-6 Green Product: RoHS, CRoHS, WEEE Note: Please check Moxa's website for the most up-to-date certification status. Warrantv Warranty Period: 5 years Details: See www.moxa.com/warranty



## **Crdering Information**

#### **Available Models**

ioLogik 2512: Ethernet remote I/O with Click&Go Plus, 8 DIs, 8 DI/Os, -10 to 60°C operating temperature ioLogik 2542: Ethernet remote I/O with Click&Go Plus, 4 AIs, 12 DI/Os, -10 to 60°C operating temperature ioLogik 2512-T: Ethernet remote I/O with Click&Go Plus, 8 DIs, 8 DI/Os, -40 to 75°C operating temperature ioLogik 2542-T: Ethernet remote I/O with Click&Go Plus, 4 AIs, 12 DI/Os, -40 to 75°C operating temperature temperature

#### Package Checklist -

- ioLogik 2500 series device
- 2 x RJ45 to DB9 connection cables
- Documentation and software CD
- Hardware installation guide