DSU9H & DSU9X MODELS

Introduction

When an automation system requires a high degree of risk mitigation of failure modes, often times Functional Safety equipment can be a part of the solution. Sensata | BEI Sensors offers a wide range of Functional Safety encoders to fit most any application or electrical interface requirement. Rated at SIL3 (PLe), these encoders allow safe operation in set-up, production and maintenance modes, significantly reducing operational risks. All encoders have the option of a Digital HTL or TTL operation as an alternative to the Sine/Cosine outputs found on most Functional Safety encoders. This makes them a compatible replacement for existing encoders when migrating to a higher safety level of operation. DSU9H & DSU9X offer 30 mm standard through shaft models with optional reduction sleeves for mounting on smaller diameter shafts. The encoder body is 90mm in diameter, available in aluminum or stainless steel.



Features

• Usable up to SIL3 and Cat.4 / PLe according to IEC 61508 / EN ISO 13849

Sensata

Technologies

- Suitable for safe motor feedback according to IEC 61800-5-2
- Especially designed for heavy-duty applications (steel, paper, wood, mills, cranes...) Compact and robust design. Excellent resistance to shock and vibration
- Stainless steel version available (DSU9X)
- 90mm encoder, 30mm standard through shaft, PEEK reduction hub available
- High protection level: IP66 (DSU9X), IP65 (DSU9H)
- High temperature performance –20°C to +85°C
- Power supply 5Vdc or 11/30Vdc
- Digital TTL/RS422 or HTL Push-pull or sine/cosine 1Vpp output
- Available resolution up to 2048 ppr
- Connector or cable output side orientation
- Adapted anti-rotation system

Applications

- Industrial automation
- Automated guided vehicles
- Mills for lumber, steel and other metals
- Printing and packaging equipment
- Food processing equipment
- Forming and die presses



Mechanical

	DSU9H	DSU9X				
Material	Cover: powder coated aluminum Body: aluminum	Cover: AISI 303 stainless steel Body: AISI 303 stainless steel				
	Shaft: AISI 303 stainless steel					
Ball Bearings	6807 - Sealed					
Maximum Landa	Axial: 25 N					
Maximum Loads	Radial: 50 N					
Shaft Inertia	< 120,000 g.mm ² < 125,000 g.mm ²					
Static/Dynamic torque	30 / 300 mN.m 250 / 600 mN.m					



Permissible max. speed	6000 RPM	3000 RPM			
Continuous max. speed	3000 RPM	1500 RPM			
Theoretical mechanical lifetime L ₁₀ h ^(A)	> 18 X 10 ⁹ turns / 100,000 hours	> 9 X 10 ⁹ turns / 100,000 hours			
Encoder weight (approx.)	0.65 kg	1.3 kg			

(A) Continuous max. speed – ½ max. load – according to ISO 281: 1990, L₁₀

Temperature Conditions

Operating temperature	- 20 + 85 °C (encoder T°)			
Storage temperature	- 20 + 85 °C			

Electrical Characteristics / Functional Safety Parameters (B)

Electronic Version	Output signals	Operating Voltage +V	Supply current	Current per channel pair	Short circuit protected	Reverse polarity protected	PFD	PFH	MTTFd	DC		
2G2	Digital TTL	$\frac{5V + -5\%^{(C)}}{250mA}$	100mA		Yes		7.51E-05	8.58E-10	1331			
5G2	RS422		11,001/(6)	11.20\/([)	11.20V(C)	with no	40mA	Not to +V		9.52E-05	1.09E-09	1050
5G5	Digital HTL	250mA	load		Yes	Yes	9.52E-05	1.09E-09	1050	HIGH		
2WT	Sine Cosine	5V +/-5% ^(C) 250mA	70mA	10 4	Yes		4.29E-05	4.90E-10	2328			
5WT	1Vpp	11-30V ^(C) 250mA	with no load	10mA	Not to +V		6.60E-05	7.53E-10	1515			

(B) Safety mission time: 20 years

^(c) UL listed: Device must be supplied by a Class 2, LPS or SELV limited energy source.

Standards Conformity

	DSU9H	DSU9X						
Protection (EN 60529)	IP65 IP66							
Humidity (EN 60068-2-38)	93% @	⊉ 65°C						
Shock (EN 60068-2-27)	≤ 500 m/s	² (during 6 ms)						
Vibration (EN 60068-2-6)	\leq 200 m/s ² ((55 2 000 Hz)						
EMC Immunity Test	EN 61000-6-2,i	ncreased levels						
EMC Emission Test	EN 61000-6-4,i	ncreased levels						
Isolation	1000) Veff						
Salt Spray (EN 60068-2-11 part 2)	96h	168h						
	IEC 61508							
Functional safety	IEC 62061							
runctional salety	ISO 13	ISO 13849-1						
	IEC 61800-5-2							
Encoders usable up to SIL3	/ PLe with external specific requirements, see	safety user manual for details.						
Z and Z/ are not safety signals.								

Electrical Connections

		OV	+V	A or S	B or C	Z	A/ or S/	B/ or C/	Z/	Ground
G6	M23 - 12 pins CW	1	2	3	4	5	6	7	8	Connector body
G8	M23 - 12 pins CCW	10 + 11	2 + 12	8	5	3	1	6	4	Connector body
G3	PVC cable 8 wires 8230/020	WH white	BN brown	GN green	YE yellow	GY grey	PK pink	BU blue	RD red	General shielding
GP	PUR cable 12 wires 8230/050	WH white + WH/GN white /green	BU blue + BN/GN brown / green	GY grey	BN brown	RD red	PK pink	GN green	BK black	General shielding
U3	PVC cable 8 wires	WH	BN	GN	YE	GY	PK	BU	RD	General shield
GC	PUR cable	ВК	RD	GN	BN	VT	YE	OG	BU	General shield
GM	M12 8 pins	1	2	3	4	5	6	7	8	Connector body

Note: All connections are UL certified, except G3 and GP



1024 2048



DSU9H – radial M23 connector









DSU9H - radial cable and 20mm reduction hub



DSU9X- radial M23 connector - IP66 option









Stator coupling kit M9445/045







www.sensata.com

Tether arm kit M9445/046





		9445/045	9445/046	
e nts	Axial	+/5mm	+/- 1mm	
Permissible misalignments	Radial	+/- 0.3mm	+/- 0.2mm	
ermi salig	Perpend.	+/- 3°	+/- 5°	
g. B	Runout	0.1mm	0.1mm	
Angular rigidity		540 N.m/rad	530 N.m/rad	



GENERAL NOTES

For a safe installation according to the required safety level needed in the application, refer to the user safety User Manual. The safety User Manual provides the technical information (drawings, electrical data, etc...) for a safe integration. A quick installation guide is provided with each encoder for use by the technician who installs the device on the equipment.

Page 5



Contact the factory for special versions, ex: resolution, connection, flange...

DSU9X	30 /	01	/ 5G2	9 //	01024 //	GP	R	050 // **	DW **
Family	\top								
DSU9H: Aluminum DSU9X: Stainless									
Shaft									
30: 30mm 58: 1.00in=25.4mm (with reduction hub) 25: 25mm (with reduction hub) 20: 20mm (with reduction hub)									
IP									
Blank: IP65 standard 1: IP66 (available for DSU9X only)									
Voltage Output									
262: 5Vdc, TTL RS422 562: 11- 30Vdc, TTL RS422 565: 11- 30Vdc, HTL 2WT: 5Vdc, Sine 1 Vpp (analog) 5WT: 11- 30Vdc, Sine 1 Vpp (analog)									
Channels									
9: Digital electronics AA/ BB/ ZZ/ B before A, CW viewed from flange side Z gated A&B	9								
N: Analog electronics SS/ CC/ ZZ/ C before S, CW viewed from flange side Z ungated Contact factory for other configurations	9								
Resolution									
024, 2048									
Output Termination									
36: M23 12 pins CW 58: M23 12 pins CCW 3M: M12 8 pins 5P: PUR cable 12 wires 33: PVC cable 8 wires 35: PVC cable 8 wires 5C: PUR cable 8 wires									
Output Orientation									
R: Radial									
Cable Length									
xxx: Cable Length (ex.: 020 = 2 Meters) Blank: No Cable									
Reduction Hub									
** : No reduction hub U2 : Insulated Reduction hub									
Anti-rotation									
W** : 9445/045 stator coupling									

DW** : 9445/045 stator coupling **BB**** : 9445/046 tether arm (delivered not mounted on flange) **** : No antirotation

* Parts mounted on encoder and fasteners included in the encoder box.



AGENCY APPROVALS & CERTIFICATIONS



BEI Sensors SAS Sensata Technologies Espace Européen de l'Entreprise 9, rue de Copenhague B.P. 70044 Schiltigheim F 67013 Strasbourg Cedex

Tél : +33 (0)3 88 20 80 80 Fax : +33 (0)3 88 20 87 87 Mail: position-info.eu@sensata.com Web: www.sensata.com

Copyright © 2022 Sensata Technologies, Inc.



Page 6





Made in France

Page 7

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS, OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, OUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE TO SENSATA DATA SHEETS.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

 Americas

 +1 (800) 350 2727

 sensors@sensata.com

 Europe, Middle East & Africa

 +33 (3) 88 20 8080

 position-info.eu@sensata.com

 Asia Pacific

 sales.isasia@list.sensata.com

 China +86 (21) 2306 1500

 Japan +81 (45) 277 7117

 Korea +82 (31) 601 2004

 India +91 (80) 67920890

 Rest of Asia +886 (2) 27602006

 ext 2808