### T-1 (3mm) RIGHT ANGLE LED INDICATOR

Part Number: WP130WDT/EYW

High Efficiency Red Yellow

#### **Features**

- Pre-trimmed leads for pc board mounting.
- 3 leads with common lead.
- Black case enhances contrast ratio.
- Housing UL rating:94V-0.
- Housing material: type 66 nylon.
- RoHS compliant.

#### Descriptions

- The High Efficiency Red source color devices are made with Gallium Arsenide Phosphide on Gallium Phosphide Orange Light Emitting Diode.
- The Yellow source color devices are made with Gallium Arsenide Phosphide on Gallium Phosphide Yellow Light Emitting Diode.

#### **Package Dimensions**



Lead spacing is measured where the leads emerge from the package.
 The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.

Notes:

**REV NO: V.5A CHECKED:** Allen Liu

DATE: APR/14/2015 DRAWN: Q.M.Chen

PAGE: 1 OF 6 ERP: 1102000194

#### Salastian Cuida

Part No.	Dice	Lens Type		lv (mcd) [2] @ 20mA	
			Min.	Тур.	201/2
WP130WDT/EYW	High Efficiency Red (GaAsP/GaP)	- White Diffused	12	30	- 60°
			*10	*24	
	Yellow (GaAsP/GaP)		10	20	
			*10	*20	

Notes:

1. 01 / 2 is the angle from optical centerline where the luminous intensity is 1 / 2 of the optical peak value.
2. Luminous intensity / luminous Flux: + / -15%.
\* Luminous intensity value is traceable to the CIE127-2007 compliant national standards.

#### Electrical / Optical Characteristics at TA=25°C

Symbol	Parameter	Device	Тур.	Max.	Units	Test Conditions
λpeak	Peak Wavelength	High Efficiency Red Yellow	627 590		nm	l⊧=20mA
λD [1]	Dominant Wavelength	High Efficiency Red Yellow	617 588		nm	l⊧=20mA
Δλ1/2	Spectral Line Half-width	High Efficiency Red Yellow	45 35		nm	l⊧=20mA
С	Capacitance	High Efficiency Red Yellow	15 20		pF	VF=0V;f=1MHz
Vf [2]	Forward Voltage	High Efficiency Red Yellow	2 2.1	2.5 2.5	V	l⊧=20mA
lr	Reverse Current	High Efficiency Red Yellow		10 10	uA	VR = 5V

Notes:

Wavelength: + / -1nm.
 Forward Voltage: + / -0.1V.

Wavelength value is traceable to the CIE127-2007 compliant national standards.
 Excess driving current and / or operating temperature higher than recommended conditions may result in severe light degradation or premature failure.

#### Absolute Maximum Ratings at TA=25°C

Parameter	High Efficiency Red	Yellow	Units		
Power dissipation	75	75	mW		
DC Forward Current	30	30	mA		
Peak Forward Current [1]	160	140	mA		
Reverse Voltage	5 V				
Operating / Storage Temperature	-40°C To +85°C				
Lead Solder Temperature [2]	260°C For 3 Seconds				
Lead Solder Temperature [3]	260°C For 5 Seconds				

Notes:

1. 1 / 10 Duty Cycle, 0.1ms Pulse Width.
 2. 2mm below package base.
 3. 5mm below package base.



Yellow





- 3. When using the products referenced in this document, please make sure the product is being operated within the environmental and electrical limits specified in the datasheet. If customer usage exceeds the specified limits, Kingbright will not be responsible for any subsequent issues.
- 4. The information in this document applies to typical usage in consumer electronics applications. If customer's application has special reliability requirements or have life-threatening liabilities, such as automotive or medical usage, please consult with Kingbright representative for further assistance.
- 5. The contents and information of this document may not be reproduced or re-transmitted without permission by Kingbright.
- 6. All design applications should refer to Kingbright application notes available at http://www.KingbrightUSA.com/ApplicationNotes

DATE: APR/14/2015 DRAWN: Q.M.Chen

#### PRECAUTIONS

1. Storage conditions:

a.Avoid continued exposure to the condensing moisture environment and keep the product away from rapid transitions in ambient temperature.

- b.LEDs should be stored with temperature  $\leq 30^{\circ}$  C and relative humidity < 60%.
- c.Product in the original sealed package is recommended to be assembled within 72 hours of opening. Product in opened package for more than a week should be baked for 30 (+10/-0) hours at 85 ~ 100°C.
- 2. The lead pitch of the LED must match the pitch of the mounting holes on the PCB during component placement. Lead-forming may be required to insure the lead pitch matches the hole pitch. Refer to the figure below for proper lead forming procedures.



" ( ) " Correct mounting method " imes " Incorrect mounting method

Note 1-3: Do not route PCB trace in the contact area between the leadframe and the PCB to prevent short-circuits.

During soldering, component covers and holders should leave clearance to avoid placing damaging stress on the LED during soldering.



4. The tip of the soldering iron should never touch the lens epoxy.

- 5. Through-hole LEDs are incompatible with reflow soldering.
- 6. If the LED will undergo multiple soldering passes or face other processes where the part may be subjected to intense heat, please check with Kingbright for compatibility.
- 7. Recommended Wave Soldering Profiles:

