## FREEWAVE

**Z9-PE2** 

**NEW MODELS** 

# **≈ ZumLink**<sup>™</sup> 900 Series

Z9-P2

## Future-Ready Industrial Ethernet Radio

FreeWave's ZumLink<sup>™</sup> 900 Series is made for secure collection, transport, and control of data in rugged industrial environments, providing a longrange, low-power solution for remote wireless communications—with capabilities that can be seamlessly added as IIoT requirements evolve.

The ZumLink Z9-PE2 and Z9-P2 operate in the unlicensed 900 MHz spectrum and utilize Frequency Hopping Spread Spectrum (FHSS) technology for cybersecure data transfer with RF link rates up to 4 Mbps. Performance is further enhanced by FreeWave's Network Accelerators, which utilize techniques such as packet compression, packet aggregation, forward error correction, and Adaptive Spectrum Learning to maximize network throughput, efficiency, and reliability.

ZumLink radios are ideal in field area networks, systems, and devices such as those used by oil and gas, precision agriculture, water / wastewater, smart cities, and utilities, and deliver advanced features to maximize performance of virtually any M2M, SCADA, or IIoT application used today or in future operations.

In fact, the ZumLink 900 Series is software upgradable to include FreeWave's IQ Application Environment, a Linux-based operating system for developing and deploying third-party applications.

### **Key Features**

**Operates in the Unlicensed 900 MHz Spectrum:** Cost-effective, easy to deploy

unnur unnur

**High Speed Data Rates:** Five RF link rates supporting from 80 kbps to 4 Mbps

**Long Range:** Up to 97 km (60 miles) with clear line of sight

**Safe for Hazardous Locations:** Class I, Division 2 certified to board level

Leverages FreeWave's Network Accelerators: to maximize network efficiency

- Packet Compression: Minimizes packet transmission
- Packet Aggregation: Increases throughput
- Forward Error Correction: Improves network reliability
- Adaptive Spectrum Learning: Reduces the impact of interferences

Low Current Consumptions: 377 mA @ 12 V in transmit; 159 mA @ 12 V in receive

**Secure:** SSH, SNMP, 128- and 256-bit AES counter mode encryption

Reliable Communication: CRC, ARQ, FEC

**Upgradable with the IQ Application Environment:** Linux-based operating system and storage for applications built in any Linux-compatible language



#### Technical Specifications | ZumLink™ 900 Series

Transmitter	
Frequency Range*	902 to 928 MHz
Output Power*	10 mW to 1 W; user selectable
Range	97 km (60 miles) with clear line of sight
Channel Spacing	230.4, 345.6, 691.2, 1382.4, 1612.8 (Beta), & 3225.6 kHz
RF Data Rate	115.2, 250, 500 kbps, 1, 1.5 (Beta), & 4 Mbps; user selectable

Receiver			
IF Selectivity	> 40 dB		
System Gain	135 dB		
Sensitivity	RF Data Rates	Without FEC	With FEC
	115.2 kbps	-105 dBm	-108 dBm
	250 kbps	-102 dBm	-105 dBm
	500 kbps	-99 dBm	-102 dBm
	1 Mbps	-95 dBm	-98 dBm
	1.5 Mbps (Beta)	-90 dBm	-93 dBm
	4 Mbps	-83 dBm	-86 dBm

Data Transmission	
Туре	Frequency Hopping Spread Spectrum
Modulation	2 level GFSK 4- and 8-ary FSK
Link Throughput	Up to 1.6 Mbps; 4 Mbps with Compression
Topology	Point to Point, Point to Multipoint, Pseudo-Mes
Error Detection	ARQ and CRC, retransmit on error, FEC
Hopping Rates	400, 200, 100, 50, 25 ms
Hopping Channels*	Up to 110; RF Data Rate Dependent
Hopping Patterns	Up to 16; RF Data Rate Dependent
AirProtocol	Adaptive Spectrum Learning (ASL)
User Interface Rates Serial Protocols	Ethernet Rate: 10/100 Mbps Serial Rate: up to 250 kbps
	Asynchronous Byte Oriented Protocols, Modbus DNP3.0, DF1, X.28 and others
Data Encryption	128-bit and 256-bit AES CCM
Advanced Features	Packet Compression and Aggregation
Computing Resour	ces (OPTIONAL UPGRADE)**
CPU	ARM Cortex-A8 1 GHz
RAM	1 GB
Storage	1 GB
os	Debian-based Linux

Management	
Management	HTTP, SSH SNMPv1/v2c/v3, MIB-II, Enterprise MIB, Modbus
Networking	
VLAN	802.1Q
Serial	Terminal Server, TCP server, Modbus/TCP, Modbus RTU, TCP client
Traffic Filtering	Netmask filter, ARP filter
Interfaces	
Data Connectors	Four RJ-45, 2 Ethernet, 2 Serial (RS232/485)
USB Connectors	Micro USB Type A (Future Expansion)
RF Connector	TNC-F, 50 Ohms Impedance
Power Connectors	Phoenix Contact (#1776692)
Power Requirement	nts
Operating Voltage	+6 to +30 VDC

Voltage

12 VDC

General Information	
Operating Temperature	<b>Z9-P2:</b> -40°C to +85°C (-40°F to +185°F) <b>Z9-PE2:</b> -40°C to +75°C (-40°F to +167°F)
Humidity	0 to 95% non-condensing
Dimensions	<b>Z9-P2:</b> 170.18 L x 86.6 W x 27.18 H (mm) 6.70 L x 3.41 W x 1.07 H (in) <b>Z9-PE2:</b> 191.00 L x 104.39 W x 41.91 H (mm) 7.52 L x 4.11 W x 1.65 H (in)
Weight	<b>Z9-P2:</b> 200.5 g (0.44 lbs) <b>Z9-PE2:</b> 750 g (1.7 lbs)
Reliability	MTBF 206,186
Safety	Class I, Division 2, Groups A-D
UL	Z9-P2: CRUUS Z9-PE2: CULUS

Transmit

377 mA

Receive

159 mA

Idle

143 mA

Information to Order	
Model Number	
Z9-P2	Board Level Unit, 902 to 928 MHz
Z9-PE2	Enclosed Unit, 902 to 928 MHz

\*Country-specific models and information are available. Contact FreeWave Sales for information.

\*\*Requires licensing. Contact FreeWave Sales for information.



5395 Pearl Parkway Boulder, CO 80301

**Current Consumption** 

**TF:** 1.866.923.6168 **Tel:** 303.381.9200

www.freewave.com

Copyright © 2019 FreeWave Technologies, Inc. All rights reserved.