



I-7012(D)

I-7012F(D)

1-channel Analog Input Module

■ Features ■ Current or Voltage Input ■ High Resolution: 16-bit ■ High/Low Alarm (Digital Output) ■ 50 Hz Event Counter (Digital Input) ■ 100 Hz High Sampling Rate ■ 3000 VDC Intra-module Isolation ■ Dual Watchdog ■ Wide Operating Temperature Range: -25 to +75°C CE FC

Introduction

The I-7012 is an Analog Input module that is designed for both voltage and current input types. In addition, the module provides 1 Digital Input channel as a 50 Hz event counter and 2 Digital Output channels that can be used as a high/low alarm. The I-7012 also features 3000 VDC intra-module isolation.

The I-7012F is an Analog Input module that is designed for both voltage and current input types. The sampling rate for the I-7012F is adjustable and can be switched between fast mode and normal mode depending on your requirements. In addition, the module provides 1 Digital Input channel as a 50 Hz event counter and 2 Digital Output channels that can be used as a high/low alarm. The I-7012F also features 3000 VDC intra-module isolation.

System Specifications

Model	I-7012	I-7012D	I-7012F	I-7012FD
Communication				
Interface	RS-485			
Bias Resistor	No (Usually supplied by the RS-485 Master. Alternatively, add a tM-SG4 or SG-785.)			
Format	N, 8, 1			
Baud Rate	1200 to 1152	00 bps		
Protocol	DCON			
Dual Watchdog	Yes, Module (1.6 Seconds), C	ommunication ((Programmable)
LED Indicators/Display				
System LED Indicator	Yes, 1 as Pow	er/Communicat	tion Indicator	
I/O LED Indicators	-			
7-segment LED Display	-	Yes	-	Yes
Isolation				
Intra-module Isolation, Field-to-Logic	3000 VDC			
EMS Protection				
ESD (IEC 61000-4-2)	±2 kV Contact for each Terminal			
EFT (IEC 61000-4-4)	±4 kV to Power Line			
Surge (IEC 61000-4-5)	±0.5 kV for Power Line			
Power				
Reverse Polarity Protection	Yes			
Input Range	+10 ~ +30 VDC			
Consumption	1.3 W	1.9 W	1.3 W	1.9 W
Mechanical				
Dimensions (L x W x H)	123 mm x 72 mm x 35 mm			
Installation	DIN-Rail or Wall Mounting			
Environment				
Operating Temperature	-25 to +75°C			
Storage Temperature	-40 to +85°C			
Humidity	10 to 95% RH, Non-condensing			

Applications

- Building Automation
- Machine Automation
- Remote Diagnosis


- Factory Automation
- Remote Maintenance
- Testing Equipment

■ I/O Specifications


	<u>-</u>	7 7010				
Model		I-7012	I-7012D	I-7012F	I-7012FD	
Analog Input						
Channels		1				
Wiring		Differential				
Input Range	Input Range		± 150 mV, ± 500 mV, ± 1 V, ± 5 V, ± 10 V, ± 20 mA (requires optional external 125 Ω resistor)			
Resolution		16-bit 16-bit				
Accuracy	Normal Mode	0.1%				
Accuracy	Fast Mode	-		0.5%		
Sampling	Normal Mode	10 Hz				
Rate	Fast Mode	-		100 Hz		
Input Impedar	nce	20 ΜΩ				
Common Volta	ge Protection	±100 VDC				
Individual Channel Configuration		-				
Overvoltage Pr	rotection	±120 VDC				
Digital Input						
Channels		1				
Contact		Dry				
Sink/Source (N	NPN/PNP)	Source				
ON Voltage Le	ON Voltage Level		Close to GND			
OFF Voltage Lo	evel	Open				
Counter		Yes, 50 Hz, 16-bit				
Input Impedar	nce	3 kΩ				
Overvoltage Protection		±30 VDC				
Digital Output						
Channels		2				
Туре		Open Collector				
Sink/Source (NPN/PNP)		Sink				
Load Voltage		+3.5 ~ +30 VDC				
Max. Load Current		30 mA/Channel				
Power-on Value		Yes				
Safe Value		Yes				

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2019.12 1/2

■ Internal I/O Structure



■ Pin Assignments



■ Wire Connections

Voltage Input Wire Connection	Current Input Wire Connection
$mV/V \stackrel{+}{\underline{\hspace{1cm}}} V $	$\begin{array}{c c} mA \stackrel{+}{\longleftarrow} & \blacksquare & \blacksquare & + IN \\ \hline \square & \blacksquare & -IN \\ \hline 125\Omega & \\ \hline Requires an Optional External 125 \Omega Resistor$

Digital Input/Counter	Readback as 1	Readback as 0	
	Open	Closed to GND	
Dry Contact	□⊕ DIO/EV B)GND	□⊜ DIO/EV DIO/EV	

Digital Output	ON State Readback as 1	OFF State Readback as 0
Resistance Load	+ DOX	+ X D DOX (B)GND
Inductance Load	+ DOX (B)GND	+ DOX D DOX (B)GND

■ Ordering Information

I-7012 CR	1-channel Analog Input Module using the DCON Protocol (Blue Cover) (RoHS)	
I-7012-G CR 1-channel Analog Input Module using the DCON Protocol (Gray Cover) (RoHS)		
I-7012D CR I-7012 with 7-segment LED Display (Blue Cover) (RoHS)		
I-7012F CR 1-channel High Speed Analog Input Module using the DCON Protocol (16-bit) (Blue Cover) (RoHS)		
I-7012FD CR I-7012F with 7-segment LED Display (16-bit) (Blue Cover) (RoHS)		

Accessories

tM-7520U CR	RS-232 to RS-485 Converter (RoHS)
tM-7561 CR	USB to RS-485 Converter (RoHS)
tM-SG4 CR	RS-485 Bias and Termination Resistor Module (RoHS)

	I-7514U CR	4-channel RS-485 Hub (RoHS)
	SG-770 CR	7-channel Differential or 14-channel Single-ended Surge Protector (RoHS)
11 12	SG-3000 Series	Signal Conditioning Modules for Thermocouple, RTD, DC Voltage, DC Current and Power Input Transformers

ICP DAS CO., LTD Website: http://www.icpdas.com Vol. 2019.12 2/2