

# 1:1 Transmission Line Transformer 50 - 1200 MHz

Rev. V4

#### **Features**


- Surface Mount Technology
- 1:1 Impedance
- Excellent Temperature Stability
- Available on Tape & Reel

### **Description**

MABA-008483-CT1760 is a welded surface mount technology 1:1 transmission line transformer designed for high volume CATV Broadband applications.

Suitable for use in 50  $\Omega$  and 75  $\Omega$  systems.

#### **Functional Schematic**



## Pin Configuration<sup>3</sup>

Pin#	Function	Pin#	Function
1	Primary Dot	3	Secondary Dot
2	Secondary	4	Primary

## Electrical Specifications: Freq. = 50 - 1200 MHz, $T_A$ = +25°C, $Z_0$ = 75 $\Omega$

Parameter	Frequency Test Conditions (MHz)	Units	Min.	Тур.	Max.
	50			0.13	0.33
Insertion Loss 1	870	dB	_	0.53	0.93
(Through) pin 3 to pin 1	1002			0.63	1.18
	1200			0.83	1.93
	50			0.43	0.47
Insertion Loss 2	870	dB		0.33	0.63
(Coupled) pin 2 to pin 1	1002	ав	_	0.43	0.78
, , , , , , , ,	1200			0.63	1.33
	50	dB	_	0.3	-0.6
Amplitude Delence	870			-0.1	+0.7
Amplitude Balance	1002	uБ		-0.2	+0.7
	1200			-0.2	+0.8
Phase Balance	50 - 1002	0		1.2	± 4.0
	1002 - 1200		_	3.2	± 8.0
	50 - 500		18.0	23.0	
Input Return Loss	500 - 1002	dB	17.5	19.0	_
·	1002 - 1200		11.0	18.0	

## **Ordering Information**

Part Number	Package	
MABA-008483-CT1760	900 piece reel	
MABA-008483-CT17TB	Customer Test Board	

## Recommended Maximum Ratings<sup>1,2</sup>

Parameter	Absolute Maximum	
Input Power	250 mW	
DC Current	30 mA	
Operating & Storage Temperature	-40°C to +85°C	

- 1. Exceeding any one or combination of these limits may cause permanent damage to this device.
- MACOM does not recommend sustained operation near these survivability limits.

MACOM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.

Visit <a href="https://www.macom.com">www.macom.com</a> for additional data sheets and product information.




## 1:1 Transmission Line Transformer

#### 50 - 1200 MHz


Rev. V4

## **Typical Performance Curves**


#### Insertion Loss 1 (thru): pin 3-1




#### Insertion Loss 2 (coup); pin 2-1




#### Amplitude Balance



#### Phase Balance



#### Return Loss: Input






### 1:1 Transmission Line Transformer

### 50 - 1200 MHz


Rev. V4

## Outline Drawing<sup>3,4</sup>



- 3. Dimensions in mm.
- 4. Tolerance: ±0.2 mm unless otherwise noted.

## **Carrier Tape Orientation**



## **Tape & Reel Information**

Parameter	Units	Value		
Qty per reel	-	900		
Reel Size	mm	330		
Tape Width	mm	16.0		
Pitch	mm	12.0		
Orientation	-	F60		
Reference Application Note ANI-019 for orientation				



1:1 Transmission Line Transformer 50 - 1200 MHz

Rev. V4

#### MACOM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with MACOM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

4