Technical Data Sheet

Luminosity white Color LED

Features

- Super luminosity white LED.
- Built in 4 LED chips.
- Wide viewing angle.
- Soldering methods: Reflow soldering.
- High performance.
- Package in 12mm tape on 7" diameter reel.
- Pb-free.
- The product itself will remain within RoHS compliant version.

Descriptions

- The 59-14 SMD LED is much smaller than lead frame type components, thus enable smaller board size, higher packing density, reduced storage space and finally smaller equipment to be obtained.
- Besides, lightweight makes them ideal for miniature applications. etc.

Applications

- Amusement equipment.
- Information boards.
- Flashlight for digital camera of cellular phone.
- Lighting for small size device.

Device Selection Guide

Cł	nip	Resin Color
Material	Material Emitted Color	
InGaN	White	Yellow diffused



http://www.everlight.com Rev.2 Page: 1 of 10 Prepared date: 17-Oct-2011 Prepared by: Ashley Kuo. Release Date:2011-10-18 19:28:01.0

Expired Period: Forever

59-14UTD/TR8





59-14UTD/TR8

Package Outline Dimensions



For Reflow Soldering(Propose)

Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm

Everlight Electronics Co., Ltd. Device No. : DSE-0005849 Revision : 2 LifecyclePhase: 正式發行 Approved http://www.everlight.com Rev.2 Page: 2 of 10
Prepared date: 17-Oct-2011 Prepared by: Ashley Kuo
Release Date:2011-10-18 19:28:01.0

59-14UTD/TR8

	Symbol	Rating	Unit		
Reverse Voltage	Vr	5	V		
Forward Current	IF	30	mA		
Peak Forward Current (Duty 1/10 @ 400ms)	I_{FP}	100	mA		
Power Dissipation	Pd	110	mW		
Electrostatic Discharge(HBM)	ESD	1000	V		
Operating Temperature	Topr	-40 ~ +85			
Storage Temperature	Tstg	-40 ~ +90			
Soldering TemperatureTsolReflow Soldering : 260for 10 sec.Hand Soldering : 350for 3 sec.					

Absolute Maximum Ratings (Ta=25)

Electro-Optical Characteristics (Ta=25)

	liceno optical characteristics (14–25)						
Parameter	Symbol	Min.	Тур.	Max.	Unit	Condition	
Luminous Intensity*1		5.0	8.5	15.0	ad	I _F =20mA*2	
	Iv	10.0	25.0	45.0	cd	I _{FP} =100mA*2 (Duty 1/10 @ 400ms)	
Viewing Angle*1	2 1/2		60		deg	$I_F = 20 m A * 2$	
Forward Voltage*2		2.7	3.3	3.7	V	I _F =20mA*2	
Forward Voltage*2	V_{F}	3.6	4.4	5.2	v	I _{FP} =100mA*2 (Duty 1/10 @ 400ms)	
Reverse Current*2	I _R			50	μA	V _R =5V*2	

*1 When 4 LED dies are operated simultaneously.

*2 For each die.

Note: The products are sensitive to static electricity and care must be fully taken when

handling products.			
Everlight Electronics Co., Ltd.	http://www.everlight.com	Rev.2	Page: 3 of 10
Device No. : DSE-0005849 Revision : 2	Prepared date: 17-Oct-2011 Relea	Prepared by: A se Date:2011-1	Ashley Kuo 0-18 19:28:01.0
正式發行 Approved	Expi	red Period: For	ever

59-14UTD/TR8

Color Ranks

	Rank A0				
х	0.280	0.264	0.283	0.296	
У	0.248	0.267	0.305	0.276	

	Rank B4				
х	0.307	0.304	0.330	0.330	
у	0.315	0.330	0.360	0.339	

	Rank B6				
х	0.311	0.307	0.330	0.330	
у	0.294	0.315	0.339	0.318	

*The C.I.E. 1931 chromaticity diagram (Tolerance ±0.01).

CIE Chromaticity Diagram



Everlight Electronics Co., Ltd. Device No. : DSE-0005849 Revision : 2 LifecyclePhase: Approved http://www.everlight.com Rev.2 Page: 4 of 10 Prepared date: 17-Oct-2011 Prepared by: Ashley Kuo Release Date:2011-10-18 19:28:01.0

	Rank B3				
х	0.287	0.283	0.304	0.307	
У	0.295	0.305	0.330	0.315	

	Rank B5				
Х	0.296	0.287	0.307	0.311	
у	0.276	0.295	0.315	0.294	

	Rank C0				
х	0.330	0.330	0.361	0.356	
У	0.318	0.360	0.385	0.351	

Ta=25°C

<u>59-14UTD/TR8</u>

Typical Electro-Optical Characteristics Curves









Everlight Electronics Co., Ltd. Device No.: DSE-0005849 **Revision** :2 正式發行 LifecyclePhase: Approved

http://www.everlight.com Prepared date: 17-Oct-2011

Rev.2 Page: 5 of 10 Prepared by: Ashley Kuo Release Date:2011-10-18 19:28:01.0

59-14UTD/TR8

Label Explanation

- **CAT: Luminous Intensity Rank**
- **HUE: Chromaticity Coordinates**
- **REF: Forward Voltage Rank**



Reel Dimensions



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm

Everlight Electronics Co., Ltd. Device No. : DSE-0005849 Revision : 2 LifecyclePhase: Approved http://www.everlight.com Rev.2 Page: 6 of 10 Prepared date: 17-Oct-2011 Prepared by: Ashley Kuo Release Date:2011-10-18 19:28:01.0



59-14UTD/TR8

Carrier Tape Dimensions: Loaded quantity 800 PCS per reel



Note: The tolerances unless mentioned is ± 0.1 mm, Unit = mm

Moisture Resistant Packaging



Everlight Electronics Co., Ltd. Device No. : DSE-0005849 Revision : 2 LifecyclePhase: 百式發行 http://www.everlight.com Rev.2 Page: 7 of 10
Prepared date: 17-Oct-2011 Prepared by: Ashley Kuo
Release Date:2011-10-18 19:28:01.0

59-14UTD/TR8

Reliability Test Items And Conditions

The reliability of products shall be satisfied with items listed below. Confidence level: 90%

LTPD: 10%

No.	Items	Test Condition	Test Hours/Cycles	Sample Size	Ac/Re
1	Reflow Soldering	Temp. : 260 ±5 Max. 10sec.	6 Min.	22 PCS.	0/1
2	Temperature Cycle	H : +100 15min 5 min L : -40 15min	300 Cycles	22 PCS.	0/1
3	Thermal Shock	H : +100 5min 10 sec L : -10 5min	300 Cycles	22 PCS.	0/1
4	High Temperature Storage	Temp. : 100	1000 Hrs.	22 PCS.	0/1
5	Low Temperature Storage	Temp. : -40	1000 Hrs.	22 PCS.	0/1
6	DC Operating Life	IF = 20 mA	1000 Hrs.	22 PCS.	0/1
7	High Temperature / High Humidity	85 / 85%RH	1000 Hrs.	22 PCS.	0/1
	EY.				

http://www.everlight.com

Prepared date: 17-Oct-2011

Page: 8 of 10

Release Date:2011-10-18 19:28:01.0

Prepared by: Ashley Kuo

Rev.2

<u>59-14UTD/TR8</u>

Precautions For Use

1. Over-current-proof

Customer must apply resistors for protection, otherwise slight voltage shift will cause big

current change (Burn out will happen).

- 2. Storage
 - 2.1 Do not open moisture proof bag before the products are ready to use.
 - 2.2 Before opening the package: The LEDs should be kept at 30 or less and 90% RH or less.
 - 2.3 After opening the package: The LED's floor life is 1 year under 30 or less and 60% RH or less.If unused LEDs remain, it should be stored in moisture proof packages.
 - 2.4 If the moisture absorbent material (silica gel) has faded away or the LEDs have exceeded the storage time, baking treatment should be performed using the following conditions.Baking treatment : 60±5 for 24 hours.
- 3. Soldering Condition
 - 3.1 Pb-free solder temperature profile



- 3.2 Reflow soldering should not be done more than two times.
- 3.3 When soldering, do not put stress on the LEDs during heating.
- 3.4 After soldering, do not warp the circuit board.

59-14UTD/TR8

4.Soldering Iron

Each terminal is to go to the tip of soldering iron temperature less than 350 for 3 seconds within once in less than the soldering iron capacity 25W. Leave two seconds and more intervals, and do soldering of each terminal. Be careful because the damage of the product is often started at the time of the hand solder.

5.Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of the LEDs will or will not be damaged by repairing.



EVERLIGHT ELECTRONICS CO., LTD. Office: No 25, Lane 76, Sec 3, Chung Yang Rd, Tucheng, Taipei 236, Taiwan, R.O.C

Tel: 886-2-2267-2000, 2267-9936 *Fax:* 886-2267-6244, 2267-6189, 2267-6306 *http://www.everlight.com*

Everlight Electronics Co., Ltd. Device No. : DSE-0005849 Revision : 2 LifecyclePhase: Approved http://www.everlight.com

Prepared date: 17-Oct-2011

Rev.2 Page: 10 of 10

Prepared by: Ashley Kuo Release Date:2011-10-18 19:28:01.0