


Standard Product Specifications

GTEW1656JTE-27Z-TR



Features

Package	High efficiency and power ceramic package Outer dimension 5.0 x 5.0 x 1.0mm (L x W x H)
Product features	 Efficiency 81lm/W, white color emitting (2,700K, Ra95) Luminous flux at 85°C(solder point temperature): 73lm Sulfuretted countermeasure LED Lead-free soldering compatible RoHS compliant

Recommended Applications


•Residential lighting, Office lighting, Plant lighting, Store lighting, etc.




Package Dimensions

GTEW1656JTE-27Z-TR

Unit : mm Weight : 67.6mg Tolerance : ± 0.2



Recommended Soldering Pattern



Unit: mm

Specifications

GTEW1656JTE-27Z-TR


[Product Overview]

DIE MATERIAL	InGaN
EMITTING COLOR	White
RESIN COLOR [EMITTING AREA]	Diffused Pale Orange
LAMP HOUSING COLOR	White

[Absolute Maximum Ratings]

ITEM	SYMBOL	MAXIMUM RATINGS	UNITS	
Power Dissipation	P_d	3,200	mW	
Continous Forward Current	I_{F}	800	mA	
I_F Derate Linearly from "Ts = 60° C"	ΔI_{F}	13.4	mA/°C	Notes 1
Repetitive Peak Forward Current "1ms, 1/20duty"	I_{FRM}	1,200	mA	
I_{FRM} Derate Linearly from "Ts=60°C"	ΔI_{FRM}	20.1	mA/°C	Notes 1
Allowable Reverse Current	I_R	85	mA	
Operating Temperature	$T_{ m opr}$	-40 ~ +85	°C	Notes 2
Storage Temperature	T_{stg}	-40 ~ +100	°C	Notes 2
Electrostatic Discharge Threshold "HBM"	ESD	1,000	V	Notes 3
Soldering temperature "Reflow Soldering"	$T_{\rm sld}$	260	°C	Notes4

Notes 1 Junction - solder point(measurement point)



Notes 2 The range of operating and storage temperature is not taping condition.

Notes 3 ESD testing method : EIAJ4071/300(304) Human Body Model (HBM) $1.5k\Omega$, 100pF

Notes 4 Please refer to page 9, Soldering Conditions.

[Thermal Characteristics]

ITEM	SYMBOL	MIN.	TYP.	MAX.	UNITS	
Thermal resistance [Junction - solder point]	$R_{th(j-s)}$	-	15	-	°C/W	Notes 1

Specifications

GTEW1656JTE-27Z-TR

[Electro-Optical Characteristics]

						(Ts=25°C)	<u>)</u>
ITEM	SYMBOL	Conditions	MIN.	TYP.	MAX.	UNITS	
Forward Voltage	$V_{\rm F}$	$I_F = 350 mA$	2.75	3.00	3.25	V	
Reverse Voltage	V _R	$I_R = 10 \text{mA}$	0.6	-	1.1	V	Notes5
Luminous Flux	$\Phi_{ m V}$	$I_F = 350 \text{mA}$	60	85	100	lm	Notes6
Luminous Flux @85°C	$\Phi_{ m V}$	$I_F = 350 \text{mA}$	-	73	-	lm	Notes7
Efficiency	-	$I_F = 350 \text{mA}$	-	81	-	lm/W	
Clara markinitas Consulius de	х	$I_F = 350 \text{mA}$	-	0.458	-		Notes8,9
Chromaticity Coordinates	у	$I_F = 350 \text{mA}$	-	0.410	-] \	Noteso,
11-16 I	Δθχ	I 250 A	-	120	-	1	Notes10
Half Intensity Angle	Δθγ	$I_F = 350 \text{mA}$	-	120	-	deg.	Notesic
General color rendering index	Ra	$I_F = 350 \text{mA}$	-	95	-		
color temperature	-	$I_F = 350 \text{mA}$	-	2,700	-	K	


Notes 5 To prevent the destruction by static electricity, please do not input reverse voltage.

Notes 6,8 Please refer to below sorting charts.

Notes 7 Luminous flux at 85°C (solder point temperature)

Notes 9 Chromaticity coordinates: x and y according to CIE1931.

Viewing Angle at 50% Iv, $\Delta\theta x$, $\Delta\theta y$, as shown in the right figure. Notes 10



[Sorting chart For Luminous Flux and Forward Voltage]

LEDs shall be sorted out into the following charts and each rank parts shall be packed separately when shipping.

(Ts=25°C)

(Ts=25°C)

Rank	Luminous 1	Condirions	
Kank	MIN.	MAX.	Condinons
MA	60	80	I = 250m A
MB	80	100	$I_F = 350 \text{mA}$

Tolerance: ±10%

Note

Rank	Forward Vo	Condirions	
Kank	MIN.	MAX.	Conditions
J	2.75	3.25	$I_F = 350 \text{mA}$


Tolerance: $\pm 0.1V$


Specifications

GTEW1656JTE-27Z-TR

[Sorting chart For Chromaticity coordinates]

Chromaticity coordinates shall be sorted out into the following chart and each rank parts shall be packed separately when shipping.





General color temperature 2,700K (2,580K~2,870K)

Ts=25°C $I_F=350$ mA)

Rank	X	y
27A	0.4585	0.4104
	0.4688	0.4290
	0.4813	0.4319
	0.4703	0.4132

Kank	X	y
27B	0.4483	0.3919
	0.4585	0.4104
	0.4703	0.4132
	0.4593	0.3944

Rank	X	y
27C	0.4468	0.4077
	0.4562	0.4260
	0.4688	0.4290
	0.4585	0.4104


Rank	X	y
27D	0.4373	0.3893
	0.4468	0.4077
27D	0.4585	0.4104
	0.4483	0.3919


Rank	X	y
27G	0.4697	0.4211
	0.4591	0.4025
	0.4477	0.3998
	0.4576	0.4183

Notes


- Chromaticity coordinates Tolerance each rank : ± 0.01
- Chromaticity rank will ship by 5 ranks (A, B, C, D, and G).
- Rank G might also be shipped as Rank A,B,C and D.































Soldering condition

GTEW1656.JTE-27Z-TR


(Soldering Precaution)

(acc.to EIAJ-4701/300)

- 1. Heat stress during soldering will influence the reliability of LEDs, however that effect will vary on heating method. Also, if components of varying shape are soldered together, it is recommended to set the soldering pad temperature according to the component most vulnerable to heat (e.g., surface mount LED).
- 2. LED parts including the resin are not stable immediately after soldering (when they are not at room temperature), any mechanical stress may cause damage to the product. Please avoid such stress after soldering, especially stacking of the boards which may cause the boards to warp and any other types of friction with hard materials.
- 3. Recommended temperature profile for the Reflow soldering is listed as the temperature of the resin surface. Temperature distribution varies on heating method, PCB material, other components in the assembly, and mounting density.

Please do not repeat the heating process in Reflow process more than twice.

[Recommended Reflow Soldering Condition]



Note 1 Temperature Profile for the reflow soldering is listed as the temperature of resin surface. This should be the maximum temperature for soldering. Lowering the heating temperature and decreasing heating time is very effective in achieving higher reliability.

Note 2 The reflow soldering process should be done up to twice(2 times Max). When second process is performed, interval between first and second process should be as short as possible to prevent absorption of moisture to resin of LED. The second soldering process should not be done until LEDs have returned to room temperature (by nature-cooling) after first soldering process.



Soldering condition

GTEW1656JTE-27Z-TR

- 4. If soldering manually, Stanley recommends using a soldering iron equipped with temperature control. During the actual soldering process, make sure that the soldering iron never touches the LED itself, and avoid the LED's electrode heating temperature reaching above the heating temperature of the solder pad. All repairs must be performed only once in the same spot, and please avoid reusing components.
- 5. In soldering process, immediately after iron tip is cleaned, please make sure that the soldering iron reaches the appropriate temperature before using. Also, please avoid applying any types of pressure to the soldered components before the solder has been cooled and hardened, as it may deteriorate solder performance and solder quality.

[Recommended Manual Soldering Condition]

Temperature of Iron Tip	350°CMAX.
Soldering Duration, Time	3sec.Max.,1 time

- 6. When using adhesive material for tentative fixatives, thermosetting resin or Ultraviolet radiation (UV) setting resin with heat shall be recommended.
 - 《The curing condition, Temperature:150°CMax./Time:300sec.Max.》
- 7. Flow soldering (dip soldering) is not recommended for this product.
- 8. Isopropyl alcohol is recommended for cleaning. Some chemicals, including Freon substitute detergent could corrode the lens or the casing surface, which cause discoloration, cloud, crack and so on. Please review the reference chart below for cleaning. If water is used to clean (including the final cleaning process), please use pure water (not tap water), and completely dry the component. Cleaning with ultrasonic is not recommended.

Chemical	Adaptability
Ethyl Alcohol	0
Isopropyl Alcohol	0
Pure Water	0
Trichloroethylene	×
Chlorothene	×
Acetone	×
Thinner	×



Handling Precaution

GTEW1656.JTE-27Z-TR

[For Electric Static Discharge (ESD)]

This type of LED lamp is highly sensitive to surge voltage generated by the On/Off status change and discharges of static electricity through frictions with synthetic materials, which may cause severe damage to the die or undermine its reliability. Damaged products may experience conditions such as extremely high reverse voltage, or a decrease of forward rise voltage, deteriorating its optical characteristic. Stanley products are designed to withstand up to 1,000V under the EIAJ ED-4701/300 Test #304 (HBM), and are packed with anti-static components. However, the following precautions and measures are vital in ensuring product quality during shipment.

EIAJ ED-4701/300 (304/HBM) Electrification model: C=100pF, R2=1.5KΩ

1. Electrification/Static Electricity protection

Stanley recommends the following precautions in order to avoid product (die) damage from static electricity, when an operator and other materials electrified by friction coming in contact with the product.

- ① Do not place electrified non-conductive materials near the LED product.

 Avoid LED products from coming into contact with metallic materials.(Should the metallic material be electrified, the sudden surge voltage will most likely damage the product.)
- ② Avoid a working process which may cause the LED product to rub against other materials.
- ③ Install ground wires for any equipment, where they can be installed, with measures to avoid static electricity surges.
- **4** Prepare a ESD protective area by placing a Conductive Mattress ($1M\Omega$ MAX.) and Ionizer to remove any static electricity.
- ⑤ Operators should wear a protective wrist-strap.
- **6** Operators should wear conductive work-clothes and shoes.
- To handle the products directly, Stanley recommends the use of ceramic, and not metallic, tweezers.

2. Working Environment

- ① A dry environment is more likely to cause static electricity. Although a dry environment is ideal for storage state of LED products, Stanley recommends an environment with approximately 50% humidity after the soldering process.
- ② Recommended static electricity level in the working environment is 150V, which is the same value as Integrated Circuits (which are sensitive to static electricity).



Handling Precaution

GTEW1656.JTE-27Z-TR

[Other Precautions]

- 1. Stanley LED Lamps have semiconductor characteristics and are designed to ensure high reliability. However, the performance may vary depending on usage conditions.
- Absolute Maximum Ratings are set to prevent LED lamps from failing due to excess stress(temperature, current, voltage, etc.). Usage conditions must not exceed the ratings for a moment, nor do reach one item of absolute maximum ratings simultaneously.
- 3. In order to ensure high reliability from LED Lamps, variable factors that arise in actual usage conditions should be taken into account for designing. (Derating of TYP., MAX Forward Voltage, etc.)
- 4. Please insert Straight Protective Resistors into the circuit in order to stabilize LED operation and to prevent the device from igniting due to excess current.
- 5. Please be careful when LED is soldered on a metal plate, since solder crack might be caused by heat .
- 6. Please avoid using this product with materials or products that contain sulfur or chlorine element which may damage the product. Keep the product in desiccator regardless of before or after mounting to prevent corrosive gas. Also make sure there is no corrosive gas which occurs in surrounding area or invade from outside when using products.
- 7. Please avoid the stick of foreign material because molding resin in the products have adhesiveness. And please don't touch lens portion.
- 8. Please check the actual performance in the assembly because the Specification Sheets are described for LED device only.
- 9. Please refrain from looking directly at the light source of LED at high output, as it may harm your vision.
- 10. The products are designed to operate without failure in recommended usage conditions. However, please take the necessary precautions to prevent fire, injury, and other damages should any malfunction or failure arise.
- 11. The products are manufactured to be used for ordinary electronic equipment. Please contact our sales staff beforehand when exceptional quality and reliability are required, and the failure or malfunction of the products might directly jeopardize life or health (such as for airplanes, aerospace, transport equipment, medical applications, nuclear reactor control systems and so on).
- 12. The formal specification sheets shall be valid only by exchange of documents signed by both parties.

Handling Precaution


GTEW1656JTE-27Z-TR

[Handling Precautions for Product Mounting]

< Recommendation >

Picking up point with nozzle: Lamp housing of the product (area) (Shown below)

The pick up point is lamp housing only because the silicone resin used for the lens is soft. (If the nozzle makes contact with the lens, the products might be destroyed)



Please adjust the load, the pick up point, the nozzle diameter and etc. before mounting because over load can cause the breakage of the lamp housing.



GTEW1656.JTE-27Z-TR

This product is baked (moisture removal) before packaging, and is shipped in moisture-proof packaging (as shown below) to minimize moisture absorption during transportation and storage. However, with regard to storing the products, Stanley recommends the use of dry-box under the following conditions is recommended. Moisture-proof bag as the packaging is made of anti-static material but packaging box is not.

[Recommended Storage Condition / Products Warranty Period]

Temperature	+5 ~ 30℃
Humidity	Under 70%

In the case of the package unopened, 6 months under [Recommended Storage Condition]. Please avoid rapid transition from low temp. condition to high temp. condition and storage in corroding and dusty environment.

Time elapsed after Package Opening

The package should not be opened until immediately prior to its use, and please keep the time frame between package opening and soldering which is **[maximum 168h]**.

If the device needs to be soldered twice, both soldering operations must be completed within the 168h.

If any components should remain unused, please reseal the package and store them under the conditions described in the [Recommended Storage Condition] above.

This product must be required to perform baking process (moisture removal) for at least 23h at 60 ± 5 degrees celsius if following conditions apply.


- 1. In the case of silica gel (blue) which indicates the moisture level within the package, changes or loses its blue color.
- 2. In the case of time passes for 168h after the package is opened once.


Baking process should be performed after LED having been taken out of the package.

Baking may be performed in the tape-reel form, however if it is performed with the reel stacked over one another, it may cause deformation of the reels and taping materials and later obstruct mounting. Please handle only once it has returned to room temperature. Provided that, baking process shall be 2 times MAX.




GTEW1656JTE-27Z-TR





NO.	PART NAME	MATERIALS	REMARKS
1	Moisture-proof bag with Aluminum layer	PET+Al+PE	with ESD protection

[Flow Chart-package Opening to Mounting]



Allowable leaving time means the maximum allowable leaving time after opening package, which depends on each LED type.

The allowable leaving time should be calculated form the first opening of package to the time when soldering process is finished.

When judging if the allowable leaving time has exceeded or not, please subtract the soldering time. The allowable leaving time after reopening should be calculated form the first opening of package, or from the time when baking process is finished.

GTEW1656JTE-27Z-TR


(RoHS•ELV Compliant)

[Packing box]

Box TYPE	Outline dimension $L \times W \times H \text{ (mm)}$	Capacity of the box
Type A	280 × 265 × 45	3 reel
Туре В	310 × 235 × 265	15 reel
Туре С	440 × 310 × 265	30 reel

The above measure is all the reference value.

The box is selected out of the above table by shipping quantity.



Type A Type B,C


Material / box : Cardboard C5BF Material / box : Cardboard K5AF Partition : Cardboard K5BF


NO.	PART NAME	MATERIAL	REMARKS
②	Packing Box	Corrugated	without ESD
	1 401411 2 511	Cardbord	protection

GTEW1656JTE-27Z-TR

(acc.to JIS-X0503(Code-39))

[Label Specification]






- A. Parts number
- B. Bar-code for parts number
- C. Parts code (In-house identification code for each parts number)
- D. Packed parts quantity
- E. Bar-Code for packed parts quantity
- F. Lot number & Rank

(refer to Lot Number Notational System for details)

G. Bar-Code for Lot number & Rank

(B) Opto Device Label



- A. Customer Name
- B. Parts Type
- C. Parts Code
- D. Parts Number
- E. Packed Parts Quantity
- F. Carton Number
- G. Shipping Date
- H. Bar-Code for In-house identification Number


<Remark> Bar-code font : acc.to Code-39(JIX0503)

Taping and Reel Specifications

GTEW1656JTE-27Z-TR

(acc.to JIS-C0806)

[Appearance]



Note

Ite	ms	Specifications Remarks	
		The end of cover-tape shall be held with adhesive tape.	
Leader area	Carrier-tape Empty pocket shall be more than 13 pieces (100mm).		Please refer to the above figure for Taping & reel orientation.
Trailer area		Empty pocket shall be more than 20 pieces (160mm).	The end of taping shall be inserted into a slit of the hub.

[&]quot;-TR" means Cathode Side of LEDs should be placed on the sprocket-hole side.



Taping and Reel Specifications

GTEW1656JTE-27Z-TR

(acc.to JIS-C0806)

[Qty. per Reel]

1,000 parts / reel

[Mechanical strength]

Cover-tape adhesive strength shall be $0.1 \sim 1.3 \text{N}$ (An angle between carrier-tape and cover-tape shall be 170 deg.). Both tapes shall be so sealed that the contained parts will not come out from the tape when it is bent at a radius of 15mm.

Others

Reversed-orientation, Up-side down placing, side placing and out of spec. parts mix shall not be held. Empty Pocket per reel is assumed until 1 piece.





Pb-free

Taping and Reel Specifications

(acc.to JIS-C0806)

[Taping Dimensions]






NO.	PART NAME	REMARKS
1	Carrier tape	with ESD protection
2	Cover tape	with ESD protection
3	Carrier reel	with ESD protection



Lot Number Notational System

GTEW1656JTE-27Z-TF



① - 1digit : Production Location (Mark identify alphabet)

② - 1digit : Production Year (Last digit of Production Year 2009→9,2010→0,2011→1,···)

③ - 2digits: Production Month (Jan. to Sep. should be 01,02,03,····)

4 - 2digits: Production Date

⑤ - 3digits : Serial Number

6 - 2digits: Tape and Reel following Number

7 - 2digits : Luminous Intensity Rank.

(If luminous intensity rank is 1 digit, "-" shall be dashed on the place for the second digit.

If there is no identified intensity rank, "--" is used to indicate.)

8 - 2digits : Chromaticity Rank

(If chromaticity rank is 1 digit, "-" shall be dashed on the place for the second digit.

If there is no identified intensity rank, "--" is used to indicate.)

Marking	Chromaticity Rank	
1A	27A	
1B	27B	
1G	27G	
1C	27C	
1D	27D	

9 - 1digit : Forward Voltage Rank (If there is no identified intensity rank, "- " is used to indicate)



Correspondence to RoHS·ELV instruction GTEW1656JTE-27Z-TR

This product is in compliance with RoHS•ELV.

Prohibition substance and it's criteria value of RoHS•ELV are as follows.

- •RoHS instruction Refer to following $(1)\sim(6)$.
- •ELV instruction Refer to following (1)~(4).

	Substance Group Name	Criteria Value
(1)	Lead and its compounds	1,000ppm Max
(2)	Cadmium and its compounds	100ppm Max
(3)	Mercury and its compounds	1,000ppm Max
(4)	Hexavalent chromium	1,000ppm Max
(5)	PBB	1,000ppm Max
(6)	PBDE	1,000ppm Max



Reliability Testing Result

GTEW1656JTE-27Z-TR

1. Reliability Testing Result

Test Item	Standard	Test Condition	Duration	Failure
Room Temperature Operating Life	EIAJ ED-4701 /100(101)	Ta=25°C I _F =800mA	1,000h	0 / 16
High Temperature Operating Life	EIAJ ED-4701 /100(101)	Ta=85°C I _F =600mA (Tj=135°C)	1,000h	0 / 16
Low Temperature Operating Life	EIAJ ED-4701 /100(101)	Ta=-40°C I _F =800mA	1,000h	0 / 16
Wet High Temperature Operating Life	EIAJ ED-4701 /100(102)	Ta=60°C 90% I _F =800mA	1,000h	0 / 16
High Temperature Storage Life	EIAJ ED-4701 /200(201)	Ta=100°C	1,000h	0 / 20
Low Temperature Storage Life	EIAJ ED-4701 /200(202)	Ta=-40°C	1,000h	0 / 20
Wet High Temperature Storage Life	EIAJ ED-4701 /100(101)	Ta=60°C 90%	1,000h	0 / 20
Thermal Shock	EIAJ ED-4701 /100(105)	Ta=-40°C ~100°C (each 15min)	1,000 cycles	0 / 20
Resistance to Reflow Soldering	EIAJ ED-4701 /300(301)	Moisture Soak: 30°C 70% 168h Preheating: 150~180°C 120sec MAX. Soldering: 260°C Peak	2times	0 / 20
Electrostatic Discharge (ESD)	EIAJ ED-4701 /300(304)	C=100pF R2=1.5kΩ ±2,000V	Once of each polarity	0 / 20
Vibration, Variable Frequency	EIAJ ED-4701 /400(403)	98.1m/s ² (10G) 100~2,000Hz 20min sweep XYZdirection	2h of each direction	0 / 20

Reference test

2. Failure Criteria

Item	Symbol	Condition	Failure Criteria
Luminous Intensity	I_{V}	I _F =100mA	Testing Min. Value $<$ Standard Min. Value \times 0.5
Forward Voltage	$V_{\rm F}$	I _F =100mA	Testing Max. Value \geq Standard Max. Value \times 1.2
Cosmetic appearance	-	-	Notable, discoloration, deformation and cracking



Special Notice to Customers Using the Products and Technical Information Shown in This Data Sheet

- The technical information shown in the data sheets are limited to the typical characteristics and circuit examples of the referenced products. It does not constitute the warranting of industrial property nor the granting of any license.
- 2) For the purpose of product improvement, the specifications, characteristics and technical data described in the data sheets are subject to change without prior notice. Therefore it is recommended that the most updated specifications be used in your design.
- 3) When using the products described in the data sheets, please adhere to the maximum ratings for operating voltage, heat dissipation characteristics, and other precautions for use. We are not responsible for any damage which may occur if these specifications are exceeded.
- 4) The products that have been described to this catalog are manufactured so that they will be used for the electrical instrument of the benchmark (OA equipment, telecommunications equipment, AV machine, home appliance and measuring instrument).
 - The application of aircrafts, space borne application, transportation equipment, medical equipment and nuclear power control equipment, etc. needs a high reliability and safety, and the breakdown and the wrong operation might influence the life or the human body. Please consult us beforehand if you plan to use our product for the usages of aircrafts, space borne application, transportation equipment, medical equipment and nuclear power control equipment, etc. except OA equipment, telecommunications equipment, AV machine, home appliance and measuring instrument.
- 5) In order to export the products or technologies described in this data sheet which are under the "Foreign Exchange and Foreign Trade Control Law," it is necessary to first obtain an export permit from the Japanese government.
- 6) No part of this data sheet may be reprinted or reproduced without prior written permission from Stanley Electric Co., Ltd.
- 7) The most updated edition of this data sheet can be obtained from the address below: http://www.stanley-components.com/en/