Issue No.	: RV-H-1719	
Date of Issue	: Dec.6.2012	_
Classification	: ■ New □ Change	_

PRODUCT SPECIFICATION FOR APPROVAL

Product Description:	: ENCODER	
Product Part Number	:	(Panasonic Part Number : EVEWRHJR012B)
Country of Origin	: VIETNAM	(Indicated on the packing label in English)
Applications	:	Model :

* In case of use other than the application described above, contact Panasonic representatives.
* If you approve this specification, please fill in and sign the below and return 1 copy to us.

Approval	No.	:					
Approval	Date	:					
Executed	by	:					
						 	
			(Signature)			
Title		:					
Dept.		:					

Electromechanical Components Business Unit Industrial Devices Company

1006 Kadoma, Kadoma City, Osaka, Japan

Phone: (06) 6908-7304 (Direct)

Prepared by : In Contact Person E

: Input Devices Development Team Engineering Group

Signature : <u>H</u>. Sad Name (Print) H.Sadamori

:

H. Sadamon

H.Sadamori Staff Engineer +81-868-26-3791

Authorized by Signature Name (Print) Title

Title

Phone

M. Aama da M.Sawada







Ο

 \triangleleft

 \bigcirc

Panasonic Corporation

enc-11gs-e0-evewrhjr012b-general

_	Ge	neral					
	1.		ification applies to re lectronic equipment.	otary er	ncoder(incre	emental type)	
	2. Standard atmospheric conditions: Unless otherwise specified. The standard range of atmospheric conditions for making measurements and tests is as follows. Ambient temperature: 15°C ~ 35°C Relative humidity : 25% ~ 75%						
	Air pressure : 86kPa ~ 106kPa 3. Operating temperature range : -40°C ~ +85°C						
			rature range :				
			e : Encoder D.C 10 Switch D.C 16				
	6.	Rated current	t : Encoder D.C 1 Switch D.C 20	mA mA			
	Pr	roduction co	<u>untry</u> : VIETNAM Marked on	package	e label as "	MADE IN VIETNAM"	
	Me	<u>echanical ch</u>	<u>aracteristics</u>				
		Item	Condit	ions		Specificati	ons
	1	Rotation angle				360° (Endless)	
	2	Detent points				24 detent poin	ts
	3	Each detent angle				15.0° ±3.0°	
	4	Rotation torque (Detent torque)	Operating temperatu			12.0 mN·m±6.0 mN·m 40 mN·m max.	n — — —
				-40	°C ~ -20°C	50 mN∙m max.	
	5	Shaft pull-push strength	opplied to the shoft in t	Pull and push static lood of 100N shall be applied to the shaft in the axial direction for 10 second. (Mount the product to P.W.B.)			
	6	Shaft side-load strength	the point 5mm from the tip direction perpendicular to	a momentary load of 0.5 Nm shall be applied at he point 5mm from the tip of the shaft in a lirection perpendicular to the axis of shaft for 10 second. (Mount the product to P.W.B.)			or y in ristics
	7	Shaft wobble	the point 2mm from the tip direction perpendiculor to	momentary load of 50 mNm shall be applied at he point 2mm from the tip of the shaft in a lirection perpendicular to the axis of shaft. (Mount the product to P.W.B.)			
	8	Shaft play in rotational wobble	Measure with jig for ro	tational	ongle.	2° max.(Initia	1)
NA	ME						
		11mm GS	LNCODER	ISSUE	F	REVISIONS	DATE
ΤY	PEI	ND. EVEWRHJR012	28	DRAWING	з ND. RV-H-1719		2/7

 \triangleleft

Ο

Γ

Ο

Electrical	characteristics((encoder)

	Item	Conditions	Specifications			
1	Dutput signal (Dutput of phase difference Fig-1)		A,B 2 signals.			
2	Output resolution	Number of pulses in 360° rotation.	12 Pulse / 360°			
3	Contact resistance	Measurement shall be stable condition which a output signal is ON condition.	la max.			
4	Bouncing	Measurement circuit diagram.(Fig-2) At rotational speed 60 min ⁻¹ <phase (fig-3)="" t1.t3=""> (Passing time between 3.5V and 1.5V)</phase>	t1,t3: 5 ms mox.			
5	Sliding noise phose t2	Take sliding noise as time in the code-on area between bouncing(t1,t3) and voltage change exceed 1.5V.(Fig-3) Rotate shaft at speed 60±3 min ⁻¹ and measure.	3 ms max.			
6	Phase-difference	Measurement shall be made under the condition which the shaft is rotated at 60 min ⁻¹ .	T1, T2, T3, T4 (Fig-1) 4 ms min.			
7	Insulation resistance	Measurement shall be made under the condition which a voltage of 250V D.C. is applied between individual terminals and a shaft.	50MΩ min.			
8	Withstand voltage	A voltage of 300V A.C. shall be applied for 1min. between individual terminals and a shaft.	Without arcing or breakdown.			

<u>Switch characteristics(switch)</u>

	Item	Condit	ions		Specificati	ons
1	Switch type				Push type S.P.S.T.	
2	Contact resistance	Measurement the contact re COM and SW when push SW is Applying force: 8.5N		between	100mΩ max.	
З	Switch operation force		Measure the max.load until switch turned on when pressing the center of shaft to the operation direction of push SW.			N
4	Push stroke		leasure the distance until switch turned on when pressing the center of shaft to the operation lirection of push SW.		0.4 mm +0.5 mm (At push force 8.5N)	
		direction of push SW.			0.3 mm +0.25 mm -0.15 mm (Travel to DN)	
5	Bouncing	At operation speed 3~4 t <phase (fig-5<="" t4.t5="" td=""><td colspan="3">Measurement circuit diagram.(Fig-4) At operation speed 3~4 times/s <phase (fig-5)="" t4.t5=""> (Passing time between 1.5V and 3.5V)</phase></td><td>¢.</td></phase>	Measurement circuit diagram.(Fig-4) At operation speed 3~4 times/s <phase (fig-5)="" t4.t5=""> (Passing time between 1.5V and 3.5V)</phase>			¢.
6	Insulation resistance	which a voltage of 250V D.	Measurement shall be made under the condition which a voltage of 250V D.C. is applied between individual terminals and a shaft.		50Mα min.	
7	Withstand voltage	A voltage of 300V A.C. shall be applied for 1min. between individual terminals and a shaft.		Without arcing breakdown.	or	
						····
AME	11mm GS	ENCODER	ISSUE			

NAME 11mm GS ENCODER ISSUE REVISIONS DATE
TYPE NO.
EVEWRHJR012B
DRAWING NO.
RV-H-1719
3/7

 \triangleleft

Ο

Ο



Ο

 \triangleleft

О

Panasonic Corporation

-	Du	urability		······································			
		Item	Conditio	ns	Specification	S	
	1	Rotation life (Encoder)	The shaft of encoder sha 200,000cycles at a speed cycles/h in room temp(5°C without electrical load of measurements shall be mad	of 600 to 1000 C to 35°C) after which	Rotation torque: Initial torque Phase-difference: 2.5 ms min. Contact resistance: 100 n m Electrical characteristics item: 4 The same as the initial specifica	ox. 1.5.7.8	
	2	Push operating life (Switch)	The shaft of encoder shall be pushed to 200,000 times at a speed of 2500 times/h in room temp(5°C to 35°C) without		Operation force: Initial operation for Contact resistance: 200 mp m Switch characteristics item: 4,5,6	nax. .7	
	3 Heat temperature The encoder shall be stored at a temperature of 85±3°C for 240±10h in a thermostatic chamber. And then the encoder shall be sub- jected to standard atmospheric conditions for 1.5h after which measurements shall be made. (Without electrical load) Contact resistance: 100 p. max.						
	4	Humidity	The encoder shall be stored of 60±3°C with relative humi 95% for 240±10h in a thermos And then the encoder shall b standard atmospheric conditi after which measurements sha (Without electrical load)	dity of 90% to static chamber. be subjected to ons for 1.5h	SW Contact resistance: 200 m Mechanical characteristics item: 4 Electrical characteristics item: 4 Switch characteristics item: 3,4,5	n mox. .5.6.7.8 .6.7	
	5	Low temperature	The encoder shall be stored of -40±3°C for 240±10h in a chamber. And then the encod jected to standard atmospher 1.5h after which measurement (Without electrical load)	thermostatic er shall be sub- ic conditions for	- The same as the initial specifica	tions.	
	(1) (2) (3) (4) Mc	Package size : L=	tic tray.(100pcs./tray	()	Polyethylene sheet Packing ca absorption t T W Iray (Empty tray of		
-	1.T e	quipment conditions bu	m specify this item only. P		ur approval test in the actual precautions.		
NAM	E	11mm GS	ENCODER	ISSUE	REVISIONS	DATE	
TYP	ΕN	EVEWRHJR012	2B	DRAWING ND. RV-H-		5/7	

Ο

 \triangleleft

Ο

Panasonic Corporation

⚠ Application Notes :

 \bigcirc

<

 \bigcirc

1. Prohibited items on fire and smoking Absolutely avoid use of a product beyond its rated range because doing so may cause a fire. If misuse or abnormal use may result under conditions in which the product is used out of its rated range take proper measures such as current interruption using a protective circuit. The grade of nonflammability for resin used in product is "94HB,"which is based on UL94 Standards (flammability test for plastic materials). Prohibit use in a location where a spreading fire may be generated or prepare against a spreading fire. 2. For use in equipment for which softy is requested Although care is taken to ensure product quality, inferior Characteristics, short circuits, and open circuits are some problems that might be generated. To design a equipment which places maximum emphasis on safety, review the affect of any single fault of a product in advance and perform virtually foil-sofe design to ensure maximum safety by: -.Preparing a protective circuit or a protective device to improve system safety, and set -. Preparing a redundant circuit to improve system safety so that the single fault of a product does not cause a dangerous situation. 3.Reliability Storage condition Do not store the product under high temperatures and/or high humidity, or in a location where corrosive gas may be generated. Store the product at room temperature and room humidity in a packed condition. Use them within a maximaum of 6 months. Check the date of manufacture on the package box and apply the "first-in-first-out" rule. If unpacked product must be stored as inventory. Store them in polyethylene bag to keep out oir. The encoder's pulse count method should be designed with taking operating speed, sampling time, and the design of the microcomputer software, etc. into consideration. The item designed mainly corresponds to JIS(Japanese Industrial Standards) on the reliability conditions. 4. This product dose not yet conform to Hologen Free regulation generally required. Information of Chemical Substances and Environmental Hazardous Substances. This product has not been manufactured with ozone depleting chemical controlled under the Montreal Protocol. This product complies with the RoHS Directive Restriction of the use of certain Hazardous Substance in electrical and electronic equipment DIRECTIV2011/65/EU). All the materials used in the part are registered material under the Law Concerning the Examination and Regulation of Manufacture etc. or Chemical Substances. s S O Soldering conditions : Perform the soldering under the conditions shown bellow. Soldering conditions (1) Specific gravity of flux ----- 0.83 ± 0.05 Flux foaming time ----- Within 5 s P.W.B Flux foaming level ----- 1/2t or less Preheating temperature ----- 100 °C mox.(Ambient temp.) Preheating time ----- 70s max. Soldering should be performed at260 °C or less within 3 s by twice maximum. Material ----- t=1.6 mm Conditions of P.W.B Thickness Double side copper clad phenolic resin Laminates. Soldering conditions (2) <Soldering iron> Soldering iron : 20W or lower. Temperature at the iron tip : 350°C or lower. The duration to apply the soldering iron : 3 seconds or lower. (1 time) PWB design - When you design mounting hole of PWB, please refer to its dimension defined in this specification. Particularly, care should be taken in the case of wiring such as jumper wire near the product body where flux is delating. If flux is spattered to the product body, it may cause electrical contact or sliding trouble. NAME 11mm GS ENCODER ISSUE DATE REVISIONS TYPE NO. DRAWING NO. EVEWRHJR012B RV-H- 1719 6/7

Panasonic Corporation

ISSUE	REVISIONS			DATE	DESIGN	CHECK	APPROV/
	New drawing.						
					*	~	r
	······						
\ME	11mm GS ENCODER						
YPE NO.	EVEWRHJR012B	ISSUE DRAWING	G NO. RV-H- 1		VISIONS		DAT

Γ

Ο

 \triangleleft

Ο