
MICRO PUSH WIRE® connector for junction boxes; for solid conductors; 0.8 mm Ø; 4-conductor; dark gray housing; light gray cover; Surrounding air temperature: max 60°C; 0,80 mm²; dark gray



www.wago.com/243-204





Data Electrical data

Ratings per IEC/EN

Ratings per	EN 60664
Nominal voltage (II/2)	100 V
Rated surge voltage (II/2)	1.5 kV
Rated current	6 A
Legend (ratings)	(II / 2) ≙ Overvoltage category II / Pollution degree 2

Connection data

Connection points	4
Total number of potentials	1
Number of connection types	1
Number of levels	1

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG Hansastr. 27

32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204



Connection 1

Connection technology	PUSH WIRE®
Actuation type	Push-in
Connectable conductor materials	Copper
Solid conductor	22 20 AWG
Conductor diameter	0.6 0.8 mm / 22 20 AWG
Conductor diameter (note)	When using conductors of the same diameter, 0.5 mm (24 AWG) or 1 mm (18 AWG) diameters are also possible.
Strip length	5 6 mm / 0.2 0.24 inches
Wiring direction	Side-entry wiring

Physical data

Width	10 mm / 0.394 inches
Height	6.8 mm / 0.268 inches
Depth	10 mm / 0.394 inches

Material Data

Note (material data)

Intormation (an matarial	specifications ca	n ha taund hara
II II OI I II auoi i	JII IIIatellai	SDECITICATIONS CA	ii be ibuliu liele

Color	dark gray
Cover color	light gray
Fire load	0.011 MJ
Weight	0.8 g

Environmental requirements

Ambient temperature (operation)	+60 °C
Continuous operating temperature	105 °C

Commercial data

eCl@ss 10.0	27-14-11-04
eCl@ss 9.0	27-14-11-04
ETIM 8.0	EC000446
ETIM 7.0	EC000446
PU (SPU)	1000 (100) pcs
Packaging type	box

 $\label{thm:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204



origin	DE	
	4044918440585	
ariff number	85369010000	
ental Product Compliance		
pliance Status	Compliant,No Exemption	
/ Certificates		
rovals		
		Certificate
Approval	Additional Approval Text	name
CCA	EN 60998	NTR NL
DEKRA Certification B.V.		7812
CSA	C22.2	70048857
DEKRA Certification B.V.		
KEMA/KEUR	EN 60998	71-
DEKRA Certification B.V.		112493
UR	UL 1059	E45172
Underwriters Laboratories Inc.		
s of conformity and manufacturer's declarations		
		Certificate
Approval	Additional Approval Text	name
EU-Declaration of Conformity	-	-
WAGO GmbH & Co. KG		
UK-Declaration of Conformity	-	-
WAGO GmbH & Co. KG		
	ental Product Compliance epliance Status / Certificates rovals Approval CCA DEKRA Certification B.V. KEMA/KEUR DEKRA Certification B.V. UR Underwriters Laboratories Inc. s of conformity and manufacturer's declarations Approval EU-Declaration of Conformity WAGO GmbH & Co. KG	ariff number 85369010000 antal Product Compliance pliance Status Compliant.No Exemption / Certificates rovals Approval Additional Approval Text CCA EN 60998 CSA DEKRA Certification B.V. CSA DEKRA Certification B.V. KEMA/KEUR EN 60998 UR Underwriters Laboratories Inc. UR Underwriters Laboratories Inc. Additional Approval Text EU-Declaration of Conformity WAGO GmbH & Co. KG

Approvals for marine applications

Certificate

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204



Logo Approval Additional Approval Text name

ABS - 18HG1755093PDA

LR Lloyds Register

EN 60998

LR22207029TA

Optional accessories

Mounting adapter

Mounting accessories



Item no.: 243-112

Mounting carrier; for 4 connectors; 243 Series; for DIN-35 rail mounting/screw mounting; orange

www.wago.com/243-112



Item no.: 243-113

Mounting carrier; for 6 connectors; 243 Series; for DIN-35 rail mounting/screw mounting; orange

www.wago.com/243-113

Downloads Documentation

Bid Text

243-204 X81 - Datei	2019 Feb 19	xml 3.3 kB	Download
243-204 doc - Datei	2017 May 17	doc 25.6 kB	Download
ausschreiben.de 243-204		URL	Download

CAD/CAE-Data

CAD data

2D/3D Models 243-204 URL Download

CAE data

EPLAN Data Portal 243-204 URL Download

Subject to changes. Please also observe the further product documentation!

WAGO GmbH & Co. KG

Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products?

We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204



WSCAD Universe 243-204	URL	Download
ZUKEN Portal 243-204	URL	Download

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 243-204


Download

URL


MICRO PUSH WIRE® connector for junction boxes; for solid conductors; 0.8 mm Ø; 4-conductor; dark gray housing; light gray cover; Surrounding air temperature: max 60° C; 0,80 mm²; dark gray

Installation Notes

Conductor termination



Strip solid conductors to $5 \dots 6$ mm (0.19 ... 0.23 inch).



Termination: Insert the stripped solid conductor until it hits the backstop.


 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204





Removal: Hold conductor to be removed and twist alternately left and right while pulling the connector.

Installation



Connector strips:

Assembling modular connectors into connector strips.

Commoning


 $\label{lem:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$

WAGO GmbH & Co. KG Hansastr. 27 32423 Minden

Phone: +49571 887-0 | Fax: +49571 887-169 Email: info.de@wago.com | Web: www.wago.com Do you have any questions about our products? We are always happy to take your call at +49 (571) 887-44222.

www.wago.com/243-204





Commoned connector strips

Testing




Testing via test port opposite to conductor entry.

 $\label{thm:condition} \textbf{Subject to changes. Please also observe the further product documentation!}$

www.wago.com/243-204





The 243 Series can be used in both communication and alarm systems according to the VdS (German Association of Property Insurers) guidelines.

No general approval is given to PUSH WIRE® connectors by the VdS association. The connectors must be tested together with the different parts of the system.

The requirements for connectors are specified in the VdS guidelines for junction boxes (VdS 2116) in section 8.7: "The junction box connectors must be designed to guarantee a reliable and stable connection."

The verification of the fulfillment of these requirements is documented in the VDE test report No. 2574-1440-4031 for the insulated 243 Series PUSH WIRE® Connectors.

 $\label{thm:continuity} \textbf{Subject to changes. Please also observe the further product documentation!}$