

### AS1355 300mA, Triple LDO

## 1 General Description

The AS1355 is a high-performance triple CMOS low-dropout voltage regulator in a single QFN package. The efficient set of programmable power supplies is optimized to deliver the best compromise between quiescent current and regulator performance for mobile phones, PDAs, MP3 players, and other battery powered devices.

Stability is guaranteed with ceramic output capacitors of only 1µF ( $\pm 20\% - X5R$ ) up to 4.7µF ( $\pm 20\% - X5R$ ). The low equivalent series resistance (ESR) of these capacitors ensures low output impedance at high frequencies.

Regulation performance is excellent even under low dropout conditions, when the power transistor has to operate in linear mode.

The low-noise performance allows direct connection of noise sensitive circuits without additional filtering networks.

The AS1355 is available in a 16-pin QFN 3x3 package.

### 2 Key Features

- 3 Independent Voltage Regulators with Shutdown
- Output Current: 300mA each LDO
- Programmable Output Voltage Range: 1.25V to 3.6V in 50mV Steps

- Accuracy: ±1.0%
- PSRR: 70dB at 1kHz, 60dB at 100kHz
- Load Regulation: 3mV (0 to 300mA)
- Supply Range: 2.3V to 5.5V
- 0.1V Dropout Voltage @ Iload = 200mA
- Shutdown Current: 1µA
- Supply Current Without Load: 160µA
- Softstart for Low Inrush Current
- Stable with low ESR Ceramic Capacitors from 1µF to 4.7µF
- Low Noise: 40µV rms @10Hz to 100kHz Bandwidth
- Thermal Protection
- Over-Current Protection
- Temperature Range: -40°C to +85°C
- Packages:
- 16-pin QFN 3x3
- 16-pin TQFN 3x3

### 3 Applications

The AS1355 is ideal for cordless and mobile phones, MP3 players, CD and DVD players, PDAs, hand-held computers, digital cameras, and any other hand-held battery-powered device.



Figure 1. AS1355 - Typical Application Diagram

Datasheet - Pin Assignments

					٠	٠	٠
	÷	é	ō ē	ō	÷	õ	ó
	٠				٠		٠
			٠			٠	٠
	٠		٠		٠	٠	٠
			•		٠	٠	٠
000					٠		
	٠	٠	•		٠	٠	٠
00000		٠	•		٠	٠	٠
00000	÷	ø	•		٠	ė	٠
	ē	ē			÷	ē	é

## 4 Pin Assignments

Figure 2. Pin Assignments (Top View)



#### 4.1 Pin Descriptions

#### Table 1. Pin Descriptions

Pin Number	Pin Name	Description				
1	EN1	Active-High Enable Input 1. Pull this pin to GND to disable the regulated output voltage Vout1.				
2	VDDA	Analog Power Supply Voltage				
3	VDD1	Unregulated Input Voltage 1				
4	VDD2	Unregulated Input Voltage 2				
5	VOUT1	Regulated Output Voltage 1				
6	VOUT2	Regulated Output Voltage 2				
7	VOUT3	Regulated Output Voltage 3				
8	NC	Not Connected				
9	VDD3	Unregulated Input Voltage 3				
10	NC	Not Connected				
11, 12	GND	Ground. Note: All GND pins must be connected together externally.				
13	REF	Reference Voltage. Note: Connect to a 100nF capacitor during normal operation.				
14	NC	Not Connected				
15	EN3	Active-High Enable Input 3. Pull this pin to GND to disable the regulated output voltage Vouts.				
16	EN2	Active-High Enable Input 2. Pull this pin to GND to disable the regulated output voltage Vout2.				
17	NC	Exposed Pad. This pad is not connected internally, it can be connected to GND.				



## 5 Absolute Maximum Ratings

Stresses beyond those listed in Table 2 may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Tahle 2	Absolute Maximum Ratings
Table Z.	Absolute Maximum Ratings

Parameter	Min	Max	Units	Comments
Electrical Parameters				
VDDx, ENx to GND	-0.3	7	V	
VOUTx to GND	-0.3	5	V	
All other pins to GND	-0.3	VDD + 0.3	V	
Electrostatic Discharge				
Electrostatic Discharge HBM		2	kV	Norm: MIL 883 E method 3015
Temperature Ranges and Storage Conditions				
Thermal Resistance OJA		33	°C/W	on PCB
Junction Temperature		+125	°C	
Storage Temperature Range	-55	+125	°C	
Package Body Temperature		+260	٥C	The reflow peak soldering temperature (body temperature) specified is in accordance with <i>IPC/</i> <i>JEDEC J-STD-020"Moisture/Reflow Sensitivity</i> <i>Classification for Non-Hermetic Solid State Surface</i> <i>Mount Devices"</i> .
Humidity non-condensing	5	85	%	
Moisture Sensitive Level		3		Represents a max. floor life time of 168h



# 6 Electrical Characteristics

VDD = 4V, COUT =  $1\mu F$ , typical values are for TAMB =  $25 \degree C$  (unless otherwise specified);

Table 3. Electrical Characteristics

Symbol	Parameter	Conditions	Min	Тур	Мах	Unit	
Тамв	Operating Temperature Range		-40		85	°C	
Vdd	Supply Voltage Range		2.3		5.5	V	
Vout	Output Voltage Range		1.25		3.6	V	
Ron	On Resistance			0.5		Ω	
	Power Supply	f = 1kHz, CREF = 100nF		70		٩D	
PSRR <sup>1</sup>	Rejection Ratio	f = 100kHz, CREF = 100nF		60		dB	
loff	Shut Down Current	ENx = Low, TAMB = +25°C			1	μA	
Ivdd	Supply Current	Without Load		160	240	μA	
tset <sup>1</sup>	Output Voltage Settling Time	ILOAD Switched from 0 to 100mA			50	μs	
		CREF = 100nF Pre-charged			300	μs	
tstart <sup>1</sup>	Start-up Time <sup>2</sup>	CREF = 0nF Uncharged		200		μs	
		CREF = 100nF Uncharged		15		ms	
	Output Voltage Tolerance	Iload = 0mA, Tamb = 25°C	-1		1	%	
Vout		Iload = 0mA	-2		2	%	
VLINEREG	Line Regulation, Static	VOUT(NOM)+0.3V to 5.4V	-1		1	%	
14	Load Regulation, Static	ILOAD = 0 to 50 mA		0.5	2.5	mV	
Vloadreg <sup>1</sup>		ILOAD = 0 to 300 mA		3	10	mV	
Vін	Enable Input Voltage High		1.5			V	
VIL	Enable Input Voltage Low				0.4	V	
Iload	Output Current		0		300	mA	
Ilimit	Output Current Limitation			450		mA	
VNoise	Output Noise Voltage	10Hz to 100kHz, CREF = 100nF		40		µVrms	
	Thermal Protection			150		°C	

1. Guaranteed by design and verified by lab evaluation.

2. Startup is performed if any EN pin goes high.

**Note:** All limits are guaranteed. The parameters with min and max values are guaranteed with production tests or SQC (Statistical Quality Control) methods.

Datasheet - Typical Operating Characteristics



## 7 Typical Operating Characteristics

VDD = 4V, VOUT = 3.3V, COUT =  $1\mu F$ , TAMB = +25°C (unless otherwise specified);



Datasheet - Typical Operating Characteristics



2V/Div

1V/Div

#### Figure 9. Startup; no Load, CREF = 100nF





Figure 11. Startup; no Load, CREF = 100nF (pre-charged)



Figure 12. Startup; RLOAD =  $11\Omega$ , CREF = 100nF (pre-charged)



Figure 13. Load Transient Response; 300mA







IOUT = 300 to



***		
000		
		000
0000	0000	000

### 8 Detailed Description

Figure 15. AS1355 - Block Diagram



0000	
0000	

# 9 Typical Application

Figure 16. Typical Application



Datasheet - Package Drawings and Markings

0000	

## 10 Package Drawings and Markings



#### NOTE:

NX L

1. DIMENSIONS & TOLERANCEING CONFIRM TO ASME Y14.5M-1994.

-NX b + bbb() CAB

- 2. ALL DIMENSIONS ARE IN MILLIMETERS. ANGELS ARE IN DEGREES.
- 3. DIMENSION & APPLIES TO METALLIZED TERMINAL AND IS MEASURED BETWEEN 0.25mm AND 0.30mm FROM TERMINAL TIP. DIMENSION L1 REPRESENTS TERMINAL FULL BACK FROM PACKAGE EDGE UP TO 0.15mm IS ACCEPTABLE.
- A COPLANARITY APPLIES TO THE EXPOSED HEAT SLUG AS WELL AS THE TERMINAL.
- 5. RADIUS ON TERMINAL IS OPTIONAL.
- 6. N IS THE TOTAL NUMBER OF TERMINALS.

#### Marking: YYWWIZZ.

YY WW		Х	22	
last two digits of the current year	manufacturing week	plant identifier	free choice / traceability code	



0.08

0.10

16

\_

ddd

eee

fff

Ν

Datasheet - Package Drawings and Markings



#### Figure 18. 16-pin TQFN 3x3 Package







REF.	MIN	NOM	MAX			
A	0.70	0.75	0.80			
A1	0	0.02	0.05			
A3		0.20 REF				
L	0.30	0.40	0.50			
b	0.18	0.25	0.30			
D	3.00 BSC					
E	3.00 BSC					
е	0.50 BSC					
D2	1.30	1.45	1.55			
E2	1.30	1.45	1.55 1.55			
aaa	_	0.15				
bbb	-	0.10				
CCC	_	0.10				
ddd	_	0.05	-			
eee	_	0.08	-			
ffſ	_	0.10	-			
N		16				

#### NOTE:

- 1. DIMENSIONS & TOLERANCEING CONFIRM TO ASME Y14.5M-1994.
- 2. ALL DIMENSIONS ARE IN MILLIMETERS. ANGELS ARE IN DEGREES.
- COPLANARITY APPLIES TO THE EXPOSED HEAT SLUG AS WELL AS THE TERMINAL.
- 5. RADIUS ON TERMINAL IS OPTIONAL.
- 6. N IS THE TOTAL NUMBER OF TERMINALS.



## **11 Ordering Information**

The devices are available as the standard products shown in Table 4.

#### Table 4. Ordering Information

Ordering Code	Marking	Output	Description	Delivery Form	Package
AS1355-BQFT-WGD		Vout1 = 3.3V			
	ASSG	Vout2 = 1.8V		Tape and Reel	16-pin QFN 3x3
		Vout3 = 1.5V			
		Vout1 = 3.3V			
AS1355-BQFT-WWW	ASSV	Vout2 = 3.3V	300mA, Triple LDO	Tape and Reel	16-pin QFN 3x3
		Vout3 = 3.3V			
		VOUT1 = 3.3V			
AS1355-BQFT-WWD2	ASTD	Vout2 = 3.3V	300mA, Triple LDO	Tape and Reel	16-pin TQFN 3x3
		Vout3 = 1.5V			
AS1355-BQFT-xyz*		Vout1*			
		Vout2*	300mA, Triple LDO	Tape and Reel	16-pin QFN 3x3
		Vout3*			

\* These devices are available in factory-set output voltages from 1.25V to 3.6V in 100mV increments. Choose the desired VOUT suffix from Table 5 and insert it instead of "xyz" in the part number.

On request also non-standard devices with output voltages between 1.25V and 3.6V in 50mV steps are available.

Table 5. Output Voltage Suffix Guide

Suffix	Min	Тур	Max	Suffix	Min	Тур	Max	Suffix	Min	Тур	Max
А		1.25		J		2.1		S		3.0	
В		1.3		K		2.2		Т		3.1	
С		1.4		L		2.3		V		3.2	
D		1.5		Μ		2.4		W		3.3	
E		1.6		Ν		2.5		Х		3.4	
F		1.7		0		2.6		Y		3.5	
G		1.8		Р		2.7		Z		3.6	
Н		1.9		Q		2.8		2		thin QFN	
I		2.0		R		2.9					

Note: All products are RoHS compliant and ams green. Buy our products or get free samples online at www.ams.com/ICdirect

Technical Support is available at www.ams.com/Technical-Support

For further information and requests, email us at sales@ams.com (or) find your local distributor at www.ams.com/distributor



### Copyrights

Copyright © 1997-2013, ams AG, Tobelbaderstrasse 30, 8141 Unterpremstaetten, Austria-Europe. Trademarks Registered ®. All rights reserved. The material herein may not be reproduced, adapted, merged, translated, stored, or used without the prior written consent of the copyright owner.

All products and companies mentioned are trademarks or registered trademarks of their respective companies.

#### Disclaimer

Devices sold by ams AG are covered by the warranty and patent indemnification provisions appearing in its Term of Sale. ams AG makes no warranty, express, statutory, implied, or by description regarding the information set forth herein or regarding the freedom of the described devices from patent infringement. ams AG reserves the right to change specifications and prices at any time and without notice. Therefore, prior to designing this product into a system, it is necessary to check with ams AG for current information. This product is intended for use in normal commercial applications. Applications requiring extended temperature range, unusual environmental requirements, or high reliability applications, such as military, medical life-support or life-sustaining equipment are specifically not recommended without additional processing by ams AG for each application. For shipments of less than 100 parts the manufacturing flow might show deviations from the standard production flow, such as test flow or test location.

The information furnished here by ams AG is believed to be correct and accurate. However, ams AG shall not be liable to recipient or any third party for any damages, including but not limited to personal injury, property damage, loss of profits, loss of use, interruption of business or indirect, special, incidental or consequential damages, of any kind, in connection with or arising out of the furnishing, performance or use of the technical data herein. No obligation or liability to recipient or any third party shall arise or flow out of ams AG rendering of technical or other services.



#### **Contact Information**

Headquarters ams AG

Tobelbaderstrasse 30 A-8141 Unterpremstaetten, Austria

Tel : +43 (0) 3136 500 0 Fax : +43 (0) 3136 525 01

For Sales Offices, Distributors and Representatives, please visit: http://www.ams.com/contact