



Document status: Preliminary



iMX7 Dual uCOM Board Feature Highlights

- NXP i.MX 7Dual, dual-core ARM Cortex-A7 and Cortex-M4, 1GHz/200MHz
- High performance 2x1800+250 DMIPS
- 1 GByte LPDDR3 1066 MT/s, 32-bit databus
- 8 GByte eMMC on-board Flash
- 24-bit parallel RGB and MIPI-DSI graphical output
- PCIe, USB, CAN and many more interfaces
- ROHM PMIC BD71815GW with on-chip battery charger
- Low-power consumption very power efficient
- Linux and Android BSP
- 27 x 37 mm ultra small form factor
- Long term availability

Introduction

GOLD PARTNER

NP

The **iMX7 Dual uCOM Board** provides a quick and easy solution for implementing a high-performance ARM dual-core Cortex-A7 / Cortex-M4 based design. The Cortex-A7 / Cortex-M4 heterogeneous architecture enables the system to run an OS like Linux on the dual-core Cortex-A7 and a Real-Time OS (RTOS) on the Cortex-M4.

ERTIFIA

ISO 140

The i.MX 7Dual supports 2D graphical acceleration and has dual display outputs (RGB and MIPI-DSI).

The design has a **low-power implementation** with LPDDR3 memories and a PMIC supporting DVFS techniques and integrated battery charger, making the board ideal for portable applications. Other typical applications are graphical interface solutions, communication solutions and connected real-time systems.

Specification

Processor	Cores	NXP i.MX 7Dual dual-core ARM Cortex-A7 and Cortex-M4				
	Frequency	1 GHz on Cortex-A7				
		200 MHz on Cortex-M4				
Memory	SDRAM	1 GByte LPDDR3 1066 MT/s, 32-bit databus				
	NAND FLASH	8 GByte eMMC NAND Flash for OS and bootloader				
Graphics	Parallel RGB	24-bit, up to 1920 x 1080 pixels at 60 Hz				
output	MIPI-DSI	2 lanes, maximum bit rate of 1.5 Gbps				
	Graphics Engine	PXP - PiXel processing pipeline for imagine resize, rotation, overlay and color space conversion.				
Graphics	CMOS sensor interface	Parallel, up to 24 bit				
input	(camera)	Serial, MIPI-CSI2, 2 lanes, maximum bit rate of 1.5 Gbps				
Ethernet		Two 10/100/1000 Mbps Gigabit Ethernet interfaces (requires off-board Ethernet-PHY)				
I/O	PCle	1x PCle 2.1, 1x lane				
(all functions	USB	2x USB2.0 OTG, 1x HSIC				
are not	UART, SPI, I2C, Audio	7x UART, 4x SPI, 4x I2C, 3x I2S/SSI				
available at	CAN	2x CAN bus 2.0B				
the same	GPIO	Large number of GPIOs and keypad pins available				
time)	Memory card	2x SD3.0/MMC5.0				
	ADC	4ch 12-bit resolution				
Other	Boot parameters	E2PROM storing board information including Ethernet MAC address and memory bus setup params.				
	Watchdog	On-board watchdog functionality				
	RTC	ROHM BD71815GW integrated low-power RTC				
	Power Management (PMIC)	ROHM BD71815GW supporting DVFS techniques for low power modes				
	Battery Charger	ROHM BD71815GW with Coulomb counter for battery fuel gauging. Up to 28V input voltage				
	White LED Driver	25mA, up to 26V				



© Copyright 2020 Embedded Artists AB. All rights reserved. All other products or service names mentioned herein are trademarks of their respective holders and should be treated as such.

Privacy policy: https://www.embeddedartists.com/privacy-policy. Legal: https://www.embeddedartists.com/terms-and-conditions/



The Art of Embedded Systems Development – made Easy™

Document status: Preliminary

Power	Supply voltage	+3.3V			
	Power consumption	TBD			
Environment	0 - 70° or -20 - 85° Celsius				
	Operating Humidity	5 - 90% relative humidity, non-condensing			
Mechanical	Dimensions (W x H x D)	27 x 37 x 4 mm			
Connectors		70 pos DF40C-70DP-0.4V connector with 0.4mm pitch			
		Dual 100 pos DF40C-100DP-0.4V connector with 0.4mm pitch			

Block Diagram



Ordering Information

Part No. ^[1]	CPU	SDRAM	eMMC	I/O	Supply	Operating
				Voltage ^[2]	Voltage	Temperature
EAC00266	MCIMX7D7DVK10SC	1 GByte LPDDR3	8 GByte	3.3V	3.3V	0 - 70° C
EAC00267	MCIMX7D5EVK10SC	1 GByte LPDDR3	8 GByte	3.3V	3.3V	-20 - 85° C
	Note, no EPDC peripheral					

^[1] Standard configurations listed. Others on request.

^[2] 1.8V I/O voltage on request.

Support Highlights

Embedded Artists is a reliable and competent partner

- we help you become successful!

- Professional and responsive support
- Pre-designed standard Carrier boards for integration
- Custom Carrier board design
- Customization
 - Different pinning, supply voltage, memory sizes, etc
 - Single Board Computer (SBC) solutions
- Display solutions
- Mechanical solutions
- Schematic review of customer carrier board designs
- Driver and application development

Development Kit

The iMX7 Dual uCOM Board is supported by the *iMX7 Dual uCOM Developer's Kit V2* that provides a quick path to get started with development and integration work.

The kit provides reference implementations of key interfaces. Ordering part No. **EAK00344**



Disclaimer: Embedded Artists reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice.



© Copyright 2020 Embedded Artists AB. All rights reserved. All other products or service names mentioned herein are trademarks of their respective holders and should be treated as such.

Privacy policy: https://www.embeddedartists.com/privacy-policy/ Legal: https://www.embeddedartists.com/terms-and-conditions/